




MOBILE·U

Live

USB2.0 High-Speed

4-In / 4-Out Recording USB Interface with Smart Device connecting I/O
(Digital & Analog) for live streaming applications





Important Safety Instructions

1. Read this manual thoroughly before using this unit.
2. Keep this manual for future reference.
3. Take notice of and comply with all warnings included in the user's manual or indicated on the appliance.
4. Follow all instructions included in this manual.
5. Do not expose this unit to rain or moisture. Avoid having water or other liquids spilled on this unit.
6. When cleaning the cabinet or other parts of this appliance, use only a dry or slightly damp soft cloth.
7. Do not block any ventilation openings or interfere with the proper ventilation of this unit. Install in accordance with the manufacturer's instructions.
8. Do not use or store near any heat sources such as radiators, heat registers, stoves, or other heat-producing appliances.
9. Do not interfere with the safety purpose of the polarized or grounding-type plug. A polarized plug has two blades with one wider than the other. A grounding-type plug has two blades and a third grounding prong. These are designated for your safety. If the provided plug does not fit into your outlet, consult an electrician.
10. Protect the power cord from being walked on or otherwise damaged by items placed on or against them. Particular attention should be given to the plugs, receptacles, and the point where the cord exits the appliance.
11. To avoid the risk of electrical shock, do not touch any exposed wiring while the unit is in operation.
12. Only use attachments/accessories specified by the manufacturer.
13. Unplug this unit and all connected electrical equipment during lightning storms or when left unused a long period of time.
14. Refer all servicing to qualified service personnel. Servicing is required when the appliance has been damaged in any way or fails to operate normally.

WARNING: To reduce the risk of fire or electric shock, do not expose this unit to rain or moisture

Contents

Introductions	4
What's in the package?	4
Register your ICON ProAudio product to your personal account	5
Features	6
Front Panel	7
Rear Panel.....	8
Mac driver installation.....	9
Mixer control panel(MAC).....	11
Windows driver installation	12
ProDriver4(Windows)	15
Mixer control panel(Windows)	16
Settings (Sample rate and latency settings).....	19
ProDriver4 hosting rack(Windows).....	23
Hardware Connections	24
Specifications	25
Services.....	26

Introductions

Thank you for purchasing the ICON ProAudio MobileU Live digital audio Interface. We sincerely trust this product will provide years of satisfactory service, but if anything is not to your complete satisfaction, we will endeavor to make things right.

In these pages, you'll find a detailed description of the features of the MobileU Live digital audio interface, as well as a guided tour through its front and rear panels, step-by-step instructions for their setup and use, and full specifications.

Please register the product on our website at the below link **[www. iconproaudio.com/registration](http://www.iconproaudio.com/registration)**:

Please follow the step by step procedures starting from input the device's serial number to your personal information etc. By registering your product online, you will entitle to several different services and after-sales supporting at our ACS help center by visting our website at **www.iconproaudio.com**. Also, all the registered products under your account will be listed on your personal product page where you could get update information such as firmware/driver upgrade, software bundle and user manual download etc for your device.

As with most electronic devices, we strongly recommend you retain the original packaging. In the unlikely event the product must be returned for servicing, the original packaging (or reasonable equivalent) is required.

With proper care and adequate air circulation, your MobileU Live digital audio interface will operate without any trouble for many years. We recommend that you record your serial number in the space provided below for future reference.

What's in the package?

- MobileU Live USB Recording Interface
- Quick Start Guide x 1
- USB 2.0 cable x 1
- 3.5mm TRS audio cable x 1

Register your ICON ProAudio product to your personal account

1. Check serial number of your device

Please go to [http:// iconproaudio.com/registration](http://iconproaudio.com/registration) or scan the QR code below.



Input your device's serial number and the other information on the screen. Click "Submit".

A message will pop up showing your device information such as model name and its serial number - Click "Register this device to my account" or if you see any other message, please contact our after-sales service team

2. Log in to your personal account page for existing user or sign up for new user

Existing user: Please log into your personal user page by inputing your user name and password.

New user: Please click "Sign Up" and fill in all the information.

3. Download all useful materials

All your registered devices under your account will show on the page. Each product will be listed along with all its available files such as drivers, firmware, user manual in different languages and bundled software etc. for download. Please make sure you have download the necessary files such as driver before you begin device installation.

Features



The ICON ProAudio Utack Liive USB recording interface provides an audio input and output module as well as analog & digital connectivity with any Smart mobile device for live streaming applications. Main features include:

- 24-Bit 192KHz 4-In/4-Out USB Recording Interface
- Professional & Hi-end grade DA/AD provides high dynamic range
 - DAC: Dynamic range - 114dB
 - ADC: Dynamic range - 114dB
- Supporting Mac/PC connectivity operating simultaneously with SmartDevice
- Live session possible with audio signal processing via ProDriver4 virtual plug-in rack
- 4x4 analog I/O full duplex recording and playback
- Smart device digital (type C) and analog (TRRS) connection jacks are both equipped
- Compatible with iOS and Android Digital I/O jack (Type C) & Analog I/O jack (3.5mm stereo TRRS) is equipped for direct connection with SmartPhone
- Mic/Instrument preamps with individual gain control and phantom power switch
- 2 analog outputs on 1/4" TRS jacks
- 1 x 1 – 16 channel MIDI I/O
- Master volume control knob on the front panel
- Direct monitor button control on the front panel
- 1 headphone output with assignable source and individual volume control
- Flexible channel routing via the ProDriver4 software control panel
- ICON ProAudio developed ultra low latency ProDriver4™ driver is provided
- ICON ProAudio innovative and user friendly plug-in hosting rack software is built-in with ProDriver4™ (Windows only)
- USB2.0 High Speed equipped and USB bus-powered
- Supports DirectSound, WDM and ASIO2.0
- Compatible with Mac OS (Intel-Mac) 10.11 and later, iOS 9 or above and Windows 7, 8 & 10 (32-bit/64-bit)
- Full duplex, simultaneous record/playback
- +5VDC power supply connector is equipped for external power supply when using with iOS
- Rugged aluminum construction

Front Panel



1. “Mic/Inst” Inputs 1/2

Unbalanced instrument and mic level inputs. These hybrid connectors will accept a standard 3-pin XLR plug or a 1/4” TS connector.

2. 48V phantom power switch

When this switch is in the IN position, +48V phantom power is supplied to the XLR input. This phantom power circuit is suitable for most condenser microphones.

3. Input gain level controls 1/2

This potentiometer controls the input level of its associated analog Mic/Instrument input.

4. Master level control

This potentiometer controls the master output level of the analog outputs.

5. Headphone level control

The potentiometer controls the output level of the headphone output.

6. Headphone output

This output jack accepts a standard 1/4” stereo TRS headphone connector.

7. Hardware / PC Monitoring Control (Direct Monitor)

Hardware direct monitoring (Clockwise - "Direct Out") eliminates the latency or delay inherent in even the best internal circuitry while listening to your input and existing tracks. You can also listen to your input complete with effects (Counter-Clockwise - "PC") while recording by using extremely the low-latency ASIO monitoring.

Rear Panel



1. Power supply connector

MobileU Live is USB-bus powered. If your computer does not supply sufficient power, connect an ICON 5VDC power supply adapter to this jack. Or you may try to use your smart phone power adapter with the correct cable type (Android). Normally it should work and provide enough power to the device.

(Note: You can get the power adapter from ICON distributors/dealers near you)

(Note: External power adapter is needed if the MobileU Live is used as a standalone unit without a Mac or PC)

2. Smart Device I/O (Digital - Type C & Analog - 3.5mm TRRS)

These ports allow you to connect your smart device and your Mac/PC simultaneously so you may process the audio signal with your Mac/PC before delivering signal to the smart device for live streaming application.

Digital - Type C jack for connecting directly to the digital jack of the smart device (OTG adapter required)

Analog - TRRS stereo jack for connecting directly to smart device's audio I/O

3. MIDI I/O connectors

MIDI input and output on standard 5-pin DIN connectors.

4. USB 2.0 connector

Connect it with the provided USB cable to your Mac/PC/iOS device camera kit's USB connector. Your Mac/PC must have a USB2.0 connector in order to run the full speed of MobileU Live.

5. Line outputs 1/2

These are balanced analog outputs on standard 1/4" TS connectors at +4dB line level. These outputs will support standard stereo, as well as 2 mono.

Mac driver installation

MobileU Live is a class compliance device. Thus there is no driver installation needed for Mac. Also, it is fully supporting iOS devices by connecting to a camera kit.

Please follow the step-by-step procedures below to install your MobileU Live USB recording interface.

1. Turn on your Mac

(Note: Do not connect the MobileU Live digital audio interface to your Mac yet.)

2. Class compliance device

MobileU Live is class compliance on Mac OSX, no driver installation is needed.

3. Copy the software control panel shortcut logo to your desktop

Open the previous “Mac” folder. Copy the “ProDriver4” software panel shortcut logo and paste it to your desktop.




Diagram 1

4. Launch the software control panel

Click the MobileU Live’s software control panel shortcut logo you have just copied to your desktop to launch the software control panel.



Diagram 2

5. Connect your MobileU Live digital audio interface

Now connect the MobileU Live digital audio interface to your Mac's USB port.

Note: MobileU Live audio interface only support USB2.0. Your Mac must have a USB2.0 port.



6. Audio MIDI setup

Open the “Audio MIDI setup” window and check if the MobileU Live device has setup properly as shown below in diagram 4.




Diagram 4

Mixer control panel(MAC)

The mixers work like a matrix mixer. Activate and adjust the corresponding input or output channel level. They are very useful and make your inputs and outputs very flexible. You may route any of your input(s) to any output(s).




Diagram 5

- 1. HW Input 1/2 level metering**
Showing the hardware 1/2 input level. (HW In 1/2).
- 2. HW Output 1/2 level metering**
Showing the hardware 1/2 output level.(HW Out 1/2).
- 3. S/PDIF In 3/4**
Showing the S/PDIF 3/4 input level (S/PDIF In 3/4).
- 4. S/PDIF Out 3/4**
Showing the S/PDIF 3/4 output level (S/PDIF Out 3/4).
- 5. Link switch**
Switch to adjust both channels level simultaneously.
- 6. Mute switch**
Switch to mute the corresponding channel.
- 7. “0dB” switch**
Switch to instantly adjust the corresponding channel to “0dB” level.
- 8. Gain control fader**
Slide to adjust the gain level for the corresponding channel.
- 9. Inputs & Outputs Matrix switches**
Switch to turn On/Off the corresponding input channel route to the corresponding output channel. The matrix is very useful and makes your inputs and outputs very flexible. You may route any of your input(s) to any output(s).

Windows driver installation

Please follow the step-by-step procedures below to install your MobileU Live USB recording interface and its driver.

1. Turn on your computer

Note: Do not connect the MobileU Live digital audio interface to your computer yet.

2. Download the Windows driver from your “Personal User Page at www.iconproaudio.com” (Please refer to Diagram 6 for instruction)

After you downloaded the driver file, please click it to start the installation process



MobileU Live

Serial Number: 00C90

Unregister this device

Latest driver for MacOS	V 1.1.0
Latest driver for Win32	V 1.1.0
Latest driver for Win64	V 1.1.0



Diagram 6

3. Installation Wizard appears

Choose "Next" when you see the Welcome Screen shown in Diagram 7.




Diagram 7

4. License Agreement

Click "I Agree" to proceed.




Diagram 8

5. Select components for installation

Check mark the components that you would like to install. We strongly recommend you to select all components.




Diagram 9

6. Preparing installation files

The installation process started, the process may take some time depending on your computer performance, please be patient and wait for the process to finish.




Diagram 10

7. Click “Install” to proceed.

Note: Same message will appear three times as there are three different drivers installation.



Diagram 11



Diagram 12



Diagram 13

8. Setup completed

A window as shown in Diagram 14 should appear. Choose "Finish".




Diagram 14

9. Launch the software control panel

You may click the ICON ProAudio logo on the system tray to launch the software control panel (Page 15).



Diagram 15

10. Connect your MobileU Live digital audio interface

Now connect the MobileU Live digital audio interface to your computer's USB port.



Diagram 16

ProDriver4(Windows)



Diagram 17



Diagram 18

Introducing ProDriver4, the leading edge in audio innovation for stage, studio and streaming from ICON ProAudio. The ProDriver audio system supplies you with the most reliable tools for almost any audio application, in the moment, right when you need it. The heart of the system, is our driver, employing breakthrough technology and zero latency monitoring. The user interface makes it easy to grab, route and redirect audio from any source in your computer with our virtual signal router. Use the ProDriver Plugin Host to connect your favorite VST, Audio Units and Direct X plugins. Run ProDriver4 in standalone mode or with your favorite DAW. Save your favorite plugin chains as presets and recall them during your session or live on stage in real time.

Mixer control panel(Windows)

There are two different audio drivers including “WDM” (Windows Driver Model) and “ASIO” (Audio Stream Input and Output) within the ICON ProAudio audio interface driver. WDM are widely used for daily software such as media player and ASIO is mainly being used for most of the recording software such as LogicPro. The advantage of ASIO is that it has much lower latency than WDM and this is very important when you are doing recording with load of plugins. Actually, most of the daily software does not support ASIO driver and using WDM only, in that case you just simply need to use the HW channel (Hardware channels). Below please find some explanations on the different terminology for each channel type.

1. HW IN (Hardware Channel IN)

This mean the hardware input channels including the microphones or internment input channels

2. HW Out (Hardware Channel OUT)

This mean the hardware output channels including the headphone or line out output channels

3. VC Out (Virtual Channel OUT)

This only exists on ASIO driver and it is a virtual channel that its output signal go to ASIO VC IN

4. VC Out (Virtual Channel IN)

This only exists on ASIO driver and it is a virtual channel that its input signal is coming from ASIO VC Out

5. LoopBack (LoopBack Channel)

ASIO internal loopback channel (e.g. ASIO VC Out signal go to ASIO VC IN)

On the mixer control panel, there are four different types of ASIO channels that you can manipulate.

1. MobileU Live Hardware channels (HW In 1/2 & HW Out 1/2)

These are the hardware input and output channels on MobileU Live .

2. MobileU Live Virtual channels (VC In 1/2, 3/4 and 5/6), (VC Out 1/2, 3/4 and 5/6)

These are the input and output virtual channels that related to the WDM.

For example: WDM Out 1/2 linked to VC In1/2

VC Out1/2 linked to WDM In1/2

3. MobileU Live Loopback channels (LB 1/2, 3/4 and 5/6)

These are the ASIO loop-back channels.




Diagram 19

By activating different cross points, you may route the corresponding signal to your desired channels.

1. **HW Input 1/2 level metering**
Showing the hardware 1/2 input level (HW In 1/2).
2. **HW Output 1/2 level metering**
Showing the hardware 1/2 output level (HW Out 1/2).
3. **VC In 1/2 (Virtual) input level metering**
Showing the WDM 1/2 output level (VC In 1/2).
4. **VC In 3/4 (Virtual) input level metering**
Showing the WDM 3/4 output level (VC In 3/4).
5. **VC Out 1/2 (Virtual) output level metering**
Showing the ASIO 1/2 VC output level (VC Out 1/2).
6. **VC Out 3/4 (Virtual) output level metering**
Showing the ASIO 3/4 VC output level (VC Out 3/4).
7. **VSC In 1/2 (Virtual) input level metering**
Showing the WDM 1/2 output level (VSC In 1/2).

8. VSC Music In 1/2 (Virtual) input level metering

Showing the WDM 1/2 output level (VSC music In 1/2).

9. VSC Out 1/2 (Virtual) output level metering

Showing the ASIO 1/2 VC output level (VSC Out 1/2).

10. VSC Music Out 1/2 (Virtual) output level metering

Showing the ASIO 1/2 VC output level (VSC music Out 1/2).

11. Loopback 1/2

Showing the ASIO loop-back 1/2 channel's level metering.

12. Loopback 3/4

Showing the ASIO loop-back 3/4 channel's level metering.

13. Loopback 5/6

Showing the ASIO loop-back 5/6 channel's level metering.

14. Link switch

Switch to adjust both channels level simultaneously.

15. Mute switch

Switch to mute the corresponding channel.

16. "0dB" switch

Switch to instantly adjust the corresponding channel to "0dB" level.

17. Gain control fader

Slide to adjust the gain level for the corresponding channel.

18. Inputs & Outputs Matrix switches

Switch to turn On/Off the corresponding input channel route to the corresponding output channel. The matrix is very useful and makes your inputs and outputs very flexible. You may route any of your input(s) to any output(s).

19. Mixer Presets

6 Mixer-Presets button slots are available for saving or loading your routing channel settings.

Settings (Sample rate and latency settings)

Click the “Setting” button to launch the settings window.




Diagram 20

Sample rate setting

Select your desired sampling rate from 44.1KHz to 192KHz on the pull down window shown in Diagram 21.




Diagram 21

Latency settings

There are six standard latency settings to select. If you would like to customize your own latency value, select custom.

- Safe (maximum latency)
- Extra Large
- Normal
- Small
- Very Small
- Minimum (minimum latency)
- Custom




Diagram 22

There are three different settings you can adjust to customize your own latency settings: These values include:

1. ASIO buffer Size

You may adjust the value ranging from 32/64/128/256/512/1024/2048 and 4096.




Diagram 23

2. Streaming buffer Size

Adjustable settings: Minimum/Low/Normal/High and Maximum.




Diagram 24

3. Streaming buffer volume

Adjustable values: 2/3 and 4.




Diagram 25




Diagram 26

(Note: If a warning message appears on the “Latency Status” windows, please adjust a larger latency setting.)

(Note: If a clicking sound occurs, you should change to a larger buffer size for the settings. If the largest buffer size has been selected and there is still a clicking sound. It means your computer performance is not able to handle the task. (It is not caused by MobileU Live digital audio interface.)

ProDriver4 hosting rack(Windows)



With the ProDriver4 Rack, you can use any of your plug-ins with your DAW. Or you may use your device as a standalone plug-ins effector without the need to run a DAW.

Hardware Connections

Connect the MobileU Live digital audio interface outputs to your amplifier, powered monitors or surround system. Two-channel stereo operation, the default outputs are channels 1 and 2.

If you are monitoring through headphones, connect your headphones to the device's headphone output.

Connect your microphones, instruments or other line level analog sources to the device's analog inputs.

Connect your MIDI device to the MIDI I/O.



PC/MAC Only



Smart Device Only



PC/MAC Smart Device Simultaneously



Different types of microphone connection method diagram



Note: For dynamic microphone user, please make sure +48V phantom power switch is "OFF" before you plug in your microphone, otherwise it may cause damage to your microphone.

Specifications

Mic/Inst Inputs 1/2 (Balanced; at Minimum Gain):

Frequency Response:	22Hz to 22kHz (+/-0.1dB)
Dynamic Range:	114dB, A-weighted
Signal-to-Noise Ratio:.....	-114dB, A-weighted
THD+N:	-100dB
Crosstalk:.....	-100dB @ 1kHz
Maximum Input level:.....	-3.8dBu, typical
Input Impedance:.....	Inst in: 500K Ohms, typical; Mic in: 1.8K Ohms, typical
Adjustable Gain:	>50dB
Total Gain Range:.....	+54dB

Line Outputs 1-2 (balanced):

Frequency Response:	22Hz to 22kHz (+/-0.1dB)
Dynamic Range:	114dB, A-weighted
Signal-to-Noise Ratio:.....	-114dB, A-weighted
THD+N:	-100dB
Crosstalk:.....	-100dB @ 1kHz
Nominal Output Level:	Balanced: +4dBu, typical;
Maximum Output Level:.....	+10.2dBu;
Output Impedance:	150 Ohm
Load Impedance:.....	600 Ohm minimum

Headphone Outputs: (at Maximum Volume; Into 100 Ohm load):

Frequency Response:	22Hz to 22kHz (+/-0.1dB)
Power into Ohms:	90 mW into 100 Ohms
THD+N:	<0.06% (-66dB)
Signal-to-Noise Ratio:.....	-90dB, A-weighted
Max Output Level into 100 Ohms:	+2.0dBV, typical
Output Impedance:	75 Ohm
Load Impedance:.....	32 to 600 Ohms

Services

If your MobileU Live needs servicing, follow these instructions.

Check our online help centre at <http://support.iconproaudio.com/hc/en-us>, for information, knowledge, and downloads such as:

1. FAQ
2. Download
3. Learn More
4. Forum

Very often you will find solutions on these pages. If you don't find a solution, create a support ticket at our online ACS (Auto Customer Support) at the below link, and our technical support team will assist you as soon as we can.

Navigate to <http://support.iconproaudio.com/hc/en-us> and then sign in to submit a ticket or click "Submit a ticket" without the need to sign in.

As soon as you have submitted an enquiry ticket, our supporting team will assist you to resolve the problem with your ICON ProAudio device as soon as possible.

To send defective products for service:

1. Ensure the problem is not related to operation error or external system devices.
2. Keep this owner's manual. We don't need it to repair the unit.
3. Pack the unit in its original packaging including end card and box. This is very important. If you have lost the packaging, please make sure you have packed the unit properly. ICON is not responsible for any damage that occurs due to non-factory packing.
4. Ship to the ICON Pro Audio tech support center or the local return authorization. See our service centres and distributor service points at the link below:

If you are located in US

Send the product to:

North America

Mixware, LLC – U.S. Distributor

11070 Fleetwood Street – Unit F.

Sun Valley, CA 91352; USA

Tel.: (818) 578 4030

Contact: www.mixware.net/help

Send the product to:

ASIA OFFICE:

**Unit F, 15/F., Fu Cheung Centre,
No. 5-7 Wong Chuk Yueng Street,
Fotan,**

Sha Tin, N.T., Hong Kong.

Tel: (852) 2398 2286

Fax: (852) 2789 3947

Email: info.asia@icon-global.com

If you are located in Europe

Send the product to:

Sound Service

GmbH European

Headquarter Moriz-Seeler-Straße

3D-12489 Berlin

Telephone: +49 (0)30 707 130-0

Fax: +49 (0)30 707 130-189

E-Mail: info@sound-service.eu

5. For additional update information please visit our website at:
www.iconproaudio.com



<p>天猫官方旗舰店</p>  <p>天猫店iconproaudio旗舰店</p>	<p>抖音号</p>  <p>抖音iCON艾肯</p>	<p>哔哩哔哩</p>  <p>B站iCONProAudio</p>	<p>微信公众号</p>  <p>微信号iCON-PRO</p>	<p>官方售后00</p>  <p>4006311312.114.qq.com</p>
--	--	---	---	--

中国地区用户

<p>Twitter</p>  <p>www.twitter.com/iconproaudio</p>	<p>Instagram</p>  <p>www.instagram.com/iconproaudio</p>	<p>Facebook</p>  <p>www.facebook.com/iconproaudio</p>	<p>Youtube</p>  <p>www.youtube.com/iconproaudio</p>
--	--	---	--

<p>Website</p>  <p>www.iconproaudio.com</p>	<p>Support</p>  <p>support.iconproaudio.com</p>	<p>Dashboard</p>  <p>iconproaudio.com/dashboard/</p>
---	---	---

www.iconproaudio.com