

## Release Notes for C•CURE 9000 v2.80 Bosch Receiver Integration v5.4.11.0

---

Document Revision B0

August 2019

This document provides important information about the installation of the C•CURE 9000 Bosch Receiver integration v2.80 on both server and client machines. In case of discrepancy, the information in this document supersedes the information in any document referenced herein. Read this document before you install the product.

**Product:** C•CURE 9000 Bosch Receiver Integration

- Integration Software Version: 5.4.11.0

This driver release is qualified with C•CURE 9000, when installed on:

- victor Unified Systems v3.81 (C•CURE v2.80 and victor v5.4.1)

### Contents:

1. [Overview](#)
2. [What's New](#)
3. [Qualified Hardware and Firmware](#)
4. [Software Requirements](#)
5. [Contents of the Installation Package](#)
6. [Supported Installation Types](#)
7. [Installation](#)
8. [Upgrade the Bosch Receiver Integration](#)
9. [Scalability](#)
10. [Language Support](#)
11. [Compatibility Matrix](#)
12. [Known Issues and Limitations](#)
13. [Defects Fixed](#)
14. [End of Release Notes](#)

## 1. Overview

---

The Bosch Receiver integration provides seamless integration of C•CURE 9000 with Bosch Receivers. Building upon the lineage of Bosch monitoring station receivers, the single-line IP receiver is designed for proprietary applications such as college or university campuses, gated communities or condominiums, dealers monitoring account system status, private corporate security, and government facilities. The receiver calendar stamps all alarm data received before transmitting it to an alarm receiving automation system through TCP/IP. Alarm data can also be transmitted directly to a printer using the parallel printer port and be viewed on the LCD screen on the front of the receiver. The scope of this Integration includes only TCP/IP communications.

## 2. What's New

---

This version of the driver supports the Maintenance Mode.

Maintenance Mode is used to limit information, about an object, displayed on the Monitoring Station. Maintenance Mode only affects what is reported at the Monitoring Station.

### 3. Qualified Hardware and Firmware

---

The following hardware and firmware versions are supported:

- Bosch Receiver 6100 with firmware version 61.04.00
- Bosch Receiver 6600 with firmware version 01.10.00

### 4. Software Requirements

---

The Bosch Receiver Integration requires the following software:

- C•CURE 9000 Security and Event Management System v2.80

### 5. Contents of the Installation Package

---

Table 1: Installation Package lists the contents of the Bosch Receiver Integration installation package:

**Table 1: Installation Package**

File	Description
Bosch_Integration.exe	Installation program for the Bosch Receiver Integration software
CC9K-Bosch-v2-8-UM-8200-1191-1105-A0-en.pdf	C•CURE 9000 Bosch Receiver Integration Guide
CC9K-Bosch-v2-8-RN-8200-1191-1104-B0-en.pdf	Release Notes for C•CURE 9000 Bosch Receiver Integration

### 6. Supported Installation Types

---

The C•CURE 9000 Bosch Intrusion Integration supports the following installation types:

- Unified Standalone
- C•CURE 9000 Standalone
- Unified Enterprise
- C•CURE 9000 Enterprise

### 7. Installation

---

See the *C•CURE 9000 Version 2.80 Bosch Receiver Integration Guide*.

### 8. Upgrade the Bosch Receiver Integration

---

**Caution:**

If you have made any changes in the configuration file - `Bosch Receiver Driver Service.exe`, ensure that you back up the file before upgrading. The configuration file is located at `Tyco\CrossFire\ServerComponents`.

Follow the steps to upgrade the Bosch Receiver Integration from v2.60 to v2.80:

1. Upgrade C•CURE 9000 to v2.80.
2. Install the Bosch Receiver Integration.

Follow the steps to upgrade the Bosch Receiver Integration from v2.70 to v2.80:

1. Upgrade C•CURE 9000 v2.70 to v2.80.
2. Install the Bosch Receiver Integration.

### 9. Scalability

---

This driver is qualified with 2 receivers per server.

## 10. Language Support

This driver supports the following languages:

- English (US)
- French
- German
- Portuguese
- Spanish

## 11. Compatibility Matrix

Table 2: Compatibility Matrix lists the Compatibility Matrix of the Bosch Receiver Integration:

Table 2: Compatibility Matrix	
C•CURE 9000 versions 2.80	
Partner	Bosch
Partner Product	Bosch 6600, Bosch 6100
Partner Product version	61.04.00/01.10.00 Supported Alarm Formats – SIA, CIA, Modem IIIa2 & Modem IV protocol.
Integration driver version	5.4.11.0
C•CURE 9000 License option	CC9000-BOSCHREC
Enterprise certified	Yes
Redundancy certified	Yes (everRun MX)
Supported Server OS	All OS supported by C•CURE 9000 server
Supported Client OS	All OS supported by C•CURE 9000 Client
Supported SQL	All SQL supported by C•CURE 9000 server

## 12. Known Issues and Limitations

This section describes the C•CURE 9000 Bosch Receiver known limitations.

- To upgrade the Bosch Receiver Integration to the current version, you must use the User Account that was used to install the previous version.
- Serial port connection is not supported.
- In communication status of the receiver, disabled status is reported as **Offline** status.
- This integration does not support **Online** status of intrusion panels.
- If you install the Bosch Receiver Integration on remote clients, the **Integration Setup** dialogue box appears and you may be prompted to select an **Installation Option for Redundancy sever**. Ignore this message and click **Next** to continue with installation. If you select the **Redundancy sever installation using supported third party redundancy** check box, provide the virtual server location, and then click **Next**; this selection is ignored and there is no functional impact.
- The Bosch Receiver Integration with C•CURE 2.40 onwards does not support EMC AutoStart or RepliStor products due to their End-Of-Life status.
- Migration of a standalone machine with a Bosch Receiver Integration to SAS is not supported.

**Note:** This driver does not support Authentication when connecting to Bosch Receiver. Bosch driver IP should be configured in Bosch Receiver under *6.Network Configuration* → *6.3 Network Automation Connection*.

Encryption of communication between the Driver and Receiver is not supported currently, but it is planned for future versions.

### 13. Defects Fixed

---

No defects in this release.

### 14. End of Release Notes

---

The trademarks, logos, and service marks displayed on this document are registered in the United States [or other countries]. Any misuse of the trademarks is strictly prohibited and Johnson Controls will aggressively enforce its intellectual property rights to the fullest extent of the law, including pursuit of criminal prosecution wherever necessary. All trademarks not owned by Johnson Controls are the property of their respective owners, and are used with permission or allowed under applicable laws.

Product offerings and specifications are subject to change without notice. Actual products may vary from photos. Not all products include all features. Availability varies by region; contact your sales representative.

© 2019 Johnson Controls.  
All Rights Reserved.