



Main

Product or component type	All-In-One
Range of product	Homeline
Meter socket type	Ringed
Hub type	A-L

Complementary

Line Rated Current	125 A
Phase	1 phase
Short-circuit current	22 kA
Device mounting	Semi flush for outdoor use
Number of spaces	20
Number of circuits	40
Number of tandem circuit breakers	20
Electrical connection	Lugs line side Lugs service ground
AWG gauge	AWG 8...AWG 2/0 (aluminium/copper) service ground AWG 4...250 kcmil (aluminium/copper) line side
Device composition	Service disconnect (factory installed)
Service disconnect rated current	125 A
Branch circuit breaker rated current	110 A
Service feed location	UG OH outdoor
Bypass type	No bypass
Connections - terminals	Plug-on neutral
Colour of enclosure	Grey
Product compatibility	Solar ready

Environment

Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 0944 - Schneider Electric declaration of conformity	Compliant - since 0944 - Schneider Electric declaration of conformity
Available	Available
Need no specific recycling operations	Need no specific recycling operations
WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Lead and lead compounds which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Lead and lead compounds which is known to the State of California to cause cancer and birth defects or other reproductive harm.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.