

United States Patent [19]

Leikus

[11] Patent Number: 4,672,308

[45] Date of Patent: Jun. 9, 1987

[54] ENHANCED FREQUENCY
DETERMINATION FOR SPECTRUM
ANALYZERS OR THE LIKE

[75] Inventor: Vincent C. Leikus, Fairfield, Conn.

[73] Assignee: Rohde & Schwarz - Polarad, Inc.

[21] Appl. No.: 805,349

[22] Filed: Dec. 5, 1985

[51] Int. Cl.⁴ G01R 23/16

[52] U.S. Cl. 324/77 B; 324/78 Z;
324/79 R

[58] Field of Search 324/77 R, 77 B, 77 C,
324/77 D, 78 R, 78 Z, 79 R, 79 D; 364/484,
485, 571; 328/140, 141

[56] References Cited

U.S. PATENT DOCUMENTS

4,249,257 2/1981 Campbell 324/78 Z
4,258,436 3/1981 Campbell 324/78 Z
4,415,854 11/1983 Remy 324/79 R

Primary Examiner—Michael J. Tokar
Attorney, Agent, or Firm—Darby & Darby

[57] ABSTRACT

An arrangement is provided for enhancing the accuracy of frequency determination in a spectrum analyzer or the like having a local oscillator heterodyned with and locked to a frequency comb, by providing a determination of whether the local oscillator frequency is above or below the comb frequency to which it is locked, thereby avoiding ambiguity in the determination of the local oscillator frequency.

12 Claims, 8 Drawing Figures




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 8





FIG. 7



ENHANCED FREQUENCY DETERMINATION FOR SPECTRUM ANALYZERS OR THE LIKE

The present invention concerns improvements enhancing the accuracy of frequency determination, as in spectrum analyzers or the like.

BACKGROUND OF THE ART

In spectrum analyzers, incoming signals of unknown frequency are received and processed to determine their frequency, among other features. This is generally done by causing a receiver circuit to sweep or scan a frequency spectrum, across a band that includes the unknown signal, and determining the frequency of the unknown signal by display or indication on a suitable display such as a cathode ray tube calibrated in frequency.

One way which has been used is to sweep a local oscillator frequency over a desired range and to heterodyne it with the input signal. By using a fixed intermediate frequency, the local oscillator frequency value becomes an indication of the input frequency value, differing from it by the value of the intermediate frequency. The sweeping is terminated when an input signal is received which produces the fixed intermediate frequency. The frequency of the local oscillator is then determined by comparing it with a "comb" of frequencies, derived from a variable control oscillator (VCO) producing an output rich in harmonics, the set of harmonics being spaced at discrete intervals equal to the fundamental frequency F_{VC} of the variable control oscillator. The VCO is varied in frequency until a harmonic (e.g. the N -th harmonic) of F_{VC} differs from the local oscillator frequency by a reference frequency F_R . Then the harmonic order N is determined, and the local oscillator frequency becomes determined as $N \times F_{VC} \pm F_R$. The input frequency F_{IN} then is known as displaced from the local oscillator frequency by the fixed intermediate frequency F_{IF} .

In such an arrangement, an ambiguity can arise, in that the local oscillator frequency may heterodyne with a comb frequency by being either above one comb frequency (which may be a harmonic N of the fundamental F_{VC} of the VCO), or below the adjacent harmonic (e.g. $N+1$) of the comb. The results may be only slightly different in the two instances, and insufficiently different to permit ready distinguishing by usual techniques. In one instance, there may be a 7 megahertz disparity between the two situations, when dealing with a range of frequencies from zero up to about 2 gigahertz.

The present invention is specifically directed toward providing a simple and convenient way of resolving that difficulty, and thereby providing an enhancement of the accuracy of the frequency determination in such situations.

The present invention will be more readily perceived from the following description, taken in conjunction with the appended drawings in which,

FIG. 1 is a schematic block diagram of a circuit according to the present invention, illustrated as applied to a triple conversion superheterodyne spectrum analyzer.

FIG. 2 is a graph showing relative frequencies in the system of the present invention.

FIG. 3 is a fragmentary circuit diagram of a portion of FIG. 1.

FIG. 4 is a graph of tuning voltage versus frequency, useful in explaining the present invention.

FIG. 5 is frequency diagram showing the relationship between the local oscillator frequency and comb frequencies.

FIG. 6 is another diagram similar to FIG. 5, useful in explaining the present invention.

FIG. 7 is a block diagram showing a portion of the circuit of FIG. 1 according to the present invention.

FIG. 8 is a graph of phase versus frequency for a phase detector used in the present invention.

Referring to the drawings,

FIG. 1 shows a block diagram of a wide-band triple-conversion superheterodyne spectrum analyzer that automatically sweeps across a wide frequency band, such as from 10 kilohertz ("Khz") to 2 gigahertz ("Ghz"), to analyze an input signal in that range.

The spectrum analyzer is particularly useful in determining the frequency value F_{IN} of an unknown received input signal. Frequency dispersion is accomplished by sweeping a first local oscillator over a desired range, such as 2 to 4.0 Ghz, and heterodyning its output with the input signal. By way of illustration, the first intermediate frequency ("IF") may be 2.06 Ghz, the second IF at 65 megahertz ("Mhz") and the third IF at 10.7 Mhz. The third IF circuit may have both a variable bandwidth amplifier for resolving closely-spaced input signals, and an amplifier that provides either logarithmic ("LOG") or linear ("LIN") gain. The LOG/LIN amplifier output amplitude is peak-detected and is fed to a display section (via a vertical deflection amplitude) where the signal appears as a frequency-versus-amplitude display. The display device may be a cathode ray tube ("CRT") whose horizontal deflection is synchronized with the local oscillator sweep so that the vertical deflection determined by the LOG/LIN peak detector is automatically positioned along the frequency-calibrated horizontal axis. One form of such a spectrum analyzer is Polarad Model 632C-1, produced by Rohde & Schwarz-Polarad, Inc., Lake Success, N.Y.

Referring to FIG. 1, the unknown input radio frequency signal ("RF") of from 10 Khz to about 2 Ghz may be applied to terminal 201. The RF input signal of frequency F_{IN} is attenuated by a step attenuator 12 to prevent overloading of a doubly balanced first mixer circuit 21 in which the input signal is heterodyned with the output of the first local oscillator ("LO") 23. The input signal is thus up-converted to the first IF (e.g. 2.06 Ghz), which eliminates spurious responses that would occur by using a low IF. Use of fundamental-frequency balanced mixing minimizes harmonic responses, and image and multiple responses may be eliminated by use of an IF amplifier 25 with an optional low-pass filter (e.g. of 1.8 Ghz).

The first LO 23 is a suitable tunable oscillator, such as a solid-state YIG-tuned oscillator, with its frequency F_{LO} tunable illustratively from 2.06 to 4.1 Ghz. For wide frequency spans (e.g. 0.5 Mhz per division or above) the first LO 23 is tuned to sweep about a selectable center frequency F_o set by a suitable frequency selector switch or control 13 supplying a center-frequency control voltage. A sweep generator 32 provides a signal for sweeping the first LO 23 output F_{LO} as described below, by supplying a voltage ramp which is summed with the center frequency control voltage in a local oscillator driver circuit 310. The frequency dispersion or sweep range is determined by a suitable attenuator 311 in the output of the sweep generator 32, which

adjusts the amplitude of the tuning voltage ramp. To cover an entire 0 to 1.8 Ghz RF input range, the LO 23 would sweep from 2.06 to 3.86 Ghz.

The sweep generator 32 thus supplies a tuning voltage ramp (such as ± 5 volts in amplitude) which is applied to the first LO driver circuit 310 to sweep the output of the first LO 23. The same ramp voltage drives the horizontal deflection circuits in a CRT or similar display V1, to provide the frequency-calibrated horizontal display. The sweep generator 32 also controls a blanking amplifier 10 to provide a blanking pulse which shuts off the high-voltage source 6 for the display V1, during beam retrace.

The first IF output F_{IF} from first mixer 21 after being amplified and filtered by first IF amplifier/filter 25 is supplied to a second mixer 216 where it is mixed with the fixed-frequency output of a second LO 212, illustratively of 1.995 Ghz. The difference frequency of 65 Mhz is the second IF, which is fed to the second IF amplifier/attenuator 217, and thence to the third mixer 36. The amount of attenuation introduced may be set by a reference level control, not shown. At the third mixer 36, the second IF signal is mixed with the output of a third LO 37 to be down-converted to the third IF, illustratively of 10.7 Mhz. The third LO 37 is preferably a stable voltage-controlled oscillator tunable over a small range, such as from 53.8 to 54.8 Mhz. For wide frequency spans (e.g. 0.5 Mhz per division or higher) the third LO frequency is fixed. For narrow frequency spans (e.g. 100 Khz per division or less) the third LO is swept under control of the sweep generator 32, in suitable manner. For fixed-frequency or zero span, the sweep generator is disconnected from both the first LO 23 and the third LO 37.

FIG. 2 illustrates the frequency conversion of the input signal F_{IN} at the first mixer to produce the first IF (F_{IF}). FIG. 4 illustrates the tuning voltage T.V. (and hence the first LO frequency F_{LO} to which it is proportional) as a function of time illustrated as a sawtooth wave of amplitude 10 volts, centered at a 5-volt value. The zero value corresponds to 2 Ghz and the 10-volt value to 4 Ghz for the local oscillator, corresponding similarly to input frequencies of 0 to 2 Ghz. This shows how the input frequency to which the system is tuned will be swept.

As shown in FIG. 3, the tuning voltage T.V. from center frequency control circuit 13 is added to the sawtooth sweep voltage from sweep generator 32 in driver circuit 310, and the sum controls the first LO 23 to vary its frequency over a range illustratively from about 2 to 4 Ghz, by repetitive sweeping as shown in FIG. 4. As appears from FIG. 2, the input signal F_{IN} is equal to the LO frequency F_{LO} less the first IF value F_{IF} . Hence, by making the IF constant (say 2.06 Ghz) the input frequency F_{IN} can be determined accurately by measuring the first LO frequency F_{LO} precisely. The principal object of the present invention is to enhance the precision of acquiring the input frequency by determining the LO frequency F_{LO} .

For narrow and zero frequency spans, the display resolution is limited by the frequency stability of the first LO 23, which is therefore held and required to be at a fixed frequency F_{LO} in those situations, as by an automatic phase-lock stabilization circuit shown in FIG. 1 formed by a phase-lock mixer 26, phase-locked to a harmonic of a stable but variable crystal-controlled reference oscillator 16 of frequency F_{VC} (illustratively of 17 Mhz output). Although crystal-controlled, the

frequency F_{VC} of reference oscillator 16 may be varied or "pulled" slightly (e.g. up to 85 Khz) from its nominal crystal-controlled frequency (e.g. 17 Mhz.). In this situation, the only inputs to the driver circuit 310 are the set center frequency tuning voltage T.V. and a phase-lock stabilization error voltage on line 51. However, for wide frequency spans, this phase-lock circuit 26 is made inoperative, as by opening line 51.

For narrow-span operation, the phase-lock circuit operates by heterodyning in phase lock mixer 26 the first LO frequency F_{LO} from first LO 23 with one of the harmonics from variable reference oscillator 16 produced in an amplifier "comb generator" circuit 27. Circuit 27 produces a richly harmonic output, with a large number of multiples of the variable reference frequency (e.g., N times 17 Mhz) which is called a frequency comb, formed as a series of separate frequencies spaced by F_{VC} . The output of the phase lock mixer 26 is passed through a fixed-tuned amplifier and filter 21 tuned to a fixed frequency F_R (e.g., 12 Mhz) and is phase-compared to the output of a fixed reference oscillator 39 in a phase-lock control circuit 40. The output of circuit 40 supplies a driver 162 which causes the variable reference oscillator frequency F_{VC} to be varied ("pulled") until a zero error voltage is sensed in circuit 40 whereupon its frequency is locked, indicating that the first LO frequency (e.g. 2.06 Ghz) differs by a fixed amount F_R (e.g. 12 Mhz) from some unknown multiple N of the first reference frequency F_{VC} (e.g. N times 17 Mhz). If the first LO frequency shifts, (due to drift of LO 23) the phase control circuit 26 feeds an appropriate error voltage to driver 310 by way of phase lock control 40 to correct the drift until the difference between the first local oscillator frequency (F_{LO}) and the comb frequency $N \times F_{VC}$ (e.g. $N \times 17$ Mhz) is again exactly the reference frequency F_R from oscillator 39 (e.g. 12 Mhz). This frequency relation is illustrated in FIG. 5, showing the comb harmonics N, N-1 and N-2 in relation to F_{LO} in the illustrative example used. In this case, the F_{LO} is shown locked to harmonic N of the 17 Mhz variable-frequency reference, from which F_{LO} differs by being exactly 12 Mhz below $N \times 17$ Mhz.

As will be seen from FIG. 5, the actual local oscillator frequency F_{LO} may be determined by knowing which harmonic N is the one to which the LO 23 is locked. Thus, from FIG. 4

$$F_{LO} = F_{IF} + \frac{T.V.}{K} \quad (1)$$

since the deviation of F_{LO} from F_{IF} is proportional to the tuning voltage T.V. with a proportionality factor (10 volt to 2 volt DVM system) of $1/K$ (e.g. $1/5$ in this instance).

Then as seen in FIG. 5, the harmonic number N is

$$N = \frac{(F_{LO} + F_R)}{F_{VC}} \quad (2)$$

where F_{VC} is the pulled frequency of the variable reference oscillator 16 and F_R is the fixed reference frequency of reference oscillator 39. From this,

$$F_{LO} = N \times F_{VC} - F_R \quad (3)$$

The value of F_{VC} can then be accurately determined by a frequency counter 403. Then

$$F_{IN} = F_{LO} - F_{IF} \text{ if in Ghz} \quad (4)$$

$$= 1000 (F_{LO} - F_{IF}) \text{ in Mhz.} \quad (5)$$

However, an error may arise if the LO frequency F_{LO} locks (with a difference equal to the reference oscillator 39 frequency F_R) onto a lower harmonic of F_{VC} as seen from FIG. 6. The proper value may be either F_{LO} or F'_{LO} in FIG. 6 differing by $F_{VC} - F_R$. According to an aspect of the invention, this ambiguity is avoided.

As seen in FIG. 1, the phase lock mixer 26 combines the output frequencies $N \times F_{VC}$ of the comb generator 127 with the frequency F_{LO} of the first local oscillator 23 to produce the reference difference frequency F_{RD} . This is compared with the fixed reference frequency F_R in phase detector 40. When the difference between F_R and F_{RD} is zero, in frequency and phase, F_{LO} is locked and equal to $N \times F_{VC} \pm F_R$. The reference difference frequency F_{RD} is also compared with a 90-degree phase-shifted version of F_R in detector 312. Each phase detector is of conventional type, producing an output characteristic as shown in FIG. 8, being positive for phase differences of 90° – 180° and negative for differences of 0° – 90° .

When LO frequency F_{LO} is locked at $N \times F_{VC} - F_{LO}$, the output of detector 312 will be positive, and for $N \times F_{VC}$ less than F_{LO} the output will be negative. This feature is utilized to resolve the ambiguity between N and $N+1$ shown in FIG. 6.

As seen in FIG. 7, a conventional polarity detector 401, with signal conversion from analog to digital form, is fed from the output of phase detector 40. In usual manner, this produces a "high" digital signal (e.g., bit "1") for a positive input signal, and a "low" digital signal (e.g. bit "0") for a negative input signal.

Another conventional analog/digital converter 402 produces in known manner a digital signal representing the tuning voltage applied to first LO 23, which is therefore representative of tuning voltage T.V. in equation (1) above. This A/D converter 402 may alternatively be supplied from the T.V. input to LO driver 310, as symbolically represented by switch SW2. A conventional counter circuit 403 determines the actual frequency F_{VC} of the variable crystal oscillator 16, in digital form.

The digital outputs of circuits 401, 402 and 403 are combined in a suitable microprocessor or CPU 404 (or equivalent electronic circuitry performing the same functions) to calculate the equations above, with the difference that, if F_{LO} is above $N \times F_{VC}$, as shown in FIG. 6, then the output from the polarity detector causes the sign of F_R in equations 2 and 3 to be reversed, so that they become:

$$N = \frac{(F_{LO} - F_R)}{F_{VC}} \quad (2')$$

and

$$F_{LO} = N \times F_{VC} + F_R \quad (3)$$

In this way, the possible error or uncertainty in the value of F_{LO} , leading to error in determining F_{IN} , is avoided and the ambiguity of the system is resolved.

While the foregoing description illustrates the present invention as applied to spectrum analyzers, it is to be understood that it is not limited thereto, but may be

used in other situations where elimination of ambiguities is desired in heterodyne systems.

What is claimed is:

1. In a superheterodyne spectrum analyzer for determining the frequency F_{IN} of a variable-frequency input signal and having a variable-frequency local oscillator producing a frequency F_{LO} and a mixer for mixing said local oscillator frequency F_{LO} and said input frequency F_{IN} to produce an intermediate frequency F_{IF} which is the difference between F_{LO} and F_{IN} , apparatus for enhancing the accuracy of determination of F_{IN} comprising:

- (a) a source of a first reference frequency F_{VC} ,
- (b) means for producing a frequency comb having numerous harmonics of said first reference frequency F_{VC} ,
- (c) a source of a second reference frequency F_R ,
- (d) means for causing said frequency F_{LO} to differ from some multiple N of said first reference frequency F_{VC} by said second reference frequency F_R when said intermediate frequency F_{IF} has a predetermined value,
- (e) means for determining the value of said multiple N regardless of whether said local oscillator frequency F_{LO} is greater than or less than said reference frequency multiple $N \times F_{VC}$,
- (f) means for determining the value of F_{LO} in response to said multiple-value-determining means and said sources of frequencies F_{VC} and F_{LO} , whereby the input frequency F_{IN} is determined as the difference between the value of F_{LO} and said predetermined value of F_{IF} .

2. Apparatus as in claim 1 further including

- (a) means determining whether said local oscillator frequency F_{LO} is greater or less than said first reference frequency multiple $N \times F_{VC}$, and
- (b) means responsive to said preceding means for determining the value of said multiple N .

3. Apparatus as in claim 2 including

means for determining said multiple N as the ratio of F_{LO} plus F_R to F_{VC} when said multiple frequency $N \times F_{VC}$ is greater than F_{LO} or as the ratio of F_{LO} minus F_R to F_{VC} when said multiple frequency $N \times F_{VC}$ is less than F_{LO} .

4. Apparatus as in claim 1 further including

means for varying the frequency of said first reference frequency F_{VC} to cause said multiple N of said first reference frequency to differ from said local oscillator frequency F_{LO} by an amount equal to said second reference frequency F_R .

5. Apparatus as in claim 4 further including means deriving a signal of a frequency equal to the difference between said local oscillator frequency F_{LO} and said multiple frequency $N \times F_{VC}$,

means responsive to said difference frequency for determining whether said multiple frequency $N \times F_{VC}$ is greater or less than said local oscillator frequency.

6. Apparatus as in claim 5 wherein a last means comprises means for phase-shifting the output of said second reference frequency source by 90 degrees, and

a phase-lock detector responsive to said phase-shifted signal and to said difference-frequency signal for producing a polarity signal whose polarity indicates whether said local oscillator frequency F_{LO} is greater or less than said multiple frequency $N \times F_{VC}$.

7. Apparatus as in claim 6 further including means determining said multiple in response to said polarity signal.

8. Apparatus as in claim 1 further including means determining said input frequency F_{IN} as the difference between said intermediate frequency F_{IF} and said multiple N times said first source frequency F_{VC} , which difference is increased or decreased by said second source frequency F_R in accordance with the polarity of said polarity signal.

9. A system for determining the frequency F_{IN} of a variable-frequency input signal, comprising

- (i) a variable-frequency local oscillator producing a frequency F_{LO} ,
- (ii) a mixer for mixing said local oscillator frequency F_{LO} and said input frequency F_{IN} to produce an intermediate frequency F_{IF} ,
- (iii) means for adjusting the frequency F_{LO} to cause said intermediate frequency F_{IF} to have a predetermined fixed value and
- (iv) means for determining the frequency of said local oscillator, said last means comprising
 - (a) a source of a first adjustable reference frequency F_{VC} ,
 - (b) means for producing a frequency comb having numerous harmonics of said first reference frequency F_{VC} ,
 - (c) a source of a second fixed reference frequency F_R ,
 - (d) means for varying said first reference frequency F_{VC} to cause some multiple N of said first reference frequency F_{VC} to differ from said local oscillator frequency F_{LO} by an amount equal to said second reference frequency F_R ,
 - (e) means for determining the value of said multiple N regardless of whether said local oscillator frequency F_{LO} is greater than or less than said reference frequency multiple $N \times F_{VC}$, and

(f) means for determining the value of F_{LO} in response to said multiple-value-determining means and said sources of frequencies F_{VC} and F_{LO} ,

whereby the input frequency F_{IN} is determined as the difference between the thus determined value of F_{LO} and said predetermined value of F_{IF} .

10. The method of determining the frequency of an unknown signal, comprising the steps of producing a first adjustable reference frequency, producing a frequency comb having numerous harmonics of such first reference frequency, producing a second fixed reference frequency, mixing said input signal and a signal of some multiple of said first reference frequency to produce a difference frequency, adjusting said first reference frequency to cause said difference frequency to equal said fixed second reference frequency, determining whether the value of said frequency multiple is greater than or less than the frequency of said unknown signal, determining the value of said multiple regardless of whether said input signal frequency is greater than or less than said multiple frequency, and determining said unknown signal frequency as the said determined multiple of said first reference frequency plus or minus said fixed reference frequency in correspondence with whether said unknown signal frequency is greater than or less than said multiple frequency.

11. A method as in claim 10, wherein said step of determining whether said unknown signal frequency is greater or less than said reference frequency multiple comprises the step of mixing said difference frequency with said second reference frequency in a phase-lock detector, and determining the polarity of the result.

12. A method as in claim 11 comprising the step of mixing a 90° phase-shifted version of said fixed reference frequency with said difference frequency and determining the polarity of the result.

* * * * *

40

45

50

55

60

65