




Adjusting the transmission power – “RF Power”



Via the “RF Power” menu item, you can adjust the transmission power in two steps (Low, Standard).

 It is vital to observe the notes on the enclosed frequency information sheet!



Activating/deactivating warning messages – “Warnings”

Via the “Warnings” menu item, you can activate or deactivate different warning messages.



Setting	Warning message*	Trigger
AF Peak	“AF Peak”	Audio overmodulation
RF Mute	“RF Mute”	RF signal is deactivated (see page 16)

* with color change on the standard display

Adjusting the contrast of the display panel – “LCD Contrast”


You can adjust the contrast of the display panel in 16 steps.

Resetting the settings made in the operating menu – “Reset”




When resetting the settings made in the operating menu, only the selected settings for the pilot tone and for the frequency banks “U1” to “U6” remain unchanged. For an overview of the factory-preset default settings, refer to the enclosed frequency information sheet.


Adjusting settings via the operating menu



Adjusting the network configuration – “IP Address”




Call up “IP-Address”



Select the mode and confirm

“Stored”



Enter the IP address; store the setting



You can either automatically allocate or manually enter an IP address. This menu item also shows the transmitter's unique and unchangeable MAC address. In order to ensure safe communication between transmitters in multi-channel systems (see page 33), we recommend using automatic allocation of IP addresses.

Displaying the software revision – “Software Revision”

You can display the current software revision of the transmitter.

- For information on software updates, visit the SR 300 IEM G3 product page on our website at www.sennheiser.com.

Synchronizing the transmitter with an EK 300 IEM G3 receiver

When synchronizing your transmitter with a receiver, please observe the following:



- ▶ Only use a transmitter and a receiver from the same frequency range (see the type plates on the transmitter and the receiver).
- ▶ Make sure that the desired frequencies are listed in the enclosed frequency information sheet.
- ▶ Make sure that the desired frequencies are approved and legal in your country and, if necessary, apply for an operating license.

Synchronizing the transmitter with an EK 300 IEM G3 receiver – individual operation

Upon delivery, transmitter and receiver are synchronized with each other. If, however, you cannot establish a transmission link between transmitter and receiver, you have to synchronize the channels of the devices:

- ▶ Carry out the Easy Setup Sync function and then the Sync function (see page 17). This establishes a transmission link between the transmitter and the receiver.


Alternatively, you can set the channel on the transmitter manually:

- ▶ Make sure that you set the transmitter to the same frequency bank and the same channel as the receiver.

Synchronizing transmitters with EK 300 IEM G3 receivers – multi-channel operation

Network operation using the WSM

In multi-channel operation, the transmitters are remote controlled via a PC running the "Wireless Systems Manager" (WSM) software.



Advantages of controlling the transmitters via the "Wireless Systems Manager" (WSM) software

- Detailed overview of all transmission and receiving channels
- Remote control of all transmitters in the network
- Combination of transmitters of different frequency ranges (see page 4)

- ▶ Connect your transmitters and your PC in a network (see page 12).
- ▶ Switch your transmitters and your PC on.
- ▶ Launch the "Wireless Systems Manager" (WSM) software.
- ▶ To set up your multi-channel system, proceed as described in the instruction manual of the "Wireless Systems Manager" (WSM) software.

Operation without network

- ▶ Carry out the Easy Setup Sync function and then, for each transmitter/receiver pair, the Sync function (see page 17).
This establishes a transmission link between the transmitter and the receiver.

Using freely selectable transmission frequencies

You can also freely select the frequencies and store these frequencies in the frequency banks "U1" to "U6".

If you want to use the frequency banks "U1" to "U6":

- ▶ Make sure to use transmitters and receivers from the same frequency range (see page 4 and the type plates of the devices).
- ▶ Only use frequencies that are approved and legal in your country (see page 33).



To ensure that the desired frequencies are intermodulation-free:

- ▶ Contact your Sennheiser partner (see www.sennheiser.com).
-

- ▶ Set each transmitter to the same frequency bank.
 - ▶ On one of the transmitters, select a channel within this frequency bank (see page 20).
 - ▶ Assign this channel one of the calculated transmission frequencies (see page 20).
 - ▶ Synchronize a receiver with your transmitter (sync▶, see page 17).
- OR
- ▶ Manually set the receiver to the same frequency bank, channel and frequency that you set on the transmitter.
 - ▶ Repeat for the remaining transmitters and receivers as described above.

Cleaning the transmitter

CAUTION!

Liquids can damage the electronics of the transmitter!

Liquids entering the housing of the transmitter can cause a short-circuit and damage the electronics.

- ▶ Keep all liquids away from the transmitter.
- ▶ Before cleaning, disconnect the transmitter from the mains.
- ▶ Use a cloth to clean the transmitter from time to time. Do not use any solvents or cleansing agents.

Recommendations and tips

... for optimum reception

- Transmission range depends to a large extent on location and can vary from about 10 m to about 150 m. There should be a "free line of sight" between transmitting and receiving antennas.
- To avoid overloading the receiver, observe a minimum distance of 5 m between transmitting and receiving antennas.

... for multi-channel operation

- Each of the frequency banks "1" to "20" accommodates factory-preset receiving frequencies which are intermodulation-free. For possible frequency combinations, please refer to the supplied frequency information sheet.
- The channels in the frequency banks "U1" to "U6" can be assigned freely selectable frequencies (see page 34).
- When using several transmitters simultaneously, interference can be avoided by maintaining a minimum distance of 20 cm between two transmitters.
- Use accessories recommended by Sennheiser for multi-channel applications (see page 36).

Accessories and spare parts

Cat. No.	Accessory/spare part
532711	Stacking elements, 1 pair
503167	GA 3 rack adapter
009912	AM 2 antenna front mount kit (for GA 3 rack adapter)
503157	NT 2-3 EU: Mains unit for powering the SR 300 IEM G3; EU version
503870	NT 2-3 US: Mains unit for powering the SR 300 IEM G3; US version
503871	NT 2-3 UK: Mains unit for powering the SR 300 IEM G3; UK version
503159	NT 3-1 EU: Table top power supply for powering the AC 3 and four transmitters; EU version
503876	NT 3-1 US: Table top power supply for powering the AC 3 and four transmitters; US version
503877	NT 3-1 UK: Table top power supply for powering the AC 3 and four transmitters; UK version
503166	AC 3 antenna combiner
528212	A 5000 CP circularly polarized broadband antenna
003658	A 2003 directional broadband antenna
004645	A 1031 omni-directional broadband antenna
087969	Antenna daisy-chain cable, 50 Ω , BNC, 0.25 m
002324	GZL 1019-A1 coaxial cable, type RG 58, BNC to BNC, 1 m

If a problem occurs ...

Problem	Possible cause	Possible solution
Transmitter cannot be operated, "Locked" appears on the display panel	Lock mode is activated	Deactivate the lock mode (see page 15 and page 20).
No operation indication	No mains connection	Check the connections of the mains unit.
No RF signal at the receiver	Transmitter and receiver are not on the same channel	Set the transmitter and receiver to the same channel. To do so, use the synchronization function (see page 16).
	If "RF Mute" additionally appears on the transmitter display: RF signal is deactivated	Activate the RF signal (see page 16).
Very weak RF signal at the receiver	Transmission range is exceeded	Reduce the distance between receiver and transmitter. Reposition the antennas. Increase the transmission power (see page 21). Check the squelch threshold setting on the receiver. Reduce the squelch threshold (see the instruction manual of the receiver).
RF signal available, no audio signal at the receiver	No input signal at the transmitter	Check the audio level on the transmitter display (see page 7).
	Very low input signal	Check the audio level on the transmitter display (see page 7), increase the level of the input signal or adjust the input sensitivity (see page 20).
Audio signal has a high level of background noise	Transmitter sensitivity is adjusted too low	Adjust the transmitter sensitivity correctly.
Audio signal is distorted	If "AF PEAK" additionally appears on the transmitter display: transmitter sensitivity is adjusted too high	Adjust the transmitter sensitivity correctly.
	Receiver's audio output level is adjusted too high	Reduce the audio output level (see the instruction manual of the receiver).

If a problem occurs that is not listed in the above table or if the problem cannot be solved with the proposed solutions, please contact your local Sennheiser partner for assistance. To find a Sennheiser partner in your country, search at www.sennheiser.com under "Service & Support".

Specifications

Specifications

RF characteristics

Frequency ranges

516–558, 566–608, 626–668, 734–776,
780–822, 823–865 MHz (A to E, G, see page 4)

Transmission frequencies

1,680 frequencies, tuneable in steps of 25 kHz
20 frequency banks, each with up to 16 factory-preset
channels

6 frequency banks with up to 16 user programmable
channels

42 MHz

±10 ppm (–10°C to +55°C)

BNC socket, 50 Ω

typ. 10/30 mW

(Low/Standard),

switchable

Switching bandwidth

Frequency stability

Antenna output

RF output power at 50 Ω

AF characteristics

Modulation

wideband FM stereo (MPX pilot tone)

Comander system

Sennheiser HDX

Nominal/peak deviation

±24 kHz/±48 kHz

MPX pilot tone (frequency/deviation)

19 kHz/±5 kHz

AF frequency response

25 Hz to 15 kHz

AF input BAL AF IN L (I)/BAL AF IN R (II)

2 x XLR-3/¼" (6.3 mm) jack combo socket,
electronically balanced

+22 dBu

Max. input level

THD

< 0.9 %

(at 1 kHz and nominal deviation)

Signal-to-noise ratio

> 90 dB

at nominal load and peak deviation

AF output LOOP OUT BAL L (I)/LOOP OUT BAL R (II)

¼" (6.3 mm) stereo jack socket, balanced

Overall device

Temperature range

–10 °C to +55 °C

Power supply

12 V ===

Current consumption

max. 350 mA

Dimensions

approx. 202 mm x 212 mm x 43 mm

Weight

approx. 980 g

In compliance with

Europa



EMC EN 301489-1/-9

Radio EN 300422-1/-2

Safety EN 60065

Approved by

Canada

Industry Canada RSS 123,
IC: 2099A-G3SREK
limited to 806 MHz

USA

FCC-Part 74 FCC-ID: DMOG3SREK
limited to 698 MHz

NT 2-3 mains unit

Input voltage

100 to 240 V~, 50/60 Hz

Current consumption

max. 120 mA

Output voltage

12 V ===

Secondary output current

400 mA

Temperature range

-10 °C to +40 °C

In compliance with

Europe

CE EMC EN 55022, EN 55024,
EN 55014-1/-2
Safety EN 60065

USA





FCC 47 CFR 15 subpart B

Canada

ICES 003

The mains unit is certified in accordance with the legal safety requirements of Europe, the United States, Canada, Russia and Japan.

Connector assignment

Audio	Other connectors
<p>1/4" (6.3 mm) stereo jack plug, balanced (Audio In/Loop out)</p> 	<p>DC connector for power supply</p> 
<p>1/4" (6.3 mm) mono jack plug, unbalanced</p> 	<p>1/4" (6.3 mm) stereo jack plug for headphone output</p> 

Manufacturer Declarations

Warranty

Sennheiser electronic GmbH & Co. KG gives a warranty of 24 months on this product.

For the current warranty conditions, please visit our website at www.sennheiser.com or contact your Sennheiser partner.


In compliance with the following requirements

- RoHS Directive (2002/95/EC)
- WEEE Directive (2002/96/EC)



Please dispose of the transmitter at the end of its operational lifetime by taking it to your local collection point or recycling center for such equipment.

CE Declaration of Conformity

- **CE 0682** 
- R&TTE Directive (1999/5/EC), EMC Directive (2004/108/EC), Low Voltage Directive (2006/95/EC)
The declarations are available at www.sennheiser.com.
Before putting the device into operation, please observe the respective country-specific regulations.

Statements regarding FCC and Industry Canada

This device complies with Part 15 of the FCC Rules and with RSS-210 of Industry Canada. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This class B digital device complies with the Canadian ICES-003.

Changes or modifications made to this equipment not expressly approved by Sennheiser electronic Corp. may void the FCC authorization to operate this equipment.

Before putting the device into operation, please observe the respective country-specific regulations!

Index

- activating/deactivating
 - AF Peak (warning message) 31
 - lock mode (Auto Lock) 28
 - RF Mute (warning message) 31
 - warning messages (Warnings) 31
- adjusting
 - contrast (LCD Contrast) 31
 - input sensitivity (Sensitivity) 24
 - network configuration (IP Address) 32
 - receiver parameters (Sync Settings) 30
 - transmission power (RF Power) 31
- Advanced Menu (extended menu)
 - overview 20
 - settings 28
- antenna
 - connecting a remote antenna 12
 - connecting the AC 3 antenna combiner 12
 - connecting the rod antenna to the front 10
 - connecting the rod antenna to the rear 8
- antenna front mount kit 10
- audio signal
 - connecting to input 11
 - daisy chaining 11
 - monitoring 16
- audio source
 - connecting 11
 - daisy chaining 11
- Auto Lock (activating/deactivating the lock mode) 28
- buttons
 - function 19
 - using 19
- channel
 - assigning a frequency 29
 - display 7
 - overview 4
 - selecting (Frequency Preset) 26
 - selecting (Tune) 28
- connecting
 - antenna 8
 - mains unit 13
 - transmitters in a network 12
- device feet, fitting 8
- displays
 - adjusting the contrast of the display panel (LCD Contrast) 31
 - AF (audio level) 7
 - equalizer setting 7
 - frequency 7
 - frequency bank and channel 7
 - input sensitivity 7
 - lock mode icon 7
 - name of the transmitter 7
 - overview 7
 - PEAK (overmodulation) 7
 - transmission icon 7
 - transmission power 7
- Easy Setup Sync 16, 17
- equalizer
 - display of equalizer setting 7
 - settings 27
- extended menu (Advanced Menu)
 - overview 20
 - settings 28
- factory default settings (resetting the settings made in the operating menu) 31
- frequency
 - ~ ranges 4
 - display 7
 - preset frequencies 4
 - selecting ~ presets 26
 - setting a transmission frequency 28
 - using freely selectable transmission frequencies 34
- frequency bank
 - ~ system 4
 - display 7
 - overview 4
 - selecting (Frequency Preset) 26
- Frequency Preset (selecting a frequency bank/channel) 26
- infra-red transmission 16
- IP-Address (adjusting the network configuration) 32
- LCD Contrast (contrast of the display panel) 31

- lock mode
 - activating/deactivating (Auto Lock) 28
 - deactivating temporarily 15
- Locked (lock mode activated) 15
- main menu (Menu)
 - overview 20
 - settings 24
- mains unit, connecting 13
- Menu (main menu)
 - overview 20
 - settings 24
- mixing console, connecting 11
- Mode (mono/stereo selection) 25
- modulation (input sensitivity/adjusting the sensitivity) 24
- mono operation 6, 25
- Name (entering a name) 26
- network
 - adjusting the network configuration (IP Address) 32
 - setting up 12
- offline operation (RF signal deactivated) 15
- online operation (RF signal activated) 14
- operating menu
 - overview 20
 - using 22
- receiver settings
 - activating/deactivating the infra-red transmission (Sync Settings) 30
 - adjusting (Sync Settings) 30
- receiver, synchronizing with transmitter 16
- Reset (resetting the settings made in the operating menu) 31
- RF Mute (warning message) 15, 16, 21
- RF Mute Off (activating the RF signal) 15, 16
- RF Mute On (deactivating the RF signal) 16
- RF Power (adjusting the transmission power) 31
- selecting
 - channel (Frequency Preset) 26
 - frequency bank (Frequency Preset) 26
 - frequency bank (Tune) 28
 - mono or stereo operation (Mode) 25
- Sensitivity (adjusting the input sensitivity) 24
- Software Revision (displaying the software revision) 32
- standby 14
- stereo operation 25
- switching on/off 14
- Sync 17
- Sync Settings (adjusting transferable receiver settings) 30
- synchronizing (transmitter/receiver) 16
- transmission frequency
 - selecting (Frequency Preset) 26, 28
 - setting (Tune) 28
- transmission power, optimizing 35
- transmitter
 - cleaning 35
 - connecting in a network 12
 - fitting the device feet 8
 - mounting into a 19" rack 9
 - setting up on a flat surface 8
 - switching on/off 14
 - switching to standby 14
 - synchronizing with receiver 16
 - using 14
- troubleshooting 37
- Tune (setting the transmission frequencies and frequency banks) 28
- Unlock (deactivating the lock mode) 15
- using
 - buttons 19
 - equalizer 27
 - operating menu 22
- warning messages (Warnings)
 - activating/deactivating 31
 - overview 21
- Warnings (warning messages)
 - activating/deactivating 31
 - overview 21
- WSM (Wireless Systems Manager) 12

Sennheiser electronic GmbH & Co. KG
Am Labor 1, 30900 Wedemark, Germany
www.sennheiser.com

Printed in Germany
Publ. 01/09
529680/A01

Sennheiser

evolutionwireless

EK 300 IEM



instruction manual

Contents

Important safety instructions	2
The EK 300 IEM G3 diversity receiver	3
Areas of application	3
The frequency bank system	3
Delivery includes	4
Product overview	5
Overview of the EK 300 IEM G3 diversity receiver	5
Overview of the displays	6
Putting the diversity receiver into operation	7
Inserting the batteries/accupack	7
Charging the accupack	7
Connecting the earphones	7
Attaching the diversity receiver to clothing	8
Using the diversity receiver	9
Switching the diversity receiver on/off and adjusting the volume	9
Deactivating the lock mode temporarily	9
Selecting a standard display	10
Using the operating menu	11
The buttons	11
Overview of the operating menu	11
Working with the operating menu	12
Adjusting settings via the operating menu	14
The main menu "Menu"	14
The extended menu "Advanced Menu"	17
Synchronizing an SR 300 IEM G3 transmitter with the diversity receiver	20
Setting the transmitters to intermodulation-free channels (Easy Setup Sync)	20
Synchronizing transmitters with diversity receivers (Sync)	21
Using freely selectable receiving frequencies	21
Cleaning the diversity receiver	22
Recommendations and tips	22
If a problem occurs	23
Accessories	24
Specifications	24
Manufacturer Declarations	25
Index	27



For further information, visit the EK 300 IEM G3 product page on our website at www.sennheiser.com.

Important safety instructions

- Read this instruction manual.
- Keep this instruction manual. Always include this instruction manual when passing the product on to third parties.
- Heed all warnings and follow all instructions in this instruction manual.
- Use only a cloth for cleaning the product.
- Do not place the product near any heat sources such as radiators, stoves, or other devices (including amplifiers) that produce heat.
- Only use attachments/accessories specified by Sennheiser.
- Refer all servicing to qualified service personnel.
Servicing is required if the product has been damaged in any way, liquid has been spilled, objects have fallen inside, the product has been exposed to rain or moisture, does not operate properly or has been dropped.
- **WARNING:** To reduce the risk of short circuits, do not use the product near water and do not expose it to rain or moisture.
- This product is also intended for professional use. Commercial use is subject to the safety-at-work regulations. Sennheiser, as the manufacturer, is therefore obliged to expressly point out possible health risks arising from use.

This product is capable of producing sound pressure exceeding 85 dB(A). 85 dB(A) is the sound pressure corresponding to the maximum permissible volume which is by law (in some countries) allowed to affect your hearing for the duration of a working day. It is used as a basis according to the specifications of industrial medicine. Higher volumes or longer durations can damage your hearing. At higher volumes, the duration must be shortened in order to prevent hearing damage. The following are sure signs that you have been subjected to excessive noise for too long a time:

- You can hear ringing or whistling sounds in your ears.
- You have the impression (even for a short time only) that you can no longer hear high notes.

Replacement parts

When replacement parts are required, be sure the service technician uses replacement parts specified by Sennheiser or those having the same characteristics as the original part. Unauthorized substitutions may result in fire, electric shock, or other hazards.

Intended use

Intended use of the EK 300 IEM G3 diversity receiver includes:

- having read these instructions especially the chapter "Important safety instructions",
- using the product within the operating conditions and limitations described in this instruction manual.

"Improper use" means using the product other than as described in this instruction manual, or under operating conditions which differ from those described herein.

The EK 300 IEM G3 diversity receiver

This diversity receiver is part of the evolution wireless series generation 3 (ew G3). With this series, Sennheiser offers high-quality state-of-the-art RF transmission systems with a high level of operational reliability and ease of use. Transmitters and receivers are designed for monitoring applications and permit wireless transmission with studio-quality sound.

Features of the evolution wireless 300 IEM G3 series:


- Optimized PLL synthesizer and microprocessor technology
- HDX noise reduction system
- Adaptive diversity technology
- Switching bandwidth of 42 MHz
- Scan function (Easy Setup) for scanning the frequency banks for unused channels
- Adjustable and switchable limiter

Adaptive diversity

This diversity receiver uses the ground connection of the earphones cable as its second antenna to provide improved reception.

Areas of application

The receiver can be combined with the SR 300 IEM G3 transmitter.




The transmitter is available in the same UHF frequency ranges and is equipped with the same frequency bank system with factory-preset frequencies. An advantage of the factory-preset frequencies is that

- a transmission system is ready for immediate use after switch-on,
- several transmission systems can be operated simultaneously on the preset frequencies without causing intermodulation interference.


The frequency bank system

The diversity receiver is available in 6 UHF frequency ranges with 1,680 receiving frequencies per frequency range:



Delivery includes

Each frequency range (A–E, G) offers 26 frequency banks with up to 16 channels each:



Each of the channels in the frequency banks "1" to "20" has been factory-preset to a fixed receiving frequency (frequency preset). The factory-preset frequencies within one frequency bank are intermodulation-free. These frequencies cannot be changed.

For an overview of the frequency presets, please refer to the supplied frequency information sheet. Updated versions of the frequency information sheet can be downloaded from the EK 300 IEM G3 product page on our website at www.sennheiser.com.

The frequency banks "U1" to "U6" allow you to freely select and store receiving frequencies. It might be that these receiving frequencies are not intermodulation-free (see page 20).


Delivery includes

The packaging contains the following items:

- 1 EK 300 G3 IEM diversity receiver
- 2 AA size batteries, 1.5 V
- 1 pair of IE 4 earphones
- 1 instruction manual
- 1 frequency information sheet

Product overview

Overview of the EK 300 IEM G3 diversity receiver
















- ❶ On/off/volume control
- ❷ 3.5 mm stereo jack socket (PHONES), lockable
(the ground contact is used by antenna II)
- ❸ Antenna I
- ❹ Operation and battery status indicator, red LED
lit = ON
flashing = LOW BATT
- ❺ RF signal indication, green LED
lit = RF
- ❻ Charging contacts
- ❼ SET button
- ❽ ▲/▼ rocker button (UP/DOWN)
- ❾ Battery compartment
- ❿ Battery compartment cover
- ⓫ Battery compartment catches
- ⓬ Infra-red interface
- ⓭ ESC button
- ⓮ Display panel, backlit in orange


Overview of the displays

After switch-on, the diversity receiver displays the "Frequency/Name" standard display. For further illustrations and examples of the different standard displays, refer to page 10.

The display backlighting is automatically reduced after approx. 20 seconds.



Display	Meaning
① RF level "RF" (Radio Frequency)	<div>  Diversity display: I Antenna input I is active II Antenna input II is active  RF signal level: Field strength of the received signal  Squelch threshold level </div>
② Audio level "AF" (Audio Frequency)	<div>  Peak hold function  Modulation of the transmitter (channel-separated when the transmitter is set to stereo mode)  When the display shows full deflection, the audio input level is excessively high. </div>
③ Frequency	Current receiving frequency (see page 17)
④ Name	Freely selectable name of the receiver (see page 15)
⑤ Lock mode icon	Lock mode is activated (see page 10)
⑥ Battery status	Charge status:  approx. 100%  approx. 70%  approx. 30%  charge status is critical, the red LOW BATT LED is flashing:
⑦ Muting function "MUTE"	"Mute" is only displayed on the "Frequency/Name" standard display (see page 10) <ul style="list-style-type: none"> when the transmitter's RF signal is deactivated or when the transmitter is set to mono mode and therefore does not transmit a pilot tone but the receiver's pilot tone evaluation is activated.
or audio channels	The audio channels are only displayed on the "Frequency/Limiter" and "Frequency/High Boost" standard displays (see page 10) <ul style="list-style-type: none">  Stereo  Focus
⑧ Pilot tone "P"	Activated pilot tone evaluation (see page 18)




Putting the diversity receiver into operation

Inserting the batteries/accupack

For powering the diversity receiver, you can either use two 1.5 V AA size batteries or the rechargeable Sennheiser BA 2015 accupack (see "Accessories" on page 24).

- ▶ Open the battery compartment by pushing the two catches ⑪ in the direction of the arrows and open the cover ⑩.



- ▶ Insert the two batteries or the accupack as shown above. Please observe correct polarity when inserting the batteries/accupack.
- ▶ Close the battery compartment by pressing on the center of the cover ⑩.
The battery compartment cover ⑩ locks into place with an audible click.

Charging the accupack

To charge the BA 2015 accupack:


- ▶ Insert the diversity receiver into the L 2015 charger (see "Accessories" on page 24).



The L 2015 charger can only charge the combination BA 2015 accupack/diversity receiver. Standard batteries (primary cells) or individual rechargeable battery cells cannot be charged.


Connecting the earphones


- ▶ Connect the earphones to the socket ②.



The ground connection of the earphones cable serves as the antenna for the second diversity section. For details on the connector assignment, refer to the diagram on page 25.

Attaching the diversity receiver to clothing


You can use the belt clip  to attach the diversity receiver to clothing (e.g. belt, waistband).



The belt clip is detachable so that you can also attach the diversity receiver with the antenna pointing downwards. To do so, withdraw the belt clip from its fixing points and attach it the other way round. The belt clip is secured so that it cannot slide out of its fixing points accidentally.

To detach the belt clip:

- Lift one side of the belt clip as shown.




- Press down the belt clip at one fixing point and pull it out of the receiver housing.
- Repeat for the other side.

Using the diversity receiver

To establish a transmission link, proceed as follows:

1. Switch the diversity receiver on (see next section)
2. Switch a transmitter on (see the instruction manual of the transmitter).

The transmission link is established and the receiver's RF level display "RF"  reacts.






It is vital to observe the notes on frequency selection on page 20.

If you cannot establish a transmission link between transmitter and receiver, read the chapter "Synchronizing an SR 300 IEM G3 transmitter with the diversity receiver" on page 20.



Switching the diversity receiver on/off and adjusting the volume

To switch the diversity receiver on:

- Turn the volume control  clockwise until it clicks.
The red ON LED  lights up. The "Frequency/Name" standard display appears on the display panel.



To switch the diversity receiver off:

- Turn the volume control  counterclockwise until it clicks.
The red ON LED  goes off and the diversity receiver switches off.

To adjust the volume:


CAUTION:



Hearing damage due to high volumes!




Listening at high volume levels for long periods can lead to permanent hearing defects.


- Set the volume to a low level before putting the earphones on.
- Do not continuously expose yourself to high volumes.

- Turn the volume control .

Deactivating the lock mode temporarily


You can activate or deactivate the automatic lock mode via the "Auto Lock" menu item (see page 16). If the lock mode is activated, you have to temporarily deactivate it in order to be able to operate the receiver:







- 
 - ▶ Press the SET button.
"Locked" appears on the display panel.
- 
 - ▶ Press the rocker button.
"Unlock" appears on the display panel.
- 
 - ▶ Press the SET button.
 - When you are in the operating menu, the lock mode remains deactivated until you exit the operating menu.
 - When one of the standard displays is shown, the lock mode is automatically activated after 10 seconds.

The lock mode icon  flashes prior to the lock mode being activated again.



Selecting a standard display

- 
 - ▶ Press the ESC button to select a standard display. In stereo mode (see page 16), you can alternatively press the rocker button.




Contents of the display	Selectable standard display
	"Frequency/Name" with "MUTE" display 
	"Frequency/Limiter" with display of the audio channels (Stereo/Focus) 
	"Frequency/High Boost" with display of the audio channels (Stereo/Focus) 

For more detailed information, refer to the chapter "Overview of the displays" on page 6.


Using the operating menu

A special feature of the Sennheiser ew G3 series is the consistent, intuitive menu structure of transmitters and receivers. As a result, adjustments to the settings can be made quickly – even in stressful situations, for example on stage or during a live show or presentation.

The buttons

Button	Function of the button
Press the ESC button 	<ul style="list-style-type: none"> Selects a standard display (see page 10) Cancels the entry and returns to the current standard display (ESC function)
Press the SET button 	<ul style="list-style-type: none"> Changes from the current standard display to the operating menu Calls up a menu item Enters a submenu Stores the settings and returns to the operating menu
Press the rocker button 	<ul style="list-style-type: none"> In Focus mode: Adjusts the balance (see page 16) In stereo mode: Selects a standard display (see page 10) Changes to the next/previous menu item Changes the setting of a menu item

Overview of the operating menu



Display	Function of the menu item	Page
Main menu "Menu"		14
Squelch	Adjusts the squelch threshold	14
Easy Setup	Scans for unused frequency presets, releases and selects frequency presets	15
Frequency Preset	Sets the frequency bank and the channel	15
Name	Enters a freely selectable name	15
Balance	Adjusts the balance	14
Mode	Selects stereo or Focus mode	14
High Boost	Activates/deactivates the treble boost	16
Auto Lock	Activates/deactivates the automatic lock mode	16
Advanced	Calls up the extended menu "Advanced Menu"	17
Exit	Exits the operating menu and returns to the current standard display	–

Display	Function of the menu item	Page
"Easy Setup"		15
Reset List	Releases all locked frequency presets	15
Current List	Selects an unused frequency preset	15
Scan New List	Scans for unused receiving frequencies (frequency preset scan)	15
Exit	Exits "Easy Setup" and returns to the main menu	—
Extended menu "Advanced Menu"		17
Tune	Sets the receiving frequencies for the frequency banks "U1" to "U6"	17
	Sets the frequency bank, the channel and the receiving frequency (frequency banks "U1" to "U6")	17
Pilot Tone	Activates/deactivates the pilot tone evaluation	18
Limiter	Adjusts the limiter	18
LCD Contrast	Adjusts the contrast of the display panel	19
Reset	Resets the settings made in the operating menu	19
Software Revision	Displays the current software revision	19
Exit	Exits the extended menu "Advanced Menu" and returns to the main menu	—

Working with the operating menu



If the lock mode is activated, you have to deactivate it in order to be able to work with the operating menu (see page 10).

By way of example of the "Frequency Preset" menu, this section describes how to use the operating menu.

Changing from a standard display to the operating menu




- ▶ Press the SET button.
The current standard display is replaced by the main menu.
The last selected menu item is displayed.

Selecting a menu item

- ▼▲ ▶ Press the rocker button to change to the "Frequency Preset" menu item.
The current setting of the selected menu item is displayed:

Menu
Frequency Preset
B.Ch: 1. 1




Changing and storing settings




- ▶ Press the SET button to call up the menu item.




- ▶ Press the rocker button to set the frequency bank.

-  ► Press the **SET** button to confirm your selection.
-  ► Press the rocker button to set the channel.
-  ► Press the **SET** button to store the setting.

Canceling an entry


-  ► Press the **ESC** button to cancel the entry.
The current standard display appears on the display panel.

To subsequently return to the last edited menu item:

-  ► Press the **SET** button repeatedly until the last edited menu item appears.


Exiting a menu item

To return to the next higher menu level:


-  ► Change to the "Exit" menu item.

Menu

Exit

-  ► Confirm your selection.
You return to the next higher menu level.


To directly return to the current standard display:

-  ► Press the **ESC** button.

Adjusting settings via the operating menu

The main menu "Menu"

Adjusting the squelch threshold – "Squelch"



Adjustment range: 5 to 25 dBµV, adjustable in 2-dB steps, can be switched off

The squelch eliminates annoying noise when the transmitter is switched off or when there is no longer sufficient transmitter power received by the receiver.

CAUTION! Danger of hearing damage!



If you switch the squelch off or adjust the squelch threshold to a very low value, loud hissing noise can occur in the receiver. The hissing noise can be loud enough to cause hearing damage!


- ▶ Always make sure that the squelch is switched on.
- ▶ Before adjusting the squelch threshold, set the volume of the headphone output **PHONES** to the minimum (see page 9).
- ▶ Never change the squelch threshold during a live transmission.

- ▶ Adjust the squelch threshold – with the transmitter switched off – to the lowest possible setting that suppresses hissing noise.



A high squelch threshold reduces the transmission range.

The squelch should only be switched off for servicing purposes. With the squelch threshold set to "5 dB", you switch the squelch off by keeping the **DOWN** rocker button pressed for 3 seconds.






If you have accidentally switched off the squelch:

- ▶ Press the **DOWN** rocker button to switch the squelch on.

Scanning for, releasing and selecting frequency presets – “Easy Setup”

Menu item	Function of the menu item
Reset List	Releases all locked frequency presets
Current List	Selects an unused frequency preset
Scan New List	Automatically scans for unused receiving frequencies (frequency preset scan) If receiving frequencies are used, they will be locked; if receiving frequencies are unused, they will be released. After the frequency preset scan, you can select an unused frequency preset.

Selecting the frequency bank and the channel – “Frequency Preset”

Menu		Frequency Preset		Frequency Preset
Frequency Preset		B.Ch: 1 1		B.Ch: 6 3
B.Ch: 1.1		863.100MHz		824.500MHz
Call up “Frequency Preset”		Select the frequency bank and confirm		Select the channel; store the setting
				▲▼
		“Stored”		






When setting up multi-channel systems, please observe the following:

Only the factory-preset receiving frequencies within one frequency bank (“1” to “20”) are intermodulation-free. It is vital to observe the notes on frequency selection on page 20.

Overview of the frequency banks and channels:

Frequency bank	Channels	Type
“1” to “20”	up to 16 per frequency bank	System bank: frequencies are factory-preset
“U1” to “U6”	up to 16 per frequency bank	User bank: frequencies are freely selectable

Entering a name – “Name”


Menu		Name		Name
Name		Lichael		Michael
Lichael				
Call up “Name”		Enter a character and confirm		Enter a character; store the setting
				▲▼
		“Stored”		

Via the “Name” menu item, you can enter a freely selectable name (e.g. the name of the performer) for the receiver. The name is displayed on the “Frequency/Name” standard display (see page 10). The name can consist of up to 8 characters such as:

- letters (without pronunciation marks),
- numbers from 0 to 9,
- special characters and spaces.


To enter a name, proceed as follows:

▼▲ ➤ Press the rocker button to select a character.

 ➤ Press the SET button to change to the next segment/character or to store the complete entry.


Adjusting settings via the operating menu

Adjusting the balance – “Balance”



You can adjust the balance in 31 steps. In Focus mode (see next section) and when one of the standard displays is shown, you can also use the rocker button to adjust the balance. The mode of operation of the balance setting depends on the selected audio mode (see next section).

Switching between “Stereo” and “Focus” mode – “Mode”



The selected audio mode influences the mode of operation of the balance setting (see previous section).

Audio mode	
Stereo	Focus
The left-right signals are available as usual.	The left-right signals are mixed and are available as a mono signal in both headphone channels.
The balance setting serves to adjust the balance between the left and right stereo signal.	The balance setting serves to adjust the relative levels of the two separate channels in the mixed mono signal.


In both audio modes, the corresponding transmitter has to be set to stereo mode!

Activating/deactivating the treble boost – “High Boost”

Via the “High Boost” menu item, you can boost the treble response of the output signal (8 dB at 10 kHz).



Activating/deactivating the automatic lock mode – “Auto Lock”



The lock mode prevents that the balance is accidentally adjusted when the receiver is in Focus mode. In addition, the lock mode prevents accidental switching off or programming during operation. The lock mode icon on the current standard display indicates that the lock mode is activated. For information on how to use the lock mode, refer to page 10.

The extended menu "Advanced Menu"

To get into the extended menu "Advanced Menu":

- From the main menu, select "Advanced".

Setting the receiving frequencies and the frequency banks "U1" to "U6 – "Tune"



When you have selected one of the system banks and then select the "Tune" menu, the diversity receiver automatically switches to channel 1 of the frequency bank "U1". In this case, "U1.1" briefly appears on the display panel.

Upon delivery, the channels of the frequency banks "U1" to "U6" are not assigned a receiving frequency.

Via the "Tune" menu item, you can set a receiving frequency to be stored in the current channel or you can select a different channel in one of the frequency banks "U1" to "U6" and assign this channel a receiving frequency.


Setting a receiving frequency for the current channel

- ▼▲ ► Press the rocker button until the "Tune" menu item appears.



- Press the SET button.

The MHz section of the receiving frequency of the channel is highlighted.



It is vital to observe the notes on frequency selection on page 20.

- ▼▲ ► Press the rocker button to set the MHz section of the frequency.



- Press the SET button to confirm the MHz section of the frequency.

The kHz section of the frequency is highlighted.

- ▼▲ ► Press the rocker button to set the kHz section of the frequency.



- Press the SET button to confirm the frequency.


"Stored" appears on the display panel. The "Tune" menu item appears again.

Selecting a channel and assigning this channel a frequency

- ▼▲ ► Press the rocker button until the "Tune" menu item appears.




- Press the SET button and keep it pressed until the frequency bank is highlighted.



Adjusting settings via the operating menu

- ▼▲ ▶ Press the rocker button to set the frequency bank.
- SET ▶ Press the SET button to confirm the frequency bank.
The channel is highlighted.
- ▼▲ ▶ Press the rocker button to set the channel.
- SET ▶ Press the SET button to confirm the channel.
The frequency (MHz section) is highlighted.
- ▶ Set the desired frequency (MHz and kHz section) as described in the previous chapter.

Activating/deactivating the pilot tone evaluation – “Pilot Tone”




The pilot tone encodes the stereo signal of the transmitter and supports the diversity receiver's squelch function, thus protecting against interference due to RF signals from other devices. When set to stereo operation, the transmitter adds an inaudible pilot tone to the transmitted stereo signal. The receiver detects and evaluates the pilot tone.

- ▶ When the transmitter is set to mono operation, deactivate the pilot tone evaluation.

Display	Meaning
No icon	The pilot tone evaluation is deactivated.
P	The pilot tone evaluation is activated. The receiver does not receive a pilot tone because the transmitter operates in mono mode.
P	The pilot tone evaluation is activated. The receiver receives a pilot tone.

Adjusting the limiter– “Limiter”



CAUTION!



Danger of hearing damage due to a switched-off limiter!


The limiter limits the volume at the headphone output PHONES and thus protects your hearing. With the limiter switched off, the receiver is capable of producing high sound pressure levels. Prolonged exposure to high sound pressure levels can cause permanent hearing defects.

- ▶ Set the limiter to a low level before putting the earphones on.
- ▶ Do not continuously expose yourself to high volumes.

You can adjust the limiter in 6-dB steps from –18 dB to –6 dB or switch it off (OFF).


Adjusting settings via the operating menu

Adjusting the contrast of the display panel – “LCD Contrast”



You can adjust the contrast of the display panel in 16 steps.

Resetting the settings made in the operating menu – “Reset”



When resetting the settings made in the operating menu, only the selected settings for the pilot tone and for the frequency banks “U1” to “U6” remain unchanged. For an overview of the factory-preset default settings, refer to the enclosed frequency information sheet.

Displaying the software revision – “Software Revision”

You can display the current software revision of the diversity receiver.

Synchronizing an SR 300 IEM G3 transmitter with the diversity receiver



When synchronizing the SR 300 IEM G3 transmitter with a diversity receiver, please observe the following:

- ▶ Only use a transmitter and a diversity receiver from the same frequency range (see the type plates on the transmitter and the diversity receiver).
- ▶ Make sure that the desired frequencies are listed in the enclosed frequency information sheet.
You can also contact your Sennheiser partner who will be pleased to calculate intermodulation-free frequencies for you.
- ▶ Make sure that the desired frequencies are approved and legal in your country and, if necessary, apply for an operating license.

Synchronization allows you to quickly and easily transfer transmitter and receiver settings from one device to the other, especially if you want to set up a multi-channel system. There are two transfer directions:

1. **Easy Setup Sync:** Transfer from the receiver to one or several transmitters

Once you have performed a frequency preset scan with a receiver, you use the **Easy Setup Sync** function to transfer unused frequency presets from the receiver to the transmitters. In order to set up a multi-channel system, you use the diversity receiver to transfer the unused channels from the selected frequency bank one after the other to the transmitters, thus ensuring that all transmitters of a multi-channel system operate on intermodulation-free frequencies.

2. **Sync:** Transfer from a transmitter to a receiver

Once you have selected and set the desired receiver settings on the transmitter (either manually or using the **Easy Setup Sync** function), you transfer these settings to a receiver. This configures the receiver and establishes a transmission link between transmitter and receiver.


When carrying out the **Sync** function, the transmitter's current frequency bank and channel setting as well as the receiver parameters adjusted via the "**Sync Settings**" submenu are transferred to the SR 300 IEM G3 receiver via the infra-red interface.

Setting the transmitters to intermodulation-free channels (Easy Setup Sync)

Upon delivery, the SR 300 IEM G3 transmitter and the diversity receiver are synchronized with each other. If, however, you cannot establish a transmission link between transmitter and diversity receiver, you first have to use the diversity receiver to determine intermodulation-free channels and then transfer these channels to the transmitters. In doing so, no transmission links are established.

- ▶ On all transmitters, call up the "**Easy Setup**" menu item.
"**Easy Setup Sync**" appears on the display panels of the transmitters. The RF signals of the transmitters are deactivated. The transmitters await the transfer of a channel and a frequency bank via their infra-red interfaces.
- ▶ With a diversity receiver, perform a frequency preset scan to scan the frequency banks for unused channels ("**Scan New List**", see page 15).
- ▶ Select a frequency bank with a sufficient number of unused channels and a channel on this receiver ("**Current List**", see page 15).

- ▶ Start the Easy Setup Sync function by placing the infra-red interface of this diversity receiver in front of the infra-red interfaces ④ of all transmitters, one after the other.



The diversity receiver transfers an unused channel from the selected frequency bank to the first transmitter and the next unused channel to the second transmitter and so on. As soon as a transfer is completed, the display panel of the transmitter displays the numbers of the transferred frequency bank and channel.

Synchronizing transmitters with diversity receivers (Sync)


In a second step, you transfer the frequency bank and channel settings from the transmitters to other diversity receivers (synchronization) and thus establish the transmission links.

If you want to carry out synchronization at a later time:

- ▶ Press the jog dial on the transmitter.
The frequency bank and the channel are stored. The transmitter's RF signal is activated again. You can synchronize this transmitter with a diversity receiver at any time (see the instruction manual of the transmitter).

To carry out synchronization immediately:

- ▶ Start the Sync function by placing the infra-red interface of the first diversity receiver in front of the infra-red interface ④ of the first transmitter while simultaneously pressing the SYNC button ③ on the transmitter.



The diversity receiver is set to the same frequency bank and channel as the transmitter. The transmitter's RF signal is activated again. A transmission link is established between the first transmitter and the first diversity receiver.

- ▶ Synchronize each of the remaining transmitters with one of the remaining diversity receivers.
Your multi-channel monitoring system is now ready for operation.

Instead of synchronizing, you can manually set the transmitters to the same frequency bank and channel that you set on the corresponding diversity receivers.

Using freely selectable receiving frequencies

You can also freely select the receiving frequencies and store these frequencies in the frequency banks "U1" to "U5".



It might be that the freely selected frequencies are not intermodulation-free

If you are using frequencies from the frequency banks "U1" to "U5", it might be that the receiving frequencies are not intermodulation-free.

- ▶ Contact your Sennheiser partner who will be pleased to calculate intermodulation-free frequencies for you (see www.sennheiser.com).

- ▶ Set each diversity receiver to the same frequency bank ("U1" to "U5").

Cleaning the diversity receiver

- ▶ On one of the receivers, select a channel within this frequency bank and assign this channel a receiving frequency (see page 17).
 - ▶ Synchronize a transmitter with this receiver (see the instruction manual of the transmitter).
- OR:
- ▶ Manually set the transmitter to the same frequency bank and channel that you set on the receiver.
 - ▶ Repeat for the remaining transmitters and receivers as described above.

Cleaning the diversity receiver

-
- CAUTION!** Liquids can damage the electronics of the receiver!
Liquids entering the housing of the device can cause a short-circuit and damage the electronics.
- ▶ Keep all liquids away from the receiver.
 - ▶ Do not use any solvents or cleansing agents.
-

- ▶ Use a cloth to clean the diversity receiver from time to time.

Recommendations and tips

... for the diversity receiver

- Make sure that the antenna and the earphones cable do not cross.
- For best results, make sure that the transmitter sensitivity is correctly adjusted.

... for optimum reception

- Transmission range depends to a large extent on location and can vary from about 10 m to about 150 m. There should be a "free line of sight" between transmitting and receiving antennas.
- To avoid overloading the receiver, observe a minimum distance of 5 m between transmitting and receiving antennas.

... for multi-channel operation

- When operating a multi-channel system, you should only use the channels within one frequency bank. Each of the frequency banks "1" to "20" accommodates factory-preset frequencies which are intermodulation-free.
- The frequency banks "U1" to "U6" allow you to freely select and store receiving frequencies (see page 17).
- When using several transmitters simultaneously, interference can be avoided by maintaining a minimum distance of 20 cm between two transmitters.

If a problem occurs ...

Problem	Possible cause	Possible solution
Diversity receiver cannot be operated, "Locked" appears on the display panel	Lock mode is activated	Deactivate the lock mode (see page 10).
No operation indication	Batteries are flat or accupack is flat	Replace the batteries or recharge the accupack (see page 7).
No RF signal	Transmitter and receiver are not on the same channel	Set the transmitter and receiver to the same channel. Synchronize the transmitter with the receiver (see page 20).
	Transmission range is exceeded	Check the squelch threshold setting (see page 14). Reduce the distance between transmitter and receiver.
	RF signal is deactivated ("RF Mute")	Activate the RF signal (see the instruction manual of the transmitter).
	Transmitter is muted	Cancel the muting (see the instruction manual of the transmitter).
RF signal available, no audio signal, "MUTE" appears on the display panel	Receiver's squelch threshold is adjusted too high	Reduce the squelch threshold setting (see page 14).
	SR 300 IEM transmitter is set to mono operation and therefore doesn't transmit a pilot tone	Deactivate the pilot tone evaluation (see page 18).
	SR 300 IEM transmitter is set to stereo operation and therefore transmits a pilot tone	Activate the pilot tone evaluation (see page 18).
Audio signal has a high level of background noise	Transmitter sensitivity is adjusted too low	Adjust the transmitter sensitivity correctly (see the instruction manual of the transmitter).
Audio signal is distorted	Transmitter sensitivity is adjusted too high	Adjust the transmitter sensitivity correctly (see the instruction manual of the transmitter).
No access to a certain channel	During scanning, an RF signal has been detected on this channel and the channel has been locked	Set the transmitter operating on this channel to a different channel and redo the frequency preset scan (see page 15).
	During scanning, a transmitter of your system operating on this channel has not been switched off	Switch the transmitter off and redo the frequency preset scan (see page 15).

If a problem occurs that is not listed in the above table or if the problem cannot be solved with the proposed solutions, please contact your local Sennheiser partner for assistance.

To find a Sennheiser partner in your country, search at www.sennheiser.com under "Service & Support".

Accessories

The following EK 300 IEM G3 accessories are available from your specialist dealer:

Cat. No.	Accessory
009950	BA 2015 accupack
009828	L 2015 charger
500432	IE 4 earphones

Specifications

RF characteristics

Modulation	wideband FM
Frequency ranges	516–558, 566–608, 626–668, 734–776, 780–822, 823–865 MHz (A to E, G, see page 3)
Receiving frequencies	1,680 frequencies, tuneable in steps of 25 kHz 20 frequency banks, each with up to 16 factory-preset channels 6 frequency banks, each with up to 16 user programmable channels
Switching bandwidth	42 MHz
Nominal/peak deviation	± 24 kHz/ ± 48 kHz
Receiver principle	adaptive diversity
Sensitivity (with HDX, peak deviation)	< 4 μ V, typ. 1.6 μ V for 52 dBA _{rms} S/N
Adjacent channel rejection	typ. ≥ 65 dB
Intermodulation attenuation	typ. ≥ 70 dB
Blocking	≥ 80 dB
Squelch	Off, 5 to 25 dB μ V, adjustable in steps of 2 dB
Pilot tone squelch	can be switched off

AF characteristics

Compander system	Sennheiser HDX
S/N ratio (1 mV, peak deviation)	approx. 90 dB
THD	$\leq 0.9\%$
Output power at 2.4 V, 5 % THD, nominal deviation	2 x 100 mW at 32 Ω
High Boost	+8 dB at 80 kHz
Limiter	–18 dB to –6 dB, adjustable in steps of 6 dB, can be switched off



Overall device

Temperature range	–10°C to +55°C
Power supply	2 AA size batteries, 1.5 V or BA 2015 accupack
Nominal voltage	2.4 V ---
Power consumption:	
• at nominal voltage	approx. 140 mA
• with switched-off receiver	≤ 25 μ A

Manufacturer Declarations

Operating time	approx. 4 to 6 hrs (depending on volume level)
Dimensions	approx. 82 x 64 x 24 mm
Weight (incl. batteries)	approx. 125 g

in compliance with


Europe	 EMC: EN 301489-1/-9 Radio: EN 300422-1/-2 Safety: EN 60065
USA	 47 CFR 15 subpart B

Approved by

Canada	Industry Canada RSS 123 IC 2099A-G3SREK300 limited to 806 MHz
--------	---

Connector assignment

3.5 mm Jack plug



Manufacturer Declarations

Warranty

Sennheiser electronic GmbH & Co. KG gives a warranty of 24 months on this product.

For the current warranty conditions, please visit our web site at www.sennheiser.com or contact your Sennheiser partner.

In compliance with the following requirements

- RoHS Directive (2002/95/EC)
- WEEE Directive (2002/96/EC)



Please dispose of the diversity receiver at the end of its operational lifetime by taking it to your local collection point or recycling center for such equipment.

- Battery Directive (2006/66/EC)



The supplied batteries or rechargeable batteries can be recycled. Please dispose of them as special waste or return them to your specialist dealer. In order to protect the environment, only dispose of exhausted batteries.

CE Declaration of Conformity

- **CE 0682**

- R&TTE Directive (1999/5/EC)

The declarations are available at www.sennheiser.com.

Before putting the device into operation, please observe the respective country-specific regulations.

Manufacturer Declarations

Statements regarding FCC and Industry Canada

This device complies with Part 15 of the FCC Rules and with RSS-210 of Industry Canada. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.


This class B digital device complies with the Canadian ICES-003.

Changes or modifications made to this equipment not expressly approved by Sennheiser electronic Corp. may void the FCC authorization to operate this equipment.

Before putting the device into operation, please observe the respective country-specific regulations!


Index

- Accessories 24
- Accupack
 - charging 7
 - inserting 7
- Advanced Menu (extended menu)
 - overview 12
 - settings 17
- Auto Lock (activating/deactivating the lock mode) 16
- Balance (adjusting the balance) 16
- Batteries
 - battery status 6
 - inserting 7
- Buttons
 - ESC button 5
 - function of the ~ 11
 - SET button 5
 - UP/DOWN button 5
- Channel
 - assigning a frequency 17
 - selecting 15
 - setting a frequency 17
- Displays
 - adjusting the contrast of the display panel (LCD Contrast) 19
 - AF (audio level) 6
 - LOW BATT 6
 - MUTE 6
 - overview 6
 - RF (RF level) 6
 - standard displays 10
- Earphones, connecting 7
- Easy Setup (scanning for, releasing and selecting frequency presets) 15
- Frequency bank
 - selecting 15
 - setting a frequency 17
 - ~ system 3
- Frequency Preset (selecting a frequency bank/channel) 15
- Frequency presets
 - releasing (Reset List) 15
 - searching for unused ~ (Scan New List) 15
 - selecting (Current List) 15
- High Boost (activating/deactivating the treble boost) 16
- LCD Contrast (adjusting the contrast of the display panel) 19
- Limiter (adjusting the limiter) 18
- Lock mode
 - activating/deactivating (Auto Lock) 16
 - deactivating temporarily 9
 - lock mode icon 6
- Locked 10
- LOW BATT 5
- Menu (main menu)
 - overview 11
 - settings 14
- Mode (switching between stereo and Focus mode) 16
- Name (entering a name) 15
- Operating menu
 - overview 11
 - settings 14
 - using 12
- Pilot Tone (activating/deactivating the pilot tone evaluation) 18
- Receiver
 - adjusting the volume 9
 - cleaning 22
 - switching off 9
 - switching on 9
- Reset (resetting the settings made in the operating menu) 19
- RF signal indication 5
- Software Revision (displaying the software revision) 19
- Squelch (adjusting the squelch) 14
- Transmitter (synchronizing with receiver) 20
- Troubleshooting 23
- Tune (setting the receiving frequencies and frequency banks) 17



Sennheiser electronic GmbH & Co. KG
Am Labor 1, 30900 Wedemark, Germany
www.sennheiser.com

Printed in Germany
Publ. 01/09
529681/A01




evolution wireless 

PC HP ProDesk 400 G4 de formato pequeño



La HP ProDesk 400 SFF, pensada para el ámbito laboral moderno y del futuro es una PC pequeña, potente, confiable y segura, con rendimiento optimizable para que crezca junto con su empresa.



HP recomienda Windows 10 Pro.

Opciones potentes

Afronte el día con procesadores de alto rendimiento de 7a generación Intel® Core™ i3/i5/i7[®]; el gran potencial de las unidades de estado sólido y las memorias opcionales Intel® Optane™, hasta 32 GB de memoria DDR4⁺ y gráficos independientes⁺.

Expansión que amplía los beneficios de su inversión

Su inversión alcanza el máximo de rentabilidad con la expansión que amplía la vida útil de la PC. La HP ProDesk 400 SFF tiene dos bahías, dos ranuras de media altura y puertos antiguos opcionales⁺.

Concentrador de conexión



La HP ProDesk 400 SFF, con 8 puertos USB, dos salidas de video y conectividad Bluetooth™ opcional⁺, se convierte en un concentrador para todos los dispositivos de la oficina.

Probada y preparada

La confiable HP ProDesk 400 SFF superó 120.000 horas de pruebas de HP Total Test Process y ahora cuenta con un filtro de polvo opcional⁺ para ampliar la vida útil de su PC, al reducir el ingreso de partículas aéreas en los entornos laborales más exigentes.

- Afronte su día con Windows 10 Pro⁺ y la potente HP ProDesk 400 SFF, de seguridad, colaboración y conectividad incorporadas.
- HP Client Security Suite Gen3⁺ cuenta con HP Multi-Factor Authenticate, HP Device Access Manager⁺, HP SpareKey y HP Password Manager. Estas herramientas se encargan de guardar los datos fuera del alcance y protegerlos de robos, ataques y usuarios no autorizados.
- Tenga mucha productividad y poco tiempo de inactividad con la automatización de nivel de firmware de HP BIOSphere Gen3⁺. Sus PC tienen protección adicional gracias a las actualizaciones automáticas y los controles de seguridad.
- El kit HP Manageability Integration⁺ ayuda a acelerar la creación de imágenes y la administración del hardware, el BIOS y la seguridad mediante Microsoft System Center Configuration Manager.
- HP WorkWise[®] es la inteligencia de oficina resumida en una aplicación de teléfono inteligente, para brindar seguridad, información de rendimiento en tiempo real e instalación simplificada de controladores de impresión para los usuarios de PC HP.
- Acelere en gran medida la transferencia de datos y la comunicación de voz y video al conectarse por redes LAN y Wi-Fi limitadas con HP Velocity.
- Disfrute del soporte autoservicio incluido, siempre disponible, integrado en su PC para toda su vida útil⁺.
- Duerma tranquilo con una PC que cumple con las expectativas y está diseñada para superar las pruebas de HP Total Test Process.
- Las conexiones de audio son sencillas con la toma de audio universal, que admite auriculares, micrófonos y auriculares con micrófono CTIA.
- HP Touchpoint Manager ofrece a los clientes herramientas y servicios simples y útiles desde una misma solución en la nube para administrar los datos, la seguridad y una amplia gama de dispositivos de marca[™].
- Simplifique el soporte técnico con Helpdesk de HP Care. Confíe en la asistencia rentable de expertos disponibles 24 x 7 y que cubre varias marcas, dispositivos y sistemas operativos⁺.
- Optimice el flujo de efectivo con una suscripción mensual de servicios y hardware del mejor nivel de su clase, y que le permite sustituir su PC con una nueva cada tres años⁺.

PC HP ProDesk 400 G4 de formato pequeño Tabla de especificaciones



Factor de forma	Factor de pequeño formato
Sistema operativo disponible	Windows 10 Pro 64 – HP recomienda Windows 10 Pro. ¹ Windows 10 Home 64 ¹ Windows 10 Pro 64 (licencia National Academic) ² Windows 10 Home en un idioma 64 ¹ Windows 7 Professional 64 (disponible mediante derechos de retroceso de versión de Windows 10 Pro) ³ FreeDOS 2.0 NeoKylin Linux® 64 ⁴⁰
Familia de procesador⁴⁵	Procesador Intel® Core™ i3 de 7ª generación (modelos i3-7100, i3-7300, i3-7320); Procesador Intel® Core™ i5 de 7ª generación (modelos i5-7500, i5-7600); Procesador Intel® Core™ i7 de 7ª generación (modelo i7-7700); Procesador Intel® Pentium® de 7ª generación (modelos G4560, G4600, G4620); Procesador Intel® Celeron® de 7ª generación (modelos G3930, G3950); Procesador Intel® Core™ i7 de 6ª generación (modelo i7-6700); Procesador Intel® Core™ i3 de 6ª generación (modelo i3-6100); Procesador Intel® Core™ i5 de 6ª generación (modelo i5-6500)
Procesadores disponibles	Intel® Core™ i7-7700 con gráficos Intel HD 630 (3,6 GHz, hasta 4,2 GHz con Intel Turbo Boost, 8 MB de caché, 4 núcleos); Intel® Core™ i5-7500 con gráficos Intel HD 630 (3,4 GHz, hasta 3,8 GHz con Intel Turbo Boost, 6 MB de caché, 4 núcleos); Intel® Core™ i5-7600 con gráficos Intel HD 630 (3,5 GHz, hasta 4,1 GHz con Intel Turbo Boost, 6 MB de caché, 4 núcleos); Intel® Core™ i3-7100 con gráficos Intel HD 630 (3,9 GHz, 3 MB de caché, 2 núcleos); Intel® Core™ i3-7300 con gráficos Intel HD 630 (4 GHz, 4 MB de caché, 2 núcleos); Intel® Core™ i3-7320 con gráficos Intel HD 630 (4,1 GHz, 4 MB de caché, 2 núcleos); Intel® Pentium® G4560 con gráficos Intel HD 610 (3,5 GHz, 3 MB de caché, 2 núcleos); Intel® Pentium® G4600 con gráficos Intel HD 630 (3,6 GHz, 3 MB de caché, 2 núcleos); Intel® Pentium® G4620 con gráficos Intel HD 630 (3,7 GHz, 3 MB de caché, 2 núcleos); Intel® Celeron™ G3930 con gráficos Intel HD 610 (2,9 GHz, 2 MB de caché, 2 núcleos); Intel® Celeron™ G3950 con gráficos Intel HD 610 (3 GHz, 2 MB de caché, 2 núcleos); Intel® Core™ i7-6700 con gráficos Intel HD 530 (3,4 GHz, hasta 4,0 GHz con Intel Turbo Boost, 8 MB de caché, 4 núcleos); Intel® Core™ i5-6500 con gráficos Intel HD 530 (3,2 GHz, hasta 3,6 GHz con Intel Turbo Boost, 6 MB de caché, 4 núcleos); Intel® Core™ i3-6100 con gráficos Intel HD 530 (3,7 GHz, 3 MB de caché, 2 núcleos) ^{41,42} <small>Su producto no es compatible con Windows 8 ni Windows 7. En conformidad con la política de compatibilidad de Microsoft, HP no admite el sistema operativo Windows 8 ni Windows 7 en los productos configurados con procesadores Intel y AMD de 7ª generación en adelante ni ofrece controladores para Windows 8 ni Windows 7 en http://www.support.hp.com.</small>
Chipset	Intel® H270
Memoria máxima	32 GB de SDRAM DDR4-2400 ⁴⁶ (Velocidades de transferencia de hasta 2400 MT/s)
Ranuras de memoria	2 DIMM
Almacenamiento interno	500 GB Hasta 2 TB Disco duro SATA de 3,5" (7200 rpm) ⁴⁷ 500 GB Hasta 1 TB Disco duro de estado sólido SATA de 2,5" (5400 rpm) ⁴⁸ Hasta 1 TB Disco duro de estado sólido SATA de 3,5" (7200 rpm) ⁴⁹ 256 GB Hasta 512 GB Unidad de estado sólido SATA con autocifrado de 2,5" ⁴⁷ 256 GB Hasta 1 TB Unidad de estado sólido TLC NMVe HP Turbo Drive G2 (PCIe) ⁴⁹ 128 GB Hasta 512 GB SSD SATA ⁴⁷
Gráficos disponibles	Integrada: Gráficos Intel® HD 530; gráficos Intel® HD 630; gráficos Intel® HD 610 ^{50,51} Discreto: NVIDIA® GeForce® GT730 HDMI (1 GB); NVIDIA® GeForce® GT730 (2 GB)
Audio	Códec Conexant CX20632 con toma de audio universal y altavoz interno de 2 W, puertos frontales para auriculares (3,5 mm) y compatibilidad con transmisión múltiple
Comunicaciones	LAN: Conexión de red GbE LOM Realtek RTL8111 HSH WLAN (opcional): Tarjeta combinada M.2 inalámbrica 802.11ac (2x2) con Bluetooth® Intel® 7265 no vPro™; Tarjeta combinada M.2 inalámbrica 802.11ac (1x1) con Bluetooth® Intel® 3168 no vPro™ ⁴⁸
Ranuras de expansión	Turbo Drive (M.2 PCIe); 1 M.2 2230 para NIC inalámbrica; PCI Express x16 (v3.0) (cableado como x4) de 2,5" de bajo perfil, longitud de 6,6" y 35 W de potencia máxima; PCI Express x16 (v3.0) de 2,5" de bajo perfil, longitud de 6,6" y 35 W de potencia máxima
Puertos y Conectores	Adelante: 1 lector de 3 tarjetas SD (opcional); 1 conector para auriculares; 2 USB 3.1 Gen 1 Atrás: 1 conector de entrada de audio; 1 RJ-45; 1 conector de salida de audio; 1 DisplayPort™; 1 VGA; 4 USB 2.0; 2 USB 3.1 Gen 1; 1 conector de alimentación Posterior (opcional): 1 puerto PS/2; 1 serie ¹⁸
Compartimientos para unidades internas	Una unidad de discos ópticos delgada de 9 mm; Lector de 3 tarjetas Secure Digital (SD)
Software disponible	Los PC empresariales HP traen una serie de títulos de software como: Compatibilidad nativa con Miracast, controlador de HP ePrint + Jet Advantage, HP Hotkey Support, HP Recovery Manager, HP Support Assistant. Consulte el documento de especificaciones rápidas de este producto para ver una lista completa del software preinstalado. ^{11,14}
Gestión de la seguridad	Chip de seguridad incorporado Trusted Platform Module TPM 2.0 (SLB9670 – Certificación Common Criteria EAL4+); Desactivación de puertos SATA 0,1 (mediante BIOS); Bloqueo de unidades; Activación/Desactivación de serie y USB (mediante BIOS); Contraseña de encendido (mediante BIOS); Contraseña de configuración (mediante BIOS); Compatibilidad con candados comunes y de cable para chasis

Características de gestión	Catálogo de clientes HP; LANDESK Management; HP SoftPaq Download Manager (SDM); HP System Software Manager (SSM); Utilidad de configuración del BIOS HP (BCU); HP MIB para Microsoft SCCM [15, 22]
Alimentación	80 PLUS Bronze: 180 W, hasta 85% de eficiencia, PFC activa
Dimensiones	3,7 x 11,7 x 10,6 pulg. 9,5 x 29,6 x 27 cm (Las dimensiones son para la orientación de torre)
Peso	10,14 lb 4,6 kg (El peso exacto depende de la configuración)
Conformidad de eficiencia de energía	Configuraciones con certificación ENERGY STAR® y registro EPEAT® disponibles ¹⁶