


INSTRUCTION MANUAL

600TV Lines Super High Resolution Color Camera



3-AXIS INFRARED - LED PLASTIC
DOME CAMERA

*Please read this manual thoroughly before use, and keep it handy for future reference.
Design and specifications are subject to change without notice.*

WARNING

TO REDUCE THE RISK OF FIRE OR ELECTRIC SHOCK, DO NOT EXPOSE THIS PRODUCT TO RAIN OR MOISTURE. DO NOT INSERT ANY METALLIC OBJECTS THROUGH THE VENTILATION GRILLS OR OTHER OPENINGS ON THE EQUIPMENT.

CAUTION



EXPLANATION OF GRAPHICAL SYMBOLS



The lightning flash with arrowhead symbol, within an equilateral triangle, is intended to alert the user to the presence of uninsulated "dangerous voltage" within the product's enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons.



The exclamation point within an equilateral triangle is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the product.

PRECAUTIONS

Installation -----

Do not install the unit in an extremely hot or humid place or in a place subject to excessive dust, mechanical vibration.

Cleaning -----

Clean the unit with a slightly damp soft cloth. Use a mild household detergent. Never use strong solvents such as thinner or benzine as they might damage the finish of the unit.

Retain the original carton and packing materials for safe transport of this unit in the future.

FCC COMPLIANCE STATEMENT

FCC INFORMATION : THIS EQUIPMENT HAS BEEN TESTED AND FOUND TO COMPLY WITH THE LIMITS FOR A CLASS A DIGITAL DEVICE, PURSUANT TO PART 15 OF THE FCC RULES. THESE LIMITS ARE DESIGNED TO PROVIDE REASONABLE PROTECTION AGAINST HARMFUL INTERFERENCE WHEN THE EQUIPMENT IS OPERATED IN A COMMERCIAL ENVIRONMENT. THIS EQUIPMENT GENERATES, USES, AND CAN RADIATE RADIO FREQUENCY ENERGY AND IF NOT INSTALLED AND USED IN ACCORDANCE WITH THE INSTRUCTION MANUAL, MAY CAUSE HARMFUL INTERFERENCE TO RADIO COMMUNICATIONS. OPERATION OF THIS EQUIPMENT IN A RESIDENTIAL AREA IS LIKELY TO CAUSE HARMFUL INTERFERENCE IN WHICH CASE THE USER WILL BE REQUIRED TO CORRECT THE INTERFERENCE AT HIS OWN EXPENSE.

CAUTION : CHANGES OR MODIFICATIONS NOT EXPRESSLY APPROVED BY THE PARTY RESPONSIBLE FOR COMPLIANCE COULD VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT.

THIS CLASS A DIGITAL APPARATUS COMPLIES WITH CANADIAN ICES-003.

CET APPAREIL NUMÉRIQUE DE LA CLASSE A EST CONFORME À LA NORME NMB-003 DU CANADA.

CE COMPLIANCE STATEMENT

WARNING

THIS IS A CLASS A PRODUCT. IN A DOMESTIC ENVIRONMENT THIS PRODUCT MAY CAUSE RADIO INTERFERENCE IN WHICH CASE THE USER MAY BE REQUIRED TO TAKE ADEQUATE MEASURES.

IMPORTANT SAFETY INSTRUCTIONS

1. Read these instructions.
2. Keep these instructions.
3. Heed all warnings.
4. Follow all instructions.
5. Do not use this apparatus near water.
6. Clean only with dry cloth.
7. Do not block any ventilation openings. Install in accordance with the manufacturer's instructions.
8. Do not install near any heat sources such as radiators, heat registers, stoves, or other apparatus (including amplifiers) that produce heat.
9. Do not defeat the safety purpose of the polarized or grounding-type plug. A polarized plug has two blades with one wider than the other. A grounding type plug has two blades and a third grounding prong. The wide blade or the third prong are provided for your safety. If the provided plug does not fit into your outlet, consult an electrician for replacement of the obsolete outlet.
10. Protect the power cord from being walked on or pinched particularly at plugs, convenience receptacles, and the point where they exit from the apparatus.
11. Only use attachments/accessories specified by the manufacturer.
12. Use only with the cart, stand, tripod, bracket, or table specified by the manufacturer, or sold with the apparatus.
When a cart is used, use caution when moving the cart/apparatus combination to avoid injury from tip-over.

13. Unplug this apparatus during lightning storms or when unused for long periods of time.
14. Refer all servicing to qualified service personnel. Servicing is required when the apparatus has been damaged in any way, such as power-supply cord or plug is damaged, liquid has been moisture, does not operate normally, or has been dropped.
15. **CAUTION THESE SERVICING INSTRUCTIONS ARE FOR USE BY QUALIFIED SERVICE PERSONNEL ONLY. TO REDUCE THE RISK OF ELECTRIC SHOCK DO NOT PERFORM ANY SERVICING OTHER THAN THAT CONTAINED IN THE OPERATING INSTRUCTIONS UNLESS YOU ARE QUALIFIED TO DO SO.**
16. Use satisfy clause 2.5 of IEC60950-1/UL60950-1 or Certified/Listed Class 2 power source only.


INTRODUCTION

The camera provides high-quality images using Sony CCD technology especially designed for closed-circuit television (CCTV) and security surveillance applications.

Features:

- High resolution and high performance Sony® Super HAD™ II Technology
- Excellent picture quality
- 600 lines(Color) of resolution
- 0.1 lux(Color), 0 lux(B/W, IR LED ON) @ F1.2 50IRE Sensitivity
- Auto electronic shutter [1/60(1/50) ~ 1/100,000] and manual electronic shutter modes
- OSD (On Screen Display)
- Auto and manual white balance modes
- DWDR
- OSD Font Color (16 Color)
- BLC (Back Light Compensation)
- Smart IR
- 30EA, 850mm IR LED
- Day&Night (Auto / DAY / NIGHT / EXT)
- Private Mask (8 position, 16 Colors)
- AGC (Auto Gain Control)
- MIRROR (ON/OFF)
- VIDEO OUT BNC
- Motion Detection(4 point)
- HLC (High Light Compensation)
- DPC (Dead Pixel Cancellation)
- 2.8~12mm A/I Varifocal Lens F1.2 (D&N Lens option)
- 9~22mm A/I Varifocal Lens F1.4 (D&N Lens option)
- 4~9mm A/I Varifocal Lens F1.6 (D&N Lens option)
- Operates in AC24V +/- 10% / DC12V +/- 10%
- Use Certified / Listed Class 2 power source only
- Test monitor Output
- Camera Mount : camera mount directly to the wall or ceiling

CAMERA CONNECTIONS



- 1. Lens :** A/I Vari-focal lens for wide area monitoring. (D&N with ICR model option)
- 2. Power :** 24V AC input / 12V DC input
power source from a DC 12V or AC 24V ac +/-10% 60/50Hz +/-1Hz
Use Certified/ Listed Class 2 power source only.
*If using DC 12V power adaptor,
use a power supply capable of supplying 7 Watts.
- 3. Video :** BNC connector used to connect the camera to a monitor, switcher, etc.



REMINDER:

Never aim the camera directly into the sun.


CONTENTS of PACKAGE

The package contains the following.


Camera in Housing.....	1
Instruction Manual (This Document).....	1
Accessory Kit for Installing.....	1
Drilling guide label.....	1

BASE INSTALLATION

1. Make mounting holes and cable hole in the place (ceiling or wall) to which this dome camera is installed using the Drilling guide label.




2. To remove dome cover, turn the dome body counterclockwise until locators reach end of travel and pull off.
Push the liner on the sides where the patterns are put in the teeth of a comb and pull it out.




3. Attach the housing to the ceiling using suitable fasteners, M6x35 tapping screws are supplied only use if they are suitable.
Turn the housing to right direction about 16 degrees to lock in place.
4. The assembly of the dome body and liner is in reverse order of disassembly.
Finally, lock dome body with locking screw(M3X5) from the accessory kit.

- Video out check-




STRUCTURE OF THE SETUP MENU



LENS (Selection)

This function is used to adjust the brightness of the screen.

1. When the SETUP menu is displayed on the screen, please position the arrow to point to 'LENS' by using the UP and DOWN buttons.
2. Please select the type of the lens you wish to use by pressing the LEFT or RIGHT button.




Note The brightness of the screen can be adjusted in DC mode.

EXPOSURE

The EXPOSURE menu is used to set the automatic light control method for this camera.

- 1) SHUTTER Select the shutter mode.(Auto,1/60(50), FLK~ 1/100,000 sec)
Can be changed while in shutter mode.
- 2) BRIGHTNESS Adjust BRIGHTNESS level (0 ~ 255)
Can be adjusted while in DC/ manual lens mode.
- 3) AGC Auto gain control (OFF / LOW / MIDDLE / HIGH)
- 4) DWDR Digital Wide dynamic range(Xtended Dynamic Range)
OFF / ON



WHITE BAL

The screen color can be adjusted by using the WHITE BALANCE function.

1) ATW1

Set the color temperature 2500°K 10000°K

2) ATW2

Set the color temperature 2000°K 13000°K

3) AWC -> SET

Please press the ENTER button while the camera is directed at a piece of white paper to obtain the optimum state under current illumination. If the environment including the light source is changed, you have to adjust the white balance again.

4) MANUAL

Manual mode. User can change R and B Gain manually.



INDOOR

Set the color temperature to 3200°K

OUTDOOR

Set the color temperature to 6300°K

<WHITE BAL MANUAL MODE>



BACKLIGHT



1) BLC

Prevents such a back light effect to secure a clear image under all illumination environments

2) HLC

The function improves the identification capability of subjects facing a brightly lit situation by filtering out the strength of the light

<BACKLIGHT MODE>




DAY NIGHT


The DAY/NIGHT menu is used to configure the day and night related setting for this camera. This camera can turn the IR(infrared)filter on or off.

Mode : AUTO / COLOR / B/W / EXT (The EXT is not operating in this mode)

<DAY NIGHT AUTO MODE>




<DAY NIGHT B/W MODE>



The IR LEVEL is not operating in DAY NIGHT B/W mode.

DPC

DPC Auto setting (Dead pixels are automatically removed)



SPECIAL

1) CAM TITLE


A —— **CAM TITLE**
0123456789
ABCDEFGHIJK
LMNOPQRSTUVWXYZ
B —— WXYZ ►→←↑↓()
~_■/= & : ~, ↴
C —— C L R P O S

A. CAM TITLE
B. Character Table
C. Command Line

: Move to left
: Move to right
CLR : Erase all characters
POS: Move the position of title
END : Save and End

2) MOTION


AREA SELECT Select MD area number. (AREA1 ~AREA4)
AREA STATE Select MD ON/OFF
HEIGHT Adjust height of MD area
WIDTH Adjust width of MD area
LEFT/RIGHT Adjust the location of the MD area with boundary LEFT and RIGHT.
TOP/BOTTOM Adjust the location of the MD area with boundary TOP and BOTTOM
DEGREE Adjust sensitivity of MD area.(0~255)
VIEW The screen displays with pink dots. When a motion is detected in the selected area, the pink dots are displayed on the screen.



3) PRIVACY


AREA SELECT	Select MASK area number.(Area 1 ~ Area 8)
AREA STATE	Select MASK ON/OFF
HEIGHT	Adjust height of MASK area
WIDTH	Adjust width of MASK area
LEFT/RIGHT	Adjust the location of the MASK area with boundary LEFT and RIGHT
TOP/BOTTOM	Adjust the location of the MASK area with boundary TOP and BOTTOM.
COLOR	Select MASK color. (0~15)
RETURN	

<PRIVACY MODE>



4) PARK.LINE

Select Parking area



5) LANGUAGE

ENGLISH or CHINESE

6) RETURN

RET

IMAGE ADJUST

1) LENS SHAD	Adjust Lens shading level (0~255)
2) 2DNR	Select 2DNR ON/OFF
3) MIRROR	Select MIRROR ON/OFF
4) FONT COLOR	Select FONT COLOR level (0~15)
5) CONTRAST	Select IDR TITLE level (0~15)
6) SHARPNESS	Adjust CONTRAST level (0~255)
7) DISPLAY	Adjust SHARPNESS level (0~31)
8) NEG. IMAGE	Select DISPLAY mode (CRT /LCD/USER)
	Select Negative image mode ON /OFF

<IMAGE ADJUST MODE>





IMAGE ADJUST	
LENS SHAD	ON ↴
2DNR	ON
MIRROR	OFF
FONT COLOR	↓
CONTRAST	122
SHARPNESS	21
? DISPLAY	CRT ↴
NEG.IMAGE	OFF
RETURN	RET ↴



CRT ADJUST	
? PED LEVEL	022
COLOR GAIN	192
RETURN	RET ↴

LCD AJUST	
? GAMMA	0.50
PED LEVEL	028
COLOR GAIN	160
RETURN	RET ↴

USER AJUST	
? GAMMA	0.45
PED LEVEL	028
COLOR GAIN	160
RETURN	RET ↴

RESET

1) FACTORY

Returns to the level which was set by the manufacturer for shipment.

EXIT


1) EXIT

Saves all settings and exits.

LENS ADJUSTMENT (OPTIONAL VARIFOCAL LENS)


Field of view: Adjust setting from Tele (T) to Wide (W) field of View.

Focus: Adjust lens focus from near (N) to infinity (∞).



DC AUTO IRIS LENS

	2.8-12mm	9-22mm	4-9mm
Image Size	1/3" CCD	1/3" CCD	1/3" CCD
Focal Length	2.8-12mm \pm 5%	9-22mm \pm 5%	4-9mm \pm 5%
Aperture Ratio	1 : 1.2 \pm 5%	1 : 1.4 \pm 5%	1 : 1.6 \pm 5%
Angular Field of View	DIAGONAL 2.8mm : 119.9° 12mm : 28.80°	DIAGONAL 9mm : 40.2° 22mm : 16.1°	DIAGONAL 4mm : 92.4° 9mm : 39.2°





SPECIFICATIONS

MODEL		NTSC	PAL
Power	Power source	AC24V ± 10% / DC12V ± 10%	
	Power consumption	410mA (5 Watts) - IR LED ON	
General	Image sensor	1/3" Sony Super HAD II	
	Total pixels	811(H) x 507(V)	795(H) x 595(V)
	Scanning system	2:1 interlace	
	Scanning frequency	15.734KHz(H) x 59.94Hz(V)	15.625KHz(H) x 50Hz(V)
	Sync. system	Internal	
	Electronic Shutter	1/60 ~ 1/100,000 sec.	1/50 ~ 1/100,000 sec.
	Resolution	600 TV lines (COLOR)	
	Min. illumination	0.1 Lux(Color), 0 Lux(B/W, IR LED ON) @ F1.2, 50IRE	
	IR LED / Sensor	IR LED 30EA(850nm / 40 degree), Sensor 1EA	
	LED Lighting Distance	30m	
F U N C T I O N	Video Output	1.0 Vp-p (75 ohm, Composite)	
	S/N Ratio	More than 50dB (AGC off)	
	Camera Control	OSD (Joystick Switch)	
	Lens	MANUAL / DC	
	Shutter	AUTO, 1/60(1/50), Flickelless, 1/250 ~ 1/100,000sec	
	Brightness	0 ~ 255	
	Backlight	OFF / BLC / HLC(High Light Compensation)	
	AGC	OFF / LOW / MIDDLE / HIGH	
	DWDR	OFF/ON	
	White Balance	ATW1 / ATW2 / AWC->SET / MANUAL	
S P E C I A L	Day & Night	AUTO / COLOR / B&W / EXT	
	Burst	OFF / ON	
	D&N	OFF / ON	
	IR Smart	OFF / ON	
	IR Smart Gain	0~255	
	Camera Title	OFF / ON	
	Motion Detection	OFF / ON (4 area)	
	Privacy Masking	OFF / ON (8.position)	
	Parking Line	OFF / ON	
	Lens Shading	OFF / ON(0~255)	
Connector & etc.	2DNR	OFF / ON	
	Mirror	OFF / ON	
	Font Color	FONT 16 COLOR, ID&TITLE 16 COLOR	
	Contrast	0~255	
	Sharpness	0~31	
	Display	CRT / LCD / USER	
	Nega Image	OFF / ON	
	Language	ENGLISH / CHINESE	
	DPC	Dead Pixel Cancellation (Auto 64 Points)	
	Reset	FACTORY RESET / RETURN	
	Power input	2-pin wire	
	Video output	BNC connector	
	Lens Mount	Fixed mount	
	Lens	f=2.8~12mm F1.2~360 Varifocal, ICR (D&N) / f=9~22mm F1.4~360 Varifocal, ICR (D&N) / f=4~9mm F1.6~360 Varifocal, ICR (D&N)	
	Operating temperature	14°F ~ 122°F (-10°C ~ +50°C)	
	Operating humidity	0 ~ 96% (non-condensing)	
	External Dimension	146(ø) x 113(H) mm	
	Weight	400g	

EXTERNAL DIMENSION

Dimensions



Unit: mm

Window Size	0.1 in. (2.5mm thick), impact-resistant P.C (LEXAN) 3.93 in. (10cm) diameter
Cable Entry	One 1" opening holes
Weight - Unit: Shipping:	0.88 lb. (0.4kg) 1.41 lb. (0.64 kg)

50303083A