

SF118/2C, SF118/4C Emergency Call Station

IL576 Specification Sheet

Tek-ENTRY Apartment Entry Systems • Rev. 12 - 4/2022

Features

- ▮ Call-placed indicator
- ▮ Call cancellation only at point of origin
- ▮ Flame retardant (UL[®] 94V-0) plastic faceplate
- ▮ Contacts to signal dome light, and buzzer or bell

Description

The SF118C Emergency Switch is available in two models. Both models feature a rugged, long-life, positive-acting switch mounted on a flame retardant (UL[®] 94V-0) plastic faceplate marked **EMERGENCY** that includes a red LED. Signaling an emergency requires just a short pull in any direction on the 6' long nylon cord. The signal cannot be canceled except at the point of origin. The SF118/2C provides two contacts, one to signal a dome light and master station, and one to signal a buzzer or DC bell. The SF118/4C provides two additional contacts that may be used to operate additional signaling devices as needed.



SF118/2C, SF118/4C Emergency Call Station

Specifications

Dimensions:	4.5"H × 2.75"W × 1.5"D (114 mm × 70 mm × 38 mm)
Switch:	SF118/2C: PDT SF118/4C: PDT
Construction:	Switch and lamp are mounted to a flame retardant (UL [®] 94V-0) plastic faceplate
Call-Placed Light:	Red LED
Connections:	Wire leads
Mounting:	Standard single-gang electrical box

Required Components

CM800 Emergency Call System