

MODEL: R4KCB13 - SLIM CODE STATION



R4KCB13

FEATURES

- Extra large back-lit button for easier activation
- Output for elapsed timer
- Call-Assurance/Monitor LED
- Cancel button
- Plug-in connectors for easy service
- Continuous supervision of station
- Optional antimicrobial Bio-seal to cover buttons and allow for easy disinfecting of station

SPECIFICATIONS

Power Required: 4mA @15VDC

Power Required when used with SLIM Speaker Module: 7mA @15VDC

Weight: 0.20 lbs. (0.09 kg)

Size: W: 3.2" (8.10 cm)

H: 4.25" (10.8 cm)

D: 0.6" (1.5 cm) in back box: 0.5" (1.3 cm) off-wall

Housing and Finish: High-impact molded Cycloy 2950 UL 94-5VB; light grey faceplate

Controls/Indicators: One (1) Push button for call actuation, One (1) Call-assurance/Monitor LED, and One (1) Cancel button

Terminations: Plug-on connectors

Backbox Requirement: 1-gang, (Non-gangable) W: 2.25" (5.7 cm) H: 4" (10.2 cm) D: 3.5" (8.9 cm)

Backbox Requirement when used with SLIM Speaker

Module: 3-gang, Non-gangable W: 5.5" (14 cm) H: 3.75" (9.5 cm) D: 3.5" (8.9 cm)

Certification: UL/C-UL 1069, FCC Part 15 Class B, IEC60601-1-2, Designed for compliance to IEC60601-1 and CE Marking (MDD), FDA Registered, and RoHS Compliant

DESCRIPTION

The Responder® 4000 SLIM Code Station is a call push-button station providing the ability to place a code call. Pressing the cancel button cancels the call. This station provides an output for an elapsed timer supporting a momentary or latched contact closure output. The Code Blue button is back-lit for easier location in a dark room. Using custom buttons, the stations can be customized for unique call-ins such as "Code Pink", and more.

The SLIM Code Station is connected to its associated corridor light and is continually supervised for station presence. Through programming, a "Trouble" message can announce at the associated console(s) when the

station is removed from the system. This station also offers enhanced supervision capabilities by notifying staff if the cancel button is depressed continuously (stuck) for long time. A "CB Fail" trouble message will announce at the associated console(s).

*Architect and Engineer (A&E) Specifications available online at: customerconnection.rauland.com
Specifications subject to change without notice*

©Copyright 2009 Rauland-Borg Corporation Printed in USA Rev 03/2009