



Description

The WNC-CI can be used as a wireless door bell or in any application where momentary push button activation is required. A call from a WNC-CI Station activates a pre-programmed call information display at the Video Display Console. If configured in system programming, pressing the WNC-CI button will additionally provide notification to associated pocket pagers or other notification devices as well as activate the associated Corridor Lamp and Corridor Zone Lamp (if installed).

Architects' and Engineers'

Push button station shall be a Vision Link WNC-CI or approved equal. It shall be flush mounted and shall provide a button for push button activation. The button shall be momentary and shall not require a reset at the station. Pressing the button shall activate a call information display at the Video Display Console as well as any associated pocket pagers or other notification devices. The push button shall be capable of being configured in programming to activate the associated corridor light and corridor zone light, if installed.

Specifications

Dimensions: Height: 4-1/2" (114mm)

Width: 2-13/16" (72mm)

Depth: 1-5/8" (41mm)

Panel: Flame retardant GE Lexan faceplate

Batteries: One CR123

Backbox: Carl on B120A plastic single gang box

Flush Mount: Cooper BB10L single gang B-Line bracket

Surface Mount: Wiremold 2348 plastic single gang box

Features

- Simple operation
- Reliable momentary switch
- Flame retardant GE Lexan faceplate