

1. INTRODUCTION

1-1-3 Combination with servo motor

The following table lists combinations of servo amplifiers and servo motors. The same combinations apply to the models with electromagnetic brakes, the models with reduction gears, the EN Standard-compliant models and UL/C-UL Standard-compliant models.

Servo Amplifier	Servo Motors							
	HC-MF□	HA-FF□	HC-SF□ (Note)			HC-RF□	HC-UF□ (Note)	
			1000r/min	2000r/min	3000r/min		2000r/min	3000r/min
MR-J2-10A (1)	053 • 13	053 • 13						13
MR-J2-20A (1)	23	23						23
MR-J2-40A (1)	43	33 • 43						43
MR-J2-60A		63		52	53			
MR-J2-70A	73						72	73
MR-J2-100A			81	102	103			
MR-J2-200A			121 • 201	152 • 202	153 • 203	103 • 153	152	
MR-J2-350A			301	352	353	203	202	

Note The HC-UF73 • HC-SF203 • HC-SF353 may not be connected depending on the production timing of the servo amplifier. Please contact us.