

## Processing Delays

### PDM1284



SDI Input	-	Delay V	-	Delay H	-	AV Delay
525	-	0 line	-	12.815 us delayed	-	1ms
625	-	0 line	-	13.296 us delayed	-	1ms
720p50	-	0 line	-	10.411 us delayed	-	1ms
1080i50	-	0 line	-	10.707 us delayed	-	1ms
720p59	-	0 line	-	5.918 us delayed	-	1ms
1080i59	-	0 line	-	4.799 us delayed	-	1ms
720p60	-	0 line	-	5.886 us delayed	-	1ms
1080i60	-	0 line	-	4.768 us delayed	-	1ms
1080sf24	-	0 line	-	12.269 us delayed	-	1ms
1080sf23	-	0 line	-	12.174 us delayed	-	1ms
1080p29	-	0 line	-	4.745 us delayed	-	0ms
1080p25	-	0 line	-	10.572 us delayed	-	0ms
1080p24	-	0 line	-	12.256 us delayed	-	0ms
1080p23	-	0 line	-	12.133 us delayed	-	0ms
1080p50	-	0 line	-	5.333 us delayed	-	1ms
1080p59	-	0 line	-	2.440 us delayed	-	1ms
1080p60	-	0 line	-	2.384 us delayed	-	1ms

#### Hint:

- AV measurement inaccuracy varies between -2 ms and 2 ms.