

*net***2***phone*

Firewall Settings

The following Networks and Addresses + Ports Should Be Allowed To Ensure The Best Possible Experience With Your net2phone Services.

SIP (Signaling)

TCP & UDP Ports 5060 and 6070

RTP (media)

TCP & UDP Ports 1000-65500

Network Ranges:

213.166.96.0 /19
111.235.152.0 /22
204.13.140.0 /22
216.53.0.0 /18
66.33.128.0 /18
206.20.0.0 /16
169.132.0.0 /16
66.33.160.0 /19

Individual IP Addresses:

3.95.70.177
52.201.151.226
54.209.90.200
34.233.46.241
34.234.156.107
3.208.48.15



Ranges and Individual Addresses MUST be allowed. ALG and SPI should be disabled. Default UDP timeout should be set to at least 300 seconds.

Tip: Please consult your specific manufacturer documentation for an exact "how to" for implementing rules on your particular security appliance.