















### Protocol3 Reset Configuration to Default

Purpose: Instructions how to reset the configuration parameters to the factory defaults.

#### Accessing the Configuration Menu:

To access the Configuration Menu, and all of its sub-menus, the control must be in its cycle complete or stopped state (not running), if it is not in that state press the  button to stop the control before proceeding.

1. Press  and  together from the Select a Mode screen. This should access the **Main** Menu.
2. From the **Main** Menu, use  to scroll to **Configuration** Menu. Press  when menu is highlighted.
3. A prompt will appear to enter an **unlock code**. Enter the correct code with  and  (the default code is 0010), then press .
4. Press  to scroll to **Reset To Defaults**, then press .
5. Press  to confirm that you want to default the parameters.
6. Select **Yes** using the  and  and pressing .
7. The display will flash and return to the Select a mode screen.
8. Test control operation and reset any special control configurations as needed.