

**UL Short Circuit Rating of Eaton Open Components for use in Industrial Control Panels**

Frame Size	Component Type	Description	Partial Catalog Number(s)	Overload FLA Dial Range	Maximum Horsepower Ratings						Standard Fault Short Circuit Rating		
					1 Phase			3 Phase					
					115V	200V	230V	200V	230V	460V		575V	
Mini	Contactor (screw terminals)	Non-reversing, 3 pole	XTMC6A10*	-	1/4	3/4	1	1.5	2	3	3	5kA	
			XTMC6A01*	-	1/4	3/4	1	1.5	2	3	3		
		XTMC9A10*	-	1/2	1	1.5	2	3	5	5			
		XTMC9A01*	-	1/2	1	1.5	2	3	5	5			
		Non-reversing, 4 pole	XTMF9A00*	-	1/2	1	1.5	2	3	5	5		
Mini	Contactor (spring cage terminals)	Non-reversing, 3 pole	XTMCC6A10*	-	1/4	3/4	1	1.5	2	3	3		
			XTMCC6A01*	-	1/4	3/4	1	1.5	2	3	3		
			XTMCC9A10*	-	1/2	1	1.5	2	3	5	5		
			XTMCC9A01*	-	1/2	1	1.5	2	3	5	5		
Mini	Contactor (screw terminals)	Reversing, 3 pole	XTMR6A21*	-	1/4	3/4	1	1.5	2	3	3	5kA	
			XTMR9A21*	-	1/2	1	1.5	2	3	5	5		
Mini	Overload Relay	Class 10A, 3 pole	XTOMP16AC1	0.10 - 0.16	-	-	-	-	-	-	-	5kA	
			XTOMP24AC1	0.16 - 0.24	-	-	-	-	-	-	-		
			XTOMP40AC1	0.24 - 0.40	-	-	-	-	-	-	-		
			XTOMP60AC1	0.4 - 0.6	-	-	-	-	-	-	-		
			XTOMP001AC1	0.6 - 1.0	-	-	-	-	-	-	-		
			XTOM1P6AC1	1.0 - 1.6	-	-	-	-	-	-	-		
			XTOM2P4AC1	1.6 - 2.4	-	-	-	-	-	-	-		
			XTOM004AC1	2.4 - 4.0	-	-	-	-	-	-	-		
			XTOM006AC1	4.0 - 6.0	-	-	-	-	-	-	-		
			XTOM009AC1	6.0 - 9.0	-	-	-	-	-	-	-		
		XTOM012AC1	9.0 - 12	-	-	-	-	-	-	-			

**UL Short Circuit Rating of Eaton Open Components for use in Industrial Control Panels**

XT Frame Size	Component Type	Description	Partial Catalog Number(s)	Overload FLA Dial Range	Maximum Horsepower Ratings							Standard Fault Short Circuit Rating
					1 Phase			3 Phase				
					115V	200V	230V	200V	230V	460V	575V	
B	Contactor	Non-reversing, 3 pole	XTCE007B10*	-	1/4	3/4	1	1.5	2	3	5	5kA
			XTCE007B01*	-	1/4	3/4	1	1.5	2	3	5	
			XTCE009B10*	-	1/2	1	1.5	3	3	5	7.5	
			XTCE009B01*	-	1/2	1	1.5	3	3	5	7.5	
			XTCE012B10*	-	1	2	2	3	3	10	10	
			XTCE012B01*	-	1	2	2	3	3	10	10	
			XTCE015B10*	-	1	2	3	5	5	10	10	
C	Contactor	Non-reversing, 3 pole	XTCE018C10*	-	2	2	3	5	5	10	15	5kA
			XTCE018C01*	-	2	2	3	5	5	10	15	
			XTCE025C10*	-	2	3	5	7.5	7.5	15	20	
			XTCE025C01*	-	2	3	5	7.5	7.5	15	20	
			XTCE032C10*	-	3	5	5	10	10	20	25	
			XTCE032C01*	-	3	5	5	10	10	20	25	
			XTCE040D00*	-	3	5	7.5	10	15	30	40	
D	Contactor	Non-reversing, 3 pole	XTCE050D00*	-	3	7.5	10	15	20	40	50	10kA
			XTCE065D00*	-	5	10	15	20	25	50	60	
			XTCE080F00*	-	7.5	15	15	25	30	60	75	
F	Contactor	Non-reversing, 3 pole	XTCE095F00*	-	7.5	15	15	25	40	75	100	10kA
			XTCE115G00*	-	10	25	25	40	50	100	125	
G	Contactor	Non-reversing, 3 pole	XTCE150G00*	-	15	25	30	40	60	125	150	10kA
			XTCE185L22*	-	-	-	-	50	60	125	150	
L	Contactor	Non-reversing, 3 pole	XTCE225L22*	-	-	-	-	60	75	150	200	18kA
			XTCE250L22*	-	-	-	-	75	100	200	250	
			XTCS185L22*	-	-	-	-	50	60	125	150	
L	Contactor (S-Series)	Non-reversing, 3 pole	XTCS225L22*	-	-	-	-	60	75	150	200	18kA
			XTCS250L22*	-	-	-	-	75	100	200	250	
			XTCE300M22*	-	-	-	-	100	125	250	300	
M	Contactor	Non-reversing, 3 pole	XTCE400M22*	-	-	-	-	125	150	300	400	30kA
			XTCE500M22*	-	-	-	-	150	200	400	500	
			XTCS300M22*	-	-	-	-	100	125	250	300	
M	Contactor (S-Series)	Non-reversing, 3 pole	XTCS400M22*	-	-	-	-	125	150	300	400	30kA
			XTCS500M22*	-	-	-	-	150	200	400	500	
			XTCE580N22*	-	-	-	-	200	200	400	600	
N	Contactor	Non-reversing, 3 pole	XTCE650N22*	-	-	-	-	200	250	500	600	42kA
			XTCE750N22*	-	-	-	-	250	300	600	700	
			XTCE820N22*	-	-	-	-	250	350	700	800	
			XTCR007B21*	-	1/4	3/4	1	1.5	2	3	5	
B	Contactor	Reversing, 3 pole	XTCR009B21*	-	1/2	1	1.5	3	3	5	7.5	5kA
			XTCR012B21*	-	1	2	2	3	3	10	10	
			XTCR018C21*	-	2	2	3	5	5	10	15	
C	Contactor	Reversing, 3 pole	XTCR025C21*	-	2	3	5	7.5	7.5	15	20	5kA
			XTCR032C21*	-	3	5	5	10	10	20	25	
			XTCR040D11*	-	3	5	7.5	10	15	30	40	
D	Contactor	Reversing, 3 pole	XTCR050D11*	-	3	7.5	10	15	20	40	50	10kA
			XTCR065D11*	-	5	10	15	20	25	50	60	
			XTCR080F11*	-	7.5	15	15	25	30	60	75	
F	Contactor	Reversing, 3 pole	XTCR095F11*	-	7.5	15	15	25	40	75	100	10kA
			XTCR095F11*	-	7.5	15	15	25	40	75	100	



B	Overload Relay	Class 10A, 3 pole Direct Mount	XTOBP60BC1	0.4 - 0.6	-	-	-	-	-	-	-	5kA	
			XTOB001BC1	0.6 - 1.0	-	-	-	-	-	-	-		-
			XTOB1P16BC1	1.0 - 1.6	-	-	-	-	-	-	-		-
			XTOB2P4BC1	1.6 - 2.4	-	-	-	-	-	-	-		-
			XTOB004BC1	2.4 - 4.0	-	-	-	-	-	-	-		-
			XTOB006BC1	4 - 6	-	-	-	-	-	-	-		-
			XTOB010BC1	6 - 10	-	-	-	-	-	-	-		-
			XTOB012BC1	9 - 12	-	-	-	-	-	-	-		-
XTOB016BC1	12 - 16	-	-	-	-	-	-	-	-	-			
C	Overload Relay	Class 10A, 3 pole Direct Mount	XTOBP16CC1	0.10 - 0.16	-	-	-	-	-	-	-	5kA	
			XTOBP24CC1	0.16 - 0.24	-	-	-	-	-	-	-		-
			XTOBP40CC1	0.24 - 0.40	-	-	-	-	-	-	-		-
			XTOBP60CC1	0.4 - 0.6	-	-	-	-	-	-	-		-
			XTOB001CC1	0.6 - 1.0	-	-	-	-	-	-	-		-
			XTOB1P6CC1	1.0 - 1.6	-	-	-	-	-	-	-		-
			XTOB2P4CC1	1.6 - 2.4	-	-	-	-	-	-	-		-
			XTOB004CC1	2.4 - 4.0	-	-	-	-	-	-	-		-
			XTOB006CC1	4 - 6	-	-	-	-	-	-	-		-
			XTOB010CC1	6 - 10	-	-	-	-	-	-	-		-
			XTOB016CC1	10 - 16	-	-	-	-	-	-	-		-
			XTOB024CC1	16 - 24	-	-	-	-	-	-	-		-
XTOB032CC1	24 - 32	-	-	-	-	-	-	-	-	-			
D	Overload Relay	Class 10A, 3 pole Direct Mount	XTOB010DC1	6 - 10	-	-	-	-	-	-	-	10kA	
			XTOB016DC1	10 - 16	-	-	-	-	-	-	-		
			XTOB024DC1	16 - 24	-	-	-	-	-	-	-		
			XTOB040DC1	24 - 40	-	-	-	-	-	-	-		
			XTOB057DC1	40 - 57	-	-	-	-	-	-	-		
			XTOB065DC1	50 - 65	-	-	-	-	-	-	-		
F - G	Overload Relay	Class 10A, 3 pole Direct Mount	XTOB035GC1	25 - 35	-	-	-	-	-	-	-	10kA	
			XTOB050GC1	35 - 50	-	-	-	-	-	-	-		
			XTOB070GC1	50 - 70	-	-	-	-	-	-	-		
			XTOB100GC1	70 - 100	-	-	-	-	-	-	-		
			XTOB125GC1	90 - 125	-	-	-	-	-	-	-		
			XTOB150GC1	120 - 150	-	-	-	-	-	-	-		
F - G	Overload Relay	Class 10A, 3 pole Separate Mount	XTOB035GC1S	25 - 35	-	-	-	-	-	-	-	10kA	
			XTOB050GC1S	35 - 50	-	-	-	-	-	-	-		
			XTOB070GC1S	50 - 70	-	-	-	-	-	-	-		
			XTOB100GC1S	70 - 100	-	-	-	-	-	-	-		
			XTOB125GC1S	90 - 125	-	-	-	-	-	-	-		
			XTOB150GC1S	120 - 150	-	-	-	-	-	-	-		
L	Overload Relay	Class 10A, 3 pole	XTOB070LC1	50 - 70	-	-	-	-	-	-	-	18kA	
			XTOB100LC1	70 - 100	-	-	-	-	-	-	-		
			XTOB125LC1	95 - 125	-	-	-	-	-	-	-		
			XTOB160LC1	120 - 160	-	-	-	-	-	-	-		
			XTOB220LC1	160 - 220	-	-	-	-	-	-	-		
			XTOB250LC1	200 - 250	-	-	-	-	-	-	-		

**Eaton XT Contactors Short Circuit Current Ratings**

XT Frame	Short Circuit Data			High-Fault Short C	
	Withstand Rating	Max. Fuse Size	Max. T/M Circuit Breaker	Withstand Rating	Max. Fuse Size
B	5,000 A. 600 Vac	45 A	60 A	30,000 A. 600 Vac	25 A
C		125 A	125 A		10,000 A. 600 Vac
D	10,000 A. 600 Vac	250 A	250 A	30,000 A. 600 Vac	250 A
F		600 A	600 A		300 A
G		600 A	600 A		300 A
L (up to 225A)		700 A (Class L)	600 A		
L (up to 250A)	18,000 A. 600 Vac	700 A (Class L)	600 A		
M (up to 400A)		800 A (Class L)	-		
M (up to 500A)	30,000 A. 600 Vac	800 A (Class L)	-		
N (up to 650A)	30,000 A. 600 Vac	2000 A (Class L)	-		
N (up to 820A)	42,000 A. 600 Vac	2000 A (Class L)	-		
N (up to 1000A)	85,000 A. 600 Vac	2000 A (Class L)	-		
R		2000 A (Class L)	-		

Circuit Data
Max. T/M Circuit Breaker
-
50 A
-
250 A
350 A
350 A

**UL Short Circuit Rating of Eaton Open Components for use in Industrial Control Panels**

XT Frame Size	Component Type	Description	Catalog No.	Overload FLA Range	Max. 3 Ph. Horsepower Ratings				Max. Protective Device - Group Motor Applications					
									Short Circuit Rating - 600 V		Max. Rated Fuse (A)		Max. Rated Circuit Breaker (A)	
					200V	230V	460V	575V	Device	w/ XTPAXCL	Device	w/ XTPAXCL	Device	w/ XTPAXCL
B	Manual Motor Protector	Pushbutton Operated, 3 pole, Class 10	XTPBP16BC1	0.10 - 0.16	-	-	-	-	50kA	-	600	-	600	-
			XTPBP25BC1	0.16 - 0.25	-	-	-	-	50kA	-	600	-	600	-
			XTPBP40BC1	0.25 - 0.40	-	-	-	-	50kA	-	600	-	600	-
			XTPBP63BC1	0.40 - 0.63	-	-	-	-	50kA	-	600	-	600	-
			XTPB001BC1	0.63 - 1.0	-	-	1/2	1/2	50kA	-	600	-	600	-
			XTPB1P6BC1	1.0 - 1.6	-	-	3/4	1	50kA	-	600	-	600	-
			XTPB2P5BC1	1.6 - 2.5	1/2	1/2	1	1.5	50kA	-	600	-	600	-
			XTPB004BC1	2.5 - 4.0	1	1	2	3	50kA	-	600	-	600	-
			XTPB6P3BC1	4.0 - 6.3	1.5	1.5	3	5	50kA	-	600	-	600	-
			XTPB010BC1	6.3 - 10	3	3	7.5	10	10kA	50kA	150	600	125	600
			XTPB012BC1	8 - 12	3	3	7.5	10	10kA	50kA	150	600	125	600
			XTPB016BC1	10 - 16	3	5	10	10	10kA	50kA	150	600	125	600
			XTPB020BC1	16 - 20	5	5	10	15	10kA	50kA	150	600	125	600
XTPB025BC1	20 - 25	5	7.5	15	20	10kA	50kA	150	600	125	600			
B	Manual Motor Protector	Rotary Operated, 3 pole, Class 10 (screw terminals)	XTPRP16BC1	0.10 - 0.16	-	-	-	-	50kA	-	600	-	600	-
			XTPRP25BC1	0.16 - 0.25	-	-	-	-	50kA	-	600	-	600	-
			XTPRP40BC1	0.25 - 0.40	-	-	-	-	50kA	-	600	-	600	-
			XTPRP63BC1	0.40 - 0.63	-	-	-	-	50kA	-	600	-	600	-
			XTPR001BC1	0.63 - 1.0	-	-	1/2	1/2	50kA	-	600	-	600	-
			XTPR1P6BC1	1.0 - 1.6	-	-	3/4	1	50kA	-	600	-	600	-
			XTPR2P5BC1	1.6 - 2.5	1/2	1/2	1	1.5	50kA	-	600	-	600	-
			XTPR004BC1	2.5 - 4.0	1	1	2	3	50kA	-	600	-	600	-
			XTPR6P3BC1	4.0 - 6.3	1.5	1.5	3	5	50kA	-	600	-	600	-
			XTPR010BC1	6.3 - 10	3	3	7.5	10	10kA	50kA	150	600	125	600
			XTPR012BC1	8 - 12	3	3	7.5	10	10kA	50kA	150	600	125	600
			XTPR016BC1	10 - 16	3	5	10	10	10kA	50kA	150	600	125	600
			XTPR020BC1	16 - 20	5	5	10	15	10kA	18kA	150	600	125	600
XTPR025BC1	20 - 25	5	7.5	15	20	10kA	18kA	150	600	125	600			
XTPR032BC1	25 - 32	7.5	10	20	30	10kA	18kA	150	600	125	600			
D	Manual Motor Protector	Rotary Operated, 3 pole, Class 10 (screw terminals)	XTPR016DC1	10 - 16	3	5	10	15	10kA	-	600	-	600	-
			XTPR025DC1	16 - 25	7.5	7.5	20	25	10kA	-	600	-	600	-
			XTPR032DC1	25 - 32	10	10	25	30	10kA	-	600	-	600	-
			XTPR040DC1	32 - 40	10	15	30	40	10kA	-	600	-	600	-
			XTPR050DC1	40 - 50	10	15	30	40	10kA	-	600	-	600	-
			XTPR058DC1	50 - 58	10	15	30	40	10kA	-	600	-	600	-
XTPR063DC1	55 - 63	15	15	40	50	10kA	-	600	-	600	-			
B	Manual Motor Protector	Rotary Operated, 3 pole, Class 10, (screw line terminals & spring-cage load terminals)	XTPRSCP16BC1	0.10 - 0.16	-	-	-	-	50kA	-	600	-	600	-
			XTPRSCP25BC1	0.16 - 0.25	-	-	-	-	50kA	-	600	-	600	-
			XTPRSCP40BC1	0.25 - 0.40	-	-	-	-	50kA	-	600	-	600	-
			XTPRSCP63BC1	0.40 - 0.63	-	-	-	-	50kA	-	600	-	600	-
			XTPRSC001BC1	0.63 - 1.0	-	-	1/2	1/2	50kA	-	600	-	600	-
			XTPRSC1P6BC1	1.0 - 1.6	-	-	3/4	1	50kA	-	600	-	600	-
			XTPRSC2P5BC1	1.6 - 2.5	1/2	1/2	1	1.5	50kA	-	600	-	600	-
			XTPRSC004BC1	2.5 - 4.0	1	1	2	3	50kA	-	600	-	600	-
			XTPRSC6P3BC1	4.0 - 6.3	1.5	1.5	3	5	50kA	-	600	-	600	-
			XTPRSC010BC1	6.3 - 10	3	3	7.5	10	10kA	50kA	150	600	125	600
			XTPRSC012BC1	8 - 12	3	3	7.5	10	10kA	50kA	150	600	125	600
			XTPRSC016BC1	10 - 16	3	5	10	10	10kA	50kA	150	600	125	600

B	Manual Motor Protector	Rotary Operated, 3 pole, Class 10, (spring cage terminals)	XTPRCP16BC1	0.10 - 0.16	-	-	-	-	50kA	-	600	-	600	-
			XTPRCP25BC1	0.16 - 0.25	-	-	-	-	50kA	-	600	-	600	-
			XTPRCP40BC1	0.25 - 0.40	-	-	-	-	50kA	-	600	-	600	-
			XTPRCP63BC1	0.40 - 0.63	-	-	-	-	50kA	-	600	-	600	-
			XTPRC001BC1	0.63 - 1.0	-	-	1/2	1/2	50kA	-	600	-	600	-
			XTPRC1P6BC1	1.0 - 1.6	-	-	3/4	1	50kA	-	600	-	600	-
			XTPRC2P5BC1	1.6 - 2.5	1/2	1/2	1	1.5	50kA	-	600	-	600	-
			XTPRC004BC1	2.5 - 4.0	1	1	2	3	50kA	-	600	-	600	-
			XTPRC6P3BC1	4.0 - 6.3	1.5	1.5	3	5	50kA	-	600	-	600	-
			XTPRC010BC1	6.3 - 10	3	3	7.5	10	10kA	50kA	150	600	125	600
			XTPRC012BC1	8 - 12	3	3	7.5	10	10kA	50kA	150	600	125	600
			XTPRC016BC1	10 - 16	3	5	10	10	10kA	50kA	150	600	125	600

**UL Short Circuit Rating of Eaton Open Components for use in Industrial Control Panels**

XT Frame Size	Component Type	Description	MMP Catalog No.	FLA Dial Range	Line Side Adaptor Catalog No.	Max. 3-Ph. Horsepower Ratings				Max. Short Circuit Ratings		
						200V	230V	460V	575V	240V	480Y / 277V	600Y / 347V
B	Type E Self-Protected Manual Motor Starter	Rotary Operated, 3 pole, Class 10, (screw terminals)	XTPRP16BC1	0.10 - 0.16	XTPAXLSA	-	-	-	-	50	50	50
			XTPRP25BC1	0.16 - 0.25		-	-	-	-	50	50	50
			XTPRP40BC1	0.25 - 0.40		-	-	-	-	50	50	50
			XTPRP63BC1	0.40 - 0.63		-	-	-	-	50	50	50
			XTPR001BC1	0.63 - 1.0	XTPAXLSA	-	-	1/2	1/2	50	50	50
			XTPR1P6BC1	1.0 - 1.6		-	-	3/4	1	50	50	50
			XTPR2P5BC1	1.6 - 2.5		1/2	1/2	1	1.5	50	50	50
			XTPR004BC1	2.5 - 4.0		1	1	2	3	50	50	50
			XTPR6P3BC1	4.0 - 6.3	XTPAXLSA	1.5	1.5	3	5	50	50	50
			XTPR010BC1	6.3 - 10		3	3	7.5	10	50	50	50
			XTPR012BC1	8 - 12		3	3	7.5	10	42	42	-
			XTPR016BC1	10 - 16		3	5	10	10	42	42	-
			XTPR020BC1	16 - 20	XTPAXLSA	5	5	10	15	18	18	-
			XTPR025BC1	20 - 25		5	7.5	15	20	18	18	-
XTPR032BC1	25 - 32	7.5	10	25		30	18	18	-			
XTPR016DC1	10 - 16	3	5	10		15	50	50	10			
D	Type E Self-Protected Manual Motor Starter	Rotary Operated, 3 pole, Class 10, (screw terminals)	XTPR016DC1	10 - 16	XTPAXLSAD	3	5	10	15	50	50	10
			XTPR025DC1	16 - 25		5	7.5	20	25	50	50	10
			XTPR032DC1	25 - 32		7.5	10	25	30	50	50	10
			XTPR040DC1	32 - 40		10	15	30	40	50	50	10

**UL Short Circuit Rating of Eaton Open Components for use in Industrial Control Panels**

XT Frame Size	Component Type	Description	Partial Catalog No.	FLA Dial Range	Max. 3 Ph. Horsepower Ratings			Max. Short Circuit Ratings		
					230V	460V	575V	240V	480 / 277V	600 / 347V
B	Manual Motor Controller/Starter	Non-reversing, 3 pole, Class 10	XTSCP25BB*	0.16 - 0.25	-	1/2	1/2	50kA	50kA	50kA
			XTSCP40BB*	0.25 - 0.40	-	1/2	1/2	50kA	50kA	50kA
			XTSCP63BB*	0.40 - 0.63	-	1/2	1/2	50kA	50kA	50kA
			XTSC001BB*	0.63 - 1.0	-	1/2	1/2	50kA	50kA	50kA
			XTSC2P5BB*	1.0 - 1.6	-	3/4	1	50kA	50kA	50kA
			XTSC004BB*	1.6 - 2.5	1/2	1	1.5	50kA	50kA	50kA
			XTSC6P3BB*	2.5 - 4.0	1	2	3	50kA	50kA	50kA
			XTSC010BB*	4.0 - 6.3	1.5	3	5	50kA	50kA	50kA
			XTSC010BB*	6.3 - 10	3	7.5	10	50kA	50kA	50kA
			XTSC012BC*	8 - 12	3	7.5	10	50kA	42kA	-
			XTSC016BC*	10 - 16	3	10	10	18kA	42kA	-
			XTSC020BC*	16 - 20	5	10	15	18kA	18kA	-
			XTSC025BC*	20 - 25	7.5	7.5	20	18kA	18kA	-
XTSC032BC*	25 - 32	10	10	25	18kA	18kA	-			
D	Manual Motor Controller/Starter	Non-reversing, 3 pole, Class 10	XTSC016DC*	10 - 16	5	10	15	50kA	50kA	-
			XTSC025DC*	16 - 25	7.5	15	20	50kA	50kA	-
			XTSC032DC*	25 - 32	10	25	30	50kA	50kA	-
			XTSC040DD*	32 - 40	10	30	30	50kA	50kA	-
			XTSC050DD*	40 - 50	15	30	40	50kA	50kA	-
			XTSC08DD*	50 - 58	15	30	40	50kA	50kA	-
B	Manual Motor Controller/Starter	Reversing, 3 pole, Class 10	XTSRP25BB*	0.16 - 0.25	-	1/2	1/2	50kA	50kA	50kA
			XTSRP40BB*	0.25 - 0.40	-	1/2	1/2	50kA	50kA	50kA
			XTSRP63BB*	0.40 - 0.63	-	1/2	1/2	50kA	50kA	50kA
			XTSR001BB*	0.63 - 1.0	-	1/2	1/2	50kA	50kA	50kA
			XTSR1P6BB*	1.0 - 1.6	-	3/4	1	50kA	50kA	50kA
			XTSR2P5BB*	1.6 - 2.5	1/2	1	1.5	50kA	50kA	50kA
			XTRS004BB*	2.5 - 4.0	1	2	3	50kA	50kA	50kA
			XTSR6P3BB*	4.0 - 6.3	1.5	3	5	50kA	50kA	50kA
			XTSR010BB*	6.3 - 10	3	7.5	10	50kA	50kA	50kA
			XTSR012BB*	8 - 12	3	7.5	10	50kA	42kA	-
			XTSR016BC*	10 - 16	3	10	10	18kA	42kA	-
			XTSR020BC*	16 - 20	5	10	15	18kA	18kA	-
			XTSR025BC*	20 - 25	7.5	7.5	20	18kA	18kA	-
XTSR032BC*	25 - 32	10	10	25	18kA	18kA	-			
D	Manual Motor Controller/Starter	Reversing, 3 pole, Class 10	XTSR016DC*	10 - 16	5	10	15	50kA	50kA	-
			XTSR025DC*	16 - 25	7.5	15	20	50kA	50kA	-
			XTSR032DC*	25 - 32	10	25	30	50kA	50kA	-
			XTSR040DD*	32 - 40	10	30	30	50kA	50kA	-
			XTSR050DD*	40 - 50	15	30	40	50kA	50kA	-
			XTSR058DD*	50 - 58	15	30	40	50kA	50kA	-
XTSR063DD*	55 - 63	15	40	50	50kA	50kA	-			

**UL Short Circuit Rating of Eaton Open Components for use in Industrial Control Panels**

XT Frame Size	Component Type	Description	Catalog No.	FLA Adjustment Range	Label to be affixed next to device on panel	Max. 3 Ph. Horsepower Ratings				Max. Protective Device - Group Motor Applications					
						200V	230V	460V	575V	Short Circuit Rating -		Max. Fuse (A)		Max. Circuit Breaker (A)	
										Device	w/ XTPAXCL	Device	w/ XTPAXCL	Device	w/ XTPAXCL
B	Transformer Protective Device	Rotary Operated, 3 pole	XTPTP16BC1	0.10 - 0.16	Pub 51226	-	-	-	-	50kA	-	600	-	600	-
			XTPTP16BC1	0.16 - 0.25		-	-	-	-	50kA	-	600	-	600	-
			XTPTP40BC1	0.25 - 0.40		-	-	-	-	50kA	-	600	-	600	-
			XTPTP63BC1	0.40 - 0.63		-	-	-	-	50kA	-	600	-	600	-
			XTPT001BC1	0.63 - 1.0	Pub 51226	-	-	1/2	1/2	50kA	-	600	-	600	-
			XTPT1P6BC1	1.0 - 1.6		-	-	3/4	1	50kA	-	600	-	600	-
			XTPT2P5BC1	1.6 - 2.5		1/2	1/2	1	1.5	50kA	-	600	-	600	-
			XTPT0004BC1	2.5 - 4.0		1	1	2	3	50kA	-	600	-	600	-
			XTPT6P3BC1	4.0 - 6.3	Pub 51226	1.5	1.5	3	5	50kA	-	600	-	600	-
			XTPT010BC1	6.3 - 10		3	3	7.5	10	10kA	50kA	150	600	125	600
			XTPT012BC1	8 - 12		3	3	7.5	10	10kA	50kA	150	600	125	600
			XTPT016BC1	10 - 16	Pub 51226	3	5	10	10	10kA	50kA	150	600	125	600
			XTPT020BC1	16 - 20		5	5	10	15	10kA	18kA	150	600	125	600
			XTPT025BC1	20 - 25		5	7.5	15	20	10kA	18kA	150	600	125	600

**UL Short Circuit Rating of Eaton Open Components for use in Industrial**

XT Frame Size	Component Type	Description	Partial Catalog No.	FLA Dial Range	Max. 3 Ph. Horsepower Ratings		
					230V	460V	575V
B	Type F Combination Motor Starter	Non-reversing, 3 pole, Class 10	XTFCP25BB*	0.16 - 0.25	-	-	-
			XTFCP40BB*	0.25 - 0.40	-	-	-
			XTFCP63BB*	0.40 - 0.63	-	-	-
			XTFC001BB*	0.63 - 1.0	-	1/2	1/2
			XTFC1P6BB*	1.0 - 1.6	-	3/4	1
			XTFC2P5BB*	1.6 - 2.5	1/2	1	1.5
			XTFC004BB*	2.5 - 4.0	1	2	3
			XTFC6P3BB*	4.0 - 6.3	1.5	3	5
			XTFC010BB*	6.3 - 10	3	7.5	10
			XTFC012BB*	8 - 12	3	7.5	-
			XTFC016BC*	10 - 16	5	10	-
			XTFC020BC*	16 - 20	5	10	-
			XTFC025BC*	20 - 25	7.5	15	-
D	Type F Combination Motor Starter	Non-reversing, 3 pole, Class 10	XTFC016DC*	10 - 16	5	10	-
			XTFC025DC*	16 - 25	7.5	20	-
			XTFC032DC*	25 - 32	10	25	-
			XTFC040DD*	32 - 40	10	30	-
B	Type F Combination Motor Starter	Reversing, 3 pole, Class 10	XTFRP25BB*	0.16 - 0.25	-	-	-
			XTFRP40BB*	0.25 - 0.40	-	-	-
			XTFRP63BB*	0.40 - 0.63	-	-	-
			XTFR001BB*	0.63 - 1.0	-	1/2	1/2
			XTFR1P6BB*	1.0 - 1.6	-	3/4	1
			XTFR2P5BB*	1.6 - 2.5	1/2	1	1.5
			XTFR004BB*	2.5 - 4.0	1	2	3
			XTFR6P3BB*	4.0 - 6.3	1.5	3	5
			XTFR101BB*	6.3 - 10	3	7.5	10
			XTFR012BB*	8 - 12	3	7.5	-
			XTFR016BC*	10 - 16	5	10	-
D	Type F Combination Motor Starter	Reversing, 3 pole, Class 10	XTFR016DC*	10 - 16	5	10	-
			XTFR025DC*	16 - 25	7.5	20	-
			XTFR032DC*	25 - 32	10	25	-
			XTFR040DD*	32 - 40	10	30	-

<b>Control Panels</b>		
<b>Max. Short Circuit Ratings</b>		
<b>240V</b>	<b>480 / 277V</b>	<b>600 / 347V</b>
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	42kA	-
18kA	18kA	-
18kA	18kA	-
18kA	18kA	-
18kA	18kA	-
50kA	50kA	-
50kA	50kA	-
50kA	50kA	-
50kA	50kA	-
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	50kA	50kA
50kA	42kA	-
18kA	18kA	-
18kA	18kA	-
18kA	18kA	-
18kA	18kA	-
50kA	50kA	-
50kA	50kA	-
50kA	50kA	-
50kA	50kA	-