

## Range Extender

DMEX1

The Dome Range Extender is designed to improve communication between Z-Wave devices. It amplifies Z-Wave signals and increases the reach of your controller, ensuring your devices stay connected. The extender consists of an LED light which serves dual purposes depending upon the requirement, one where it works as an indicator and other, where it works as a night light. The extender also includes a suction cup which enables mounting onto any smooth surface. All these features makes range extender the perfect choice for security and commercial systems.

- Compatible with all Z-Wave controllers as binary switch
- Power on inclusion ensures easy one step installation
- Extends Z-Wave range by more than 400 ft in all six directions
- Z-Wave Plus Certified
- LED light has night-light mode or can be used as an indicator
- Plug into wall outlet or power with micro USB (micro USB not included)
- Suction cup mount included for window installation

### KEY FEATURES



#### ONE STEP INSTALLATION

Install in seconds



#### EXTENDS RANGE

Over 400 ft of range extension



#### NIGHT LIGHT

Night light On/Off Status

### TECHNICAL SPECIFICATIONS

- Dimensions of main enclosure: 3.15 x 1.81 x 1.1 in (8.0 x 4.6 x 2.8 cm)
- Required tools: None
- Wireless protocol: Z-Wave (500 series)
- Frequency Band: 916 MHz (US)
- Range: More than 400 ft in all 6 directions (line of sight)
- Power supply: 100-120V ~ 60Hz, 30mA, or 5V DC
- Reported data: Light on/off status
- Available modes: Night light, on/off light
- Button functionality: Inclusion, Exclusion, Factory default, Light on/off, mode change
- Operating Conditions: 32°F to 104°F (0°C to 40°C)
- Package Contents: User Manual, Range Extender, Suction Cup