


Date:



Unit: mm (in)



3. System remote controller

Controller

1. Specifications

(1). Device Specifications

Item	Description							
Power Supply	24 VDC ±10%: 5 W						Screw terminal block (M3) (*5)	
Interface	M-NET communication		17 to 30 VDC (*1)				Screw terminal block (M3) (*5)	
	Input (*2)	Ch	Sensor	Measurement target	Measurement range	Measurement error	External connection method	
		Ch1	Pt100 (3-wire system)		Temperature	-30 to 60°C [-22 to 140°F]	± 0.3%FS ± 0.1°C (0.18°F) (*3) [at 25°C(77°F)]	Screwless terminal block (3 poles)
			Analog	4 to 20 mADC	Temperature/humidity	(Set by system controller)	± 0.5%FS ± 0.1°C (0.18°F) (*3)	Screwless terminal block (2 poles)
				1 to 5 VDC			± 0.5%FS ± 0.1%RH [at 25°C(77°F)]	
		0 to 10 VDC						
		Ch2	Analog	4 to 20 mADC	Temperature/humidity	(Set by system controller)	± 0.5%FS ± 0.1°C (0.18°F) (*3)	Screwless terminal block (2 poles)
			1 to 5 VDC	± 0.5%FS ± 0.1%RH [at 25°C(77°F)]				
0 to 10 VDC								
Output	Upper/lower limit alarm interlock output (non-voltage contact)		Applied load MAX: 24 VDC, 5 W MIN: 5 VDC, 2 mW * AC loads cannot be connected.			Screw terminal block (M3.5) (*5)		
Interlock Function	Interlock M-NET devices according to measurement data values. (*4)							
Environment Conditions	Temperature		Operating temperature range		0 to 40°C [32°F to 104°F]			
	Humidity		Storage temperature range		-20 to 60°C [-4°F to 140°F]			
Dimensions	200 (W) × 120 (H) × 45 (D) mm / 77/8 (W) × 43/4 (H) × 125/32 (D) in							
Weight	0.6 kg / 13/8 lb							
Time Backup During Power Failure	In the event of power failure or shut-off, the internal capacitor will continue to track time for approximately one week. (The internal capacitor takes about 24 hours to fully charge; a replacement battery is not necessary.)							
Installation Environment	Inside the metal control board (indoors) * Use this product in a hotel, a business office environment or similar environment.							

*1: Supply electric power from a power supply unit for the transmission line or an outdoor unit. Furthermore, the power consumption factor of the MNET circuitry of this unit is "1/4".

*2: Configure the dip switch settings for the analog input method to use.

*3: The measurement error for the system includes the measurement error for this unit, sensor, and wiring.

a%FS (full scale) = a% × ([measurement range's upper limit value] - [lower limit value])

*4: Settings for the interlock function are performed from the Maintenance Tool. For details, refer to the operation manual for the Maintenance Tool.


*5: M3 and M3.5 are sizes of the screw on the terminal block (ISO metric screw thread). The number indicates the screw diameter (mm).

CONTROLLER

3. System remote controller

Controller

CONTROLLER



*This figure omits the power supply line and only shows the transmission line.

<Restrictions>

Maximum of 50 units per AE-200A/AE-50A/EW-50A/AG-150A-A/EB-50GU-A

However, the number of units that can be connected to a AE-200A/AE-50A/EW-50A/AG-150A-A/EB-50GU-A is up to 50 including this device, an indoor unit, Lossnay unit, etc.

NOTE

- For the shield ground of the M-NET centralized control line, use single-point grounding at the power unit for the transmission line. However, when supplying electric power to the M-NET centralized control line from the R410A-Series outdoor unit^{*1} without using a power supply unit for the transmission line, use single-point grounding at the TB7 of that outdoor unit. *1: Except PUMY model and PUHY/PURY-T(S)LMU/T(S)KMU model (Y/R2/H2i R2-Series) Furthermore, when connecting the M-NET transmission line of this device to the M-NET indoor control line, use grounding at the TB3 for each outdoor unit system.
- If the M-NET transmission line of this device is connected to an M-NET indoor control line and the outdoor unit is down because, for example, the power supply is interrupted for servicing or there is a failure, the AI controller can not be set and monitored from the system controller.
- The sensor connected to the AI controller can only be monitored from AE-200A/AE-50A/EW-50A/AG-150A-A/EB-50GU-A and TG-2000A. The sensor can be monitored from the AG-150A-A LCD.

3. System remote controller

Controller

(2). Parts Purchased Separately

Prepare the following parts to install this device.

Required Part	Specification
Unit fixing screws	M4 screw × 4 (* M4: ISO metric screw thread)
Power supply for this device	Commercially available power source: 24 VDC ±10% 0.2 A (Minimum loading), SELV circuit, power line with grounding terminal Ripple noise: Lower than 200 mVp-p Compatible specification Authorized or CE marked products. Subject to regulations: - IEC60950 (or EN60950) - CISPR22/24 (or EN55022/24) - IEC61000-3-2/3-3 (or EN61000-3-2/3-3)
Power supply for sensors	A separate power supply for sensors may be required. In the case of 24 VDC voltage, the capacity of the power supply for this unit can be increased so that the power supply can be shared.
Power line	Use a sheathed vinyl cord or cable. At least 0.75 mm ² (AWG18)
M-NET transmission line	Type of the cable: Sheathed vinyl cords or cable which comply with the following specifications or equivalent. • CPEV ø 1.2 mm to ø 1.6 mm • CVVS 1.25 mm ² to 2 mm ² (AWG 16 to 14) * CPEV: PE insulated PVC sheathed shielded communication cable * CVVS: PVC insulated PVC sheathed shielded control cable PE: Polyethylene PVC: Polyvinyl chloride Power needs to be supplied to the M-NET circuitry of this device. Use an outdoor unit or a separately purchased power supply unit for the transmission line.
Signal lines (Sensor input lines)	Shows the size of the electric wire (copper wire) that is adapted to the terminal block of this device. Refer to the usage and cautionary items of the sensor when performing settings. However, use a line with shielded line. Electric wire size (1)Solid wire: ø 0.65 mm (AWG21) - ø 1.2 mm (AWG16) (2)Stranded wire: 0.75 mm ² (AWG18) - 1.25 mm ² (AWG16) Single strand: At least ø 0.18 mm

[Parts to be Purchased Separately]

Name	Model	Application	Remark
Power supply unit	PAC-SC51KUA	Power supply to the M-NET transmission line	This is not required when power is to be supplied from an outdoor unit.

[Commercially available parts]

Part	Use	Remark
External 24 VDC power source	Supplies power to the AI controller.	Refer to "Power supply for this device" and "Power supply for sensors" in "Required Part" above for the capacity of the power supply.
Sensor	Measures temperature and humidity.	Temperature sensor (PAC-SE40TSA) cannot be connected.

CONTROLLER

3. System remote controller

Controller

3. Interlock control

AI controller (PAC-YG63MCA) has an interlock control function, which enables operation or set temperature change on the M-NET devices such as indoor units.

Interlock control covers the units connected to the AI controller with M-NET system. AE-200A/AE-50A/EW-50A/AG-150A-A/EB-50GU-A must be connected to use the function.

Ask your dealer for interlock control setting. The setting requires special tool support.

CAUTION

Before using the interlock control, you must agree to the following.

- 1.This feature must not be used for disaster prevention or security purpose.
(Not designed to be used in situations that are life-threatening)
- 2.No functions must be added that allow the malfunctioning unit to run by defeating the safety features, such as an external ON/OFF switch or a short-circuit.
- 3.Those settings for the function that are not supported by the interlocked units must not be made. All the settings must be made within the specified range.
(Failure to observe these precautions may result in malfunctions and failures.)
- 4.Perform a test run for interlock control, and confirm the correct settings and normal operation.
- 5.The system must be configured in the way that integrates the operation of the interlocked fire and emergency control systems.

Item	Content	Remarks
Number of events	24 events	1 event interlock with 1 unit
Determinant condition for interlock control	Measurement value Measurement interval is 1 to 7200 seconds.	• Exceeding measurement value in setting range • Exceeding upper/lower limit alarm detection value and cancellation value
Interlock control contents (to be output)	1 action for 1 condition • ON/OFF operation of indoor units • Operation mode change of indoor units • Temperature setting of indoor units (*1) • Contact output to DIDO controller	Interlock control covers the units connected to AI controllers with M-NET system. (*1) Temperature setting range: 19-28°C (Standard setting)
Other	Interlock control prohibition function is enabled at emergency stop from AE-200A/AE-50A/EW-50A/AG-150A-A/EB-50GU-A	

