

SPECIFICATION

宏致電子股份有限公司

桃園縣中壢市東園路13號

No.13, Dongyuan Rd., Jhongli City,

Taoyuan County 320, Taiwan (R.O.C.)

TEL: +886-3-463-2808 FAX: +886-3-463-1800

SPEC. NO.: PS-51614-XXXXXX-XXX REVISION: B

PRODUCT NAME: 0.5 mm PITCH EASY ON FPC CONN.

SMT R/A B/C TYPE


PRODUCT NO: 51614 \cdot 51645 \cdot 51644 SERIES

PREPARED: CHECKED: APPROVED:

GUKEQING DAVID FRANK

DATE: DATE:

2014/10/15 2014/10/15 2014/10/15



connectors					
C	€	5			

TITLE: FPC 0.5 PITCH EASY ON FPC CONN

1 Revision History

Rev.	ECN#	Revision Description	Prepared	Date
1	ECN-1307387	FOR APD1020189 ADD 51614 SPEC	HUANTY	2013/7/23
0	ECN-1401143	ADD Working voltage	YANGYANG	2014/01/10
Α	ECN-1407464	FOR APD1030104 ADD 51645	BRAVE	2014/07/30
В	ECN-1410022	FOR APD1030077 ADD 51644	GUKEQING	2014/10/15



TITLE: FPC 0.5 PITCH EASY ON FPC CONN

RELEASE DATE: 2014/10/15 REVISION: B ECN No: ECN-1410022 PAGE: **4** OF **11**

2 SCOPE

This specification covers performance, tests and quality requirements for 0.5mm pitch FPC SMT R/A Easy on connector.

3 APPLICABLE DOCUMENTS

EIA-364: ELECTRONICS INDUSTRIES ASSOCIATION

4 REQUIREMENTS

- 4.1 Design and Construction
 - 4.1.1 Product shall be of design, construction and physical dimensions specified on applicable product drawing.
 - 4.1.2 All materials conform to R.o.H.S. and the standard depends on TQ-WI-140101.
- 4.2 Materials and Finish
 - 4.2.1 Contact: High performance copper alloy (Phosphor Bronze)

Finish: (a) Contact Area: Refer to the drawing.

- (b) Under plate: Refer to the drawing.
- (c) Solder area: Refer to the drawing.
- 4.2.2 Housing: Thermoplastic or Thermoplastic High Temp., UL94V-0
- 4.2.3 Actuator: Thermoplastic or Thermoplastic High Temp., UL94V-0
- 4.2.4 Fitting Nail: Copper Alloy, Finish: Refer to the drawing.
- 4.3 Ratings
 - 4.3.1 Working voltage less than 36 volts AC (per pin)
 - 4.3.2 Voltage: 50 Volts AC (per pin)
 - 4.3.3 Current: 0.5 Amperes (per pin)
 - 4.3.4 Operating Temperature : -40°C to +85°C



TITLE: FPC 0.5 PITCH EASY ON FPC CONN

5 Performance

5.1. Test Requirements and Procedures Summary

Item Requirement		Standard					
Examination of Product	Product shall meet requirements of applicable product drawing and specification.	Visual, dimensional and functional per applicable quality inspection plan.					
ELECTRICAL							
Item	Requirement	Standard					
Low Level Contact Resistance	$\frac{50 \text{ m } \Omega}{\Omega}$ Max. (initial)per contact $\frac{20 \text{ m } \Omega}{\Omega}$ Max. change allowed	Mate connectors, measure by dry circuit, 20mV Max., 100mA Max. (EIA-364-23)					
Insulation Resistance	500 M Ω Min.	Unmated connectors, apply 500 V DC between adjacent terminals. (EIA-364-21)					
Dielectric Withstanding Voltage	No discharge, flashover or breakdown. Current leakage: 1 mA max.	300 VAC Min. at sea level for 1 minute. Test between adjacent contacts of unmated connectors. (EIA-364-20)					
Temperature Rise	30°C Max. Change allowed	Mate connector: measure the temperature rise at rated current until temperature stable. The ambient condition is still air at 25°C (EIA-364-70, METHOD1,CONDITION1)					



TITLE: FPC 0.5 PITCH EASY ON FPC CONN

RELEASE DATE: 2014/10/15 REVISION: B ECN No: ECN-1410022 PAGE: **6** OF **11**

MECHANICAL						
Item	Requirement	Standard				
Durability	30 cycles.	The sample should be mounted in the tester and fully mated and unmated the number of cycles specified at the rate of 25.4 ± 3mm/min. (EIA-364-09)				
FPC Retention Force	30gf/PIN MIN.	A connector shall be soldered on a board and insert the actuator, pull the FPC at the speed rate of 25.4 ± 3 mm/min.				
Terminal / Housing Retention Force	100 gf MIN.	Operation Speed : 25.4 ± 3 mm/minute. Measure the contact retention force with tester.				
Fitting Nail /Housing Retention Force	100 gf MIN.	Operation Speed: 25.4 ± 3 mm/minute. Measure the contact retention force with tester.				
Vibration	1 μs Max.	The electrical load condition shall be 100 mA maximum for all contacts. Subject to a simple harmonic motion having amplitude of 0.76mm (1.52mm maximum total excursion) in frequency between the limits of 10 and 55 Hz. The entire frequency range, from 10 to 55 Hz and return to 10 Hz, shall be traversed in approximately 1 minute. This motion shall be applied for 2 hours in each of three mutually perpendicular directions. (EIA-364-28 Condition I)				
Shock (Mechanical)	1 μs Max.	Subject mated connectors to 50 G's (peak value) half-sine shock pulses of 11 milliseconds duration. Three shocks in each direction shall be applied along the three mutually perpendicular axes of the test specimen (18 shocks). The electrical load condition shall be 100mA maximum for all contacts. (EIA-364-27, test condition A)				



TITLE: FPC 0.5 PITCH EASY ON FPC CONN

ENVIRONMENTAL						
Item	Requirement	Standard				
Resistance to Reflow Soldering Heat	See Product Qualification and Test Sequence Group 10 (Lead Free)	Pre Heat: 150°C~180°C, 60~120sec. Heat: 230°C Min., 40sec Min. Peak Temp.: 260°C Max, 10sec Max. Reflow number cycle: 2 times (EIA-364-56)				
Hand Soldering Temperature Resistance	Appearance: No damage	T≧350°C, 5sec at least.				
Thermal Shock	See Product Qualification and Test Sequence Group 4	-40 +0/-3 ℃, 30 minutes +85 +3/-0 ℃, 30 minutes (EIA-364-32, test condition I)				
Humidity	See Product Qualification and Test Sequence Group 4	Mated Connector 40°C, 90~95% RH, 96 hours. (EIA-364-31,Condition A, Method II)				
Temperature life	See Product Qualification and Test Sequence Group 5	Subject mated connectors to temperature life at 85°C for 96 hours. (EIA-364-17, Test condition A)				
Salt Spray (Only For Gold Plating)	See Product Qualification and Test Sequence Group 6	Subject mated/unmated connectors to 5% salt-solution				
Solder ability	Tin plating: Solder able area shall have minimum of 95% solder coverage. Gold plating: Solder able area shall have minimum of 75% solder coverage	And then into solder bath, Temperature at 245 ±5°C, for 4-5 sec. (EIA-364-52)				
Resistance to Wave Soldering Heat	See Product Qualification and Test Sequence Group 10 (Lead Free)	Solder Temp. : 265±5°C, 10±0.5sec.				


Note. Flowing Mixed Gas shell be conduct by customer request.



TITLE: FPC 0.5 PITCH EASY ON FPC CONN

6 INFRARED REFLOW CONDITION

Lead-free Process



connectors					
C	ᇀ	5			

TITLE: FPC 0.5 PITCH EASY ON FPC CONN

7 PRODUCT QUALIFICATION AND TEST SEQUENCE

	Test Group									
Test or Examination	1	2	3	4	5	6	7	8	9	10
	Test Sequence									
Examination of Product	1、3	1 . 8	1 . 7	1、6	1 \ 4				1	
Low Level Contact Resistance		2 \ 11	2 \ 10	2 · 9	2 \ 5				3	1 \ 4
Insulation Resistance		3 \ 10	3、9	3、8						
Dielectric Withstanding Voltage		4 \ 9	4 \ 8	4 · 7						
Temperature rise	2									
Durability		6								
Vibration										2
Shock (Mechanical)										3
Thermal Shock			5							
Humidity			6							
Temperature life				5						
Salt Spray					3					
Solder ability						1				
FPC Retention Force		5 . 7								
Terminal / Housing Retention Force							1			
Fitting Nail /Housing Retention Force								1		
Resistance to Soldering Heat									2	
Sample Size	2	4	4	4	4	2	4	4	4	4



TITLE: FPC 0.5 PITCH EASY ON FPC CONN


RELEASE DATE: 2014/10/15 REVISION: B ECN No: ECN-1410022 PAGE: **10** OF **11**

8 INSTRUCTION UPON USAGE


Operation

FPC/FFC Termination procedure. Connector installed on the board.


1) Lift up the actuator. Use thumb or index finger.



2) Do with the actuator opened completely, and insert it in the interior of the insertion entrance surely when you insert FPC/FFC. There are some insertion resistance because this connector has the FPC/FFC temporary retention mechanism.




3) Rotate down the actuator until firmly closed. It is critical that the inserted FPC/FFC is not moved and remains fully inserted. Should the FPC/FFC be moved, open the actuator and repeat the process, starting with Step 1 above.




FPC/FFC Removal

- 1) Lift up the actuator.
- 2) Carefully remove the FPC/FFC.




Precautions


Do when yon pull out mating FPC/FFC with the Actuator opened completely. Confirm whether to Have adhered to the terminal contact part before FPC/FFC is mated with the connector housing when the opening of the actuator is the un-complete and FPC/FFC is pulled out.



Do not add the load mating FPC/FFC with connector housing.



 Due to the structure of the connectors, they do not have string resistance to upward pulling; therefore, support the FPC/FFC when a pulling force is applied to it.





TITLE: FPC 0.5 PITCH EASY ON FPC CONN

RELEASE DATE: 2014/10/15 REVISION: B ECN No: ECN-1410022 PAGE: **11** OF **11**

Precautions

4)This connector is small and thin and requires delicate and careful handling.

Be very careful not to apply any force to the FPC after inserting it.

Otherwise, the connector may become unlocked or the FPC may break.

Fix the FPC, in particular, when loads are applied to it continuously.

Design the FPC layout with care not to bend it sharply near the insertion opening.

