



## Installation Instructions

### Electrical Sub-base Assembly

#### For Use with PTAC and PTHP Models



Please read these instructions completely before attempting installation.

NOTE: These instructions apply to the installation of the Electrical Sub-base assembly.

Contents:

1. Sub-base Assembly
2. Side brackets, adjustable
3. Wire nuts (x 3)
4. #10 screws (x 4)
5. Installation instructions

**NOTE: All electrical work must conform to local codes and ordinances, the national electrical code, ANSI/NFPA NO. 70-1993 or current edition, and in Canada, the Canadian electrical code PART I, CSA STANDARD C22.1-1993 or current edition.**

 <b>WARNING</b>	
	<p><b>Electrical Shock Hazard</b></p> <p>Turn off electrical power before service or installation.</p> <p>ALL electrical connections and wiring <b>MUST</b> be installed by a qualified electrician and conform to the National Code and all local codes which have jurisdiction.</p> <p>Failure to do so can result in property damage, personal injury and/or death.</p>

**Step 1.** Disconnect ALL power to unit.

**Step 2.** Using Sub-base as a guide, mark the location for the mounting holes (See Figure 2). Drill a 1/8" hole on each side of the Wall Sleeve.

**Step 3.** Side brackets can be attached to the sub-base to cover the open space between the wall and sub-base. Bend the bracket to size. Slip the bracket inside the sub-base and use the adjustable mounting hole to adjust fit against the wall. See Figure 3.



- Step 4.** Route building power through knockouts provided for conduit connectors into junction box. See Figure 4.
- Step 5.** Remove Left access cover and connect building power wires to the receptacle wires using wire nuts and replace cover. See Figure 5.
- Step 6.** Using screws provided, attached sub-base to wall sleeve using the drilled holes from Step 2. Be careful not to over tighten screws.
- Step 7.** Adjust legs to level the sub-base. See Figure 6.
- Step 8.** Remove Right access cover. Push excess cord through opening on the right. Plug the power cord into the receptacle. Re-install access cover making sure cord is routed through notch in sub-base.
- Step 9.** Re-connect power to unit

