



Overview

- This UL Recognized power supply/charger converts a 115VAC/60Hz input into a single 12VDC or 24VDC non-power limited output.

Specifications

- | | |
|---|--|
| <ul style="list-style-type: none"> • 12VDC or 24VDC selectable operation. • 6 amp supply current. • Non-power limited output. • Input 115VAC 60Hz, 1.9 amp. • Filtered and electronically regulated outputs. • Short circuit and thermal overload protection. • Built-in charger for sealed lead acid or gel type batteries. | <ul style="list-style-type: none"> • Switching Power Supply/Charger. • Maximum charge current @ .7 amp. • Automatic switch over to stand-by battery when AC fails (zero voltage drop). • AC fail supervision (form "C" contacts). • Low battery supervision (form "C" contacts). • Battery presence supervision (form "C" contacts). • AC input and DC output LED indicators. |
|---|--|

Agency Approvals



UL Recognized component for Access Control System Units (UL 294)
Power Supplies for use with Burglar-Alarm Systems (UL 603)
Standard for Safety for Fire Protective Signaling Systems (UL 1481).

Board Dimensions (approximate):

AL600ULXB: 5.1"W x 7.8"L x 2.6"H

