

# Model 393-00x

# **Emergency Hands-free Telephones**

### **Features**

- Weather-Resistant Wall-Mount Design, Type-3R
- Telephone Line Powered, (No Battery or External Power Required for Telephone Operation)
- Large "Palm" Activation HELP Pushbutton For Emergency Call
- Standard or SMART Operation
- Auto Answer (with Silent Monitoring)
- (2) Programmable Auxiliary Outputs for Peripheral Equipment Control
- Operating Range of -20°C to +60°C
- Call Received When Lit LED
- Voice Annunciation Option
- Extreme Cold Weather Option (-40°C)
- 3-Number Rollover
- UL/CSA 60950 Compliant
- FCC Part 68 Certified
- ADA Compliant
- Monitored by TMA (Telephone Management Application) Software

GAI-Tronics' RED ALERT® Emergency Telephones are designed to provide clear and reliable communications in almost any environment. The model 393-00x is considered to be Type-3R weatherproof compliant when installed on any flat surface.

The 393-00x RED ALERT® Emergency Telephones provides reliable two-way communications with the press of a single button and can be installed on any analog PSTN, PBX, PABX, or KSU network providing 24 V dc or 48 V dc line voltage with a minimum line current of 24 mA. **No external power is required for normal operation.** 

The Model 393-00x is capable of providing two (2) auxiliary outputs for control of peripherals such as strobes, door/gate access, alarms, or lamps via local or remote activation. These outputs can be programmed for a variety of control parameters including telephone HELP button or remote DTMF activation. Each telephone can additionally be configured to automatically answer when called.

Each telephone is ADA compliant, with a "Call Received When Lit" L.E.D. providing visual indication that a call is active and a Braille HELP label.



Although each of these telephones will function as a standard Emergency Telephone, connecting a customer-provided, central computer equipped with GAI-Tronics' TMA (Telephone Management Application) software will allow them to operate in SMART (Self-Monitoring and Reporting Technology) mode. With TMA connected, each RED ALERT® telephone will be polled on a scheduled basis to report:

- Line integrity
- Microprocessor health
- Stuck buttons
- Microphone integrity

email: info@gai-tronics.com

- Speaker integrity
- Line interrupt (power failure)
- Low Battery (Voice Annunciation Option only)

Additionally, each RED ALERT® Emergency Telephone is available with a user programmable Voice Annunciation option and/or an Extreme Cold Weather option (to -40°C).

www.gai-tronics.com Toll Free: 1-800-492-1212



## Model 393-00x

# **Emergency Hands-free Telephones**

## **Specifications**

TMA compatibility profile type . . . . GTC SMART Hands-free

#### **Electrical**

Audio Output
@ 1 meter with 40 mA loop current
Battery Voltage (tip and ring)24 V dc or 48 V dc
Phone line requirements Loop start, central office
(CO), or Analog station port (PBX, PABX, or KSU)
Minimum loop current
(35 mA recommended)
(2) Auxiliary outputs (Isolated solid state switch)
48 V dc @ 125 mA
28 V <sub>RMS</sub> ac @ 80 mA <sub>RMS</sub>
Signaling DTMF 100 ms tone
Memory Non-volatile EEPROM

#### Mechanical

**Operating Temperature Range:** 

#### **Approval Standards**

#### **IC information (Canada)**

IC Certification Number	882B-GTC 2010
Ringer Equivalent Number	
Connection Method	CA11A

### **Model Chart**

Model	Description	
393-001	Weatherproof, Surface-mount, One-Button, Emergency Telephone , Valox	
393-002	Weatherproof, Surface-mount, One-Button, Emergency Telephone, Valox with Voice Annunciation Option	
393-003	Weatherproof, Surface-mount, One-Button, Emergency Telephone, Valox with Extreme Cold Weather Option	
393-004	Weatherproof, Surface-mount, One-Button, Emergency Telephone, Valox with Voice Annunciation Option and Extreme Cold Weather Option	
12509-037	TMA Application Package (includes single line transceiver, security key, interconnecting cables, software CD, and manual)	
12509-036	TMA Line Expansion Kit; one required for each additional monitored line…8 max. (includes single line transceiver, interconnecting cables, and manual)	
233-001	Security Screwdriver	



