

## MODEL NUMBER:



The B140-004 transmits a DVI-D Single-Link signal to four monitors up to 200 ft. away using a single Cat5e/6 patch cable. To achieve maximum distance and resolution, use 24AWG Solid Wire Cat5e/6 cable (Tripp Lite's [N202-Series](#)). An additional DVI port is provided for the connection of a local monitor. This local DVI port can also be used to daisychain up to 3 units together, allowing for the connection of up to 13 monitors (12 remote, 1 local). Mounting hardware is included that allows the unit to be rackmounted, wallmounted or pole mounted. In addition, up to three units can be mounted in 1U of rack space using a Tripp Lite [B132-004-RB](#) 19" rackmount bracket. The B140-004 is compatible with all operating systems, and is plug and play, with no software or drivers required. Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases.

Installation is simple. Connect the B140-004 transmitter to a DVI source using a Tripp Lite [P561-Series DVI cable](#) (not included). Connect a Tripp Lite B140-series receiver (not included) to each display using a Tripp Lite [P561-Series DVI cable](#) (not included). Finally, each remote receiver is connected to an RJ45 port on the B140-004 using a single Cat5e/6 cable.

For longer extension distances, use a [B140-1A0](#) or [B140-1A0-WP](#) active receiver unit to extend a 1920 x 1080 @ 60Hz signal up to 150 ft., or a 1024 x 768 @ 60Hz signal up to 200 ft..

For shorter extension distances, use a [B140-1P0](#) or [B140-1P0-WP-1](#) passive receiver unit to extend a 1920 x 1080 @ 60Hz signal up to 50 ft., or a 1024 x 768 @ 60Hz signal up to 100 ft..

Further expand the range and number of monitors by using a [B140-110](#) repeater unit. Add up to four remote units (three repeaters and one active receiver) to each channel of the B140-004, for a total of 4 displays per channel. (An active receiver should be the last unit in a channel) A 1920 x 1080 @ 60Hz signal can be extended up to 125 ft. from each repeater to the next unit in the channel, or a 1024 x 768 @ 60Hz signal can be extended up to 175 ft.

- Supports DVI-D Single-Link video resolutions up to 1920 x 1080 @ 60Hz
- For longer distances - Use a [B140-1A0](#) or [B140-1A0-WP](#) active receiver unit to extend a 1920 x 1080 @ 60Hz signal up to 150 ft., or a 1024 x 768 @ 60Hz signal up to 200 ft.
- For shorter distances - Use a [B140-1P0](#) or [B140-1P0-WP-1](#) passive receiver unit to extend a 1920 x 1080 @ 60Hz signal up to 50 ft., or a 1024 x 768 @ 60Hz signal up to 100 ft.
- Use 24AWG, Solid Wire Cat5e/6 cable, such as Tripp Lite's [N202-Series](#), to achieve maximum distance and resolution
- Can further expand the range and number of monitors by adding [B140-110](#) repeaters
- Compatible with all operating systems
- Plug and play, no software or drivers required
- Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases
- B140-004 DVI Over Cat5 Extender/Splitter, 4-Port Local Transmitter Unit
- 1 ft. DVI daisychain cable
- Mounting hardware
- External power supply (Input: 100-240V, 50/60Hz, 0.5A Output: 5V, 2A)
- Owner's Manual



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
www.tripplite.com

- Transmit a DVI-D Single-Link signal to four monitors up to 200 ft. away using a single Cat5e/6 patch cable
- Supports DVI-D Single-Link video resolutions up to 1920 x 1080 @ 60Hz
- For longer distances - Use a [B140-1A0](#) or [B140-1A0-WP](#) active receiver unit to extend a 1920 x 1080 @ 60Hz signal up to 150 ft., or a 1024 x 768 @ 60Hz signal up to 200 ft.
- For shorter distances - Use a [B140-1P0](#) or [B140-1P0-WP-1](#) passive receiver unit to extend a 1920 x 1080 @ 60Hz signal up to 50 ft., or a 1024 x 768 @ 60Hz signal up to 100 ft.
- Use 24AWG, Solid Wire Cat5e/6 cable, such as Tripp Lite's [N202-Series](#), to achieve maximum distance and resolution
- An additional DVI port is provided for the connection of a local monitor. This local DVI port can also be used to daisychain up to 3 units together, allowing for the connection of up to 13 monitors (12 remote, 1 local).
- Further expand the range and number of monitors by using a [B140-110](#) repeater unit
- Add up to four remote units (three repeaters and one active receiver) to each channel of the B140-004, for a total of 4 displays per channel. (An active receiver should be the last unit in a channel)
- A 1920 x 1080 @ 60Hz signal can be extended up to 125 ft. from each repeater to the next unit in the channel, or a 1024 x 768 @ 60Hz signal can be extended up to 175 ft.
- HDCP compatible
- Compatible with all operating systems
- Plug and play; no software or drivers required
- Mounting hardware is included that allows the unit to be rackmounted, wallmounted or pole mounted. In addition, up to three units can be mounted in 1U of rack space using a Tripp Lite [B132-004-RB](#) 19" rackmount bracket.
- Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases

RoHS	Y
Chromebook Compatible	No
Display Style	Splitter
Model Type	DVI
Cable Types	CAT5/CAT5E
Optional Mounting Accessory Notes	Up to three <a href="#">B140-004</a> local units can be mounted in 1U of rack space using a Tripp Lite <a href="#">B132-004-RB</a> Extender/Splitter 19in rackmount bracket
Unit Dimensions (hwd / in.)	1.125 x 5 x 4
Unit Dimensions (hwd / cm)	2.86 x 12.7 x 10.16
Included Mounting Accessories	Yes
Color	Black



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
[www.tripplite.com](http://www.tripplite.com)

Connector A	RJ45 (FEMALE) (X4)
Connector B	DVI-I (FEMALE) (X2)
Product Warranty Period (Worldwide)	1-year limited warranty

© 2015 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.