

# 1078CW-N



**interlogix**  
A UTC Fire & Security Company



Made in China

Res and Com Magnetically Actuated Switch

## SPECIFICATIONS:

Gap Distance:	2" (in wood), Up to 3/4" (in steel)
Loop Type:	Closed
Voltage:	100V AC/DC MAX
Current:	0.5 A MAX
Power:	7.5 W MAX
Electrical Configuration:	NO

## INSTALLATION INSTRUCTIONS:

**Step 1:** Drill 0.75" diameter hole for both contact and magnet.

The hole for the contact should be drilled 1.125" deep, while the hole for the magnet should be drilled 1.563" deep. (Hole arbors available from Sentrol)

**Step 2:** Connect contact leads to security system loop and test for continuity.

**Step 3:** Lightly coat the contact and magnet with RTV mounting compound (Sentrol Part Number 1905) and insert into their respective holes.

4

13234



\*1078CW-N\*



0

46188 01563

4