



eFlow104NX

Overview

eFlow104NX is a power supply/charger that converts a 120VAC 60Hz input into a single 24VDC output with a total of 10 amps max. The unit includes an unswitched aux. output. It also offers a suite of features that includes fire alarm disconnect, overvoltage protection, and low power disconnect which prevents deep discharge of stand-by batteries.



Specifications

Input:

- 120VAC, 60Hz, 4.5 amp.
- Input fuse: 5A/250V.

Output:

- 24VDC @ 10.0 amp supply current.
- Auxiliary power-limited output rated @ 1 amp (unswitched).
- Overvoltage protection.

Battery Backup:

- Built-in charger for sealed lead acid or gel type batteries.
- Maximum charge current 1.54 amp.
- Automatic switch over to stand-by battery when AC fails. Transfer to stand-by battery power is instantaneous with no interruption.

Supervision:

- AC fail supervision (form "C" contacts).
 - Notification trigger is selectable for 30 seconds (factory set) or 2 hours.
- Battery fail and presence supervision (form "C" contacts).
- Low power shutdown. Shuts down DC output terminals if battery voltage drops below 70-75% (depending on the power supply). Prevents deep battery discharge.

Fire Alarm Disconnect:

- Supervised Fire Alarm disconnect (latching or non-latching) 10K EOL resistor. Operates on a normally open (NO) or normally closed (NC) trigger.

Electrical:

- Operating temperature: 0° C to 49° C ambient.
- BTU/Hr.: 124.85 BTU/Hr.
- System AC input VA requirement: 540VA.

Visual Indicators:

- Green AC Power LED indicates 120VAC present.
- AC input, DC output, and Battery LED indicators.

Additional Features:

- Short circuit and overload protection.
- Unit is complete with power supply, enclosure, battery leads and cam lock.

Mechanical:

- Enclosure Dimensions (H x W x D approx.): 15.5" x 12" x 4.5" (393.7mm x 304.8mm x 114.3mm)
 - Accommodates up to two (2) 12VDC/12AH batteries.
- Product weight (approx.): 8.65 lbs. (3.92 kg).
- Shipping weight (approx.): 9.75 lbs. (4.42 kg).

Agency Approvals



- UL 294 UL Listed for Access Control System Units.
- UL 603 UL Listed for Power Supplies for Use with Burglar-Alarms Systems.
- UL 1481 UL Listed for Power Supplies for Fire Protective Signaling Systems.



- ULC-S318-96 - Power Supplies for Burglar Alarm Systems. Also suitable for Access Control.



- CE - European Conformity



- CSFM - California State Fire Marshal Approved.

