



Professional Smart Security

BAT-Connect Communicator

BAT-CONNECT-V, BAT-CONNECT-A

BAT-Connect is engineered for professional security dealers and integrators who want the most versatile communicator on the market. The universal dual-path communicator can be used with most hardwired or hybrid panels. LTE-M cellular technology and automatic panel detection allows alarm dealers to complete more installations and skip the next cellular sunset.



alula.com/bat-connect

Offer a modern interactive experience on new and existing systems with the Alula Smart Security app. Customers can arm and disarm the system, view cameras, control smart devices and initiate scenes right from their phones or the Slimline Touchpad PRO interface.

Why Choose BAT-Connect?

- » **Works with most panels**
You'll always have the right part for the job with this universal communicator
- » **Saves money**
Equipped with LTE-M technology so you can skip the 4G sunset
- » **Eliminates service hassles**
Remote programming, troubleshooting, and over-the-air firmware updates will fix most issues
- » **Faster and easier installations**
Automatic panel detection and zone configuration means less work for you

Features

- » Provides interactive services, home automation, and the ability to update the user interface on existing panels without panel replacement
- » Three network connectivity paths: cellular, ethernet, and Wi-Fi
- » Full interactive support of Honeywell Vista, DSC PowerSeries, Interlogix NX, Interlogix Concord, and Napco panels
- » Telco event capture and reporting on most legacy panels using phone line emulation
- » Keyswitch arming for remote control of most legacy panels
- » Optional remote control is available via the Alula Security app from the Apple App Store or the Google Play store

Technical Specifications

Physical

Housing Dimensions	8.5 x 5.0 x 1.3 in
Weight	10 oz
Mounting Fasteners	#6 screws & wall anchors (included)
Cover Securing Screw	#4 screw (included)

Environmental

Operating Temperature	32° F to 120° F
Maximum Humidity	85% non-condensing relative humidity

Device

Reported Indications	Cover tamper, Wall tamper
Current Draw	100mA, Maximum: 300mA
Input Voltage	9-14V DC

Communications

Cell	Yes
Ethernet	Yes
Wi-Fi	Yes, local network

Accessories

RE048	Antenna, LTE, MMCX/M R/A, 90mm Cable
RE036	Antenna, LTE, MMCX, 2.5m Cable
RE036-0	Antenna, LTE, MMCX, 0.3m Cable
RE046	Antenna Assembly, LTE, Sidemount, 1-piece bag
ANTENNA-CBL-5	Cellular External Antenna Cable, 5 pieces
RE049	BAT-Connect, DSC PC-Link Cable
RE050-4	Antenna, Indoor/Outdoor, Cellular, 4' Coax, Kit
RE050-20	Antenna, Indoor/Outdoor, Cellular, 20' Coax, Kit
RE050-50	Antenna, Indoor/Outdoor, Cellular, 50' Coax, Kit
RE050-100	Antenna, Indoor/Outdoor, Cellular, 100' Coax, Kit

Models

BAT-CONNECT-V (Verizon), BAT-CONNECT-A (AT&T)

Regulatory

FCC, IC

Compatibility

Honeywell	DSC	Interlogix	NAPCO
Vista 15p	PC1616	NX-4/NX-4V2	GEM P800
Vista 20p	PC1832	NX-6/NX-6V2	GEM P801
Vista 21ip	PC1864	NX-8/NX-8V2	GEM P816
First Alert FA148CP	PC5020	NX-8E	GEM P1632
First Alert FA168CP	PC580	Concord 4	
Safewatch Pro 3000	PC1555/1555MX PC5010		

Tip and ring support for all Contact ID panels including:

Honeywell: Vista 10p, 15p, 20, 128

DSC: Alexor, Impassa, Neo

Interlogix/GE: Concord 2, 3 Express