

MODEL: 354011 - CODE STATION



354011

FEATURES

- Extra large back-lit button for easier activation
- Elapsed timer output
- Call-assurance LED
- Plug-in connectors for easy service
- Continuous supervision of station
- Optional antimicrobial Bio-seal to cover buttons and allow for easy disinfecting of the station

SPECIFICATIONS

Power Required: 6A @ 18VDC

Weight: 0.2 lbs (0.8 kg)

Size: W: 3.2" (8.0 cm)

H: 4.25" (10.8 cm)

D: 0.6" (1.5 cm) in back box: 0.5" (1.3 cm) off-wall

Housing and Finish: High-impact molded Cycloy 2950
UL 94-5VB; light grey faceplate

Controls/ Indicators: One (1) push button for call actuation, One (1) Call-assurance LED, One (1) Cancel button

Terminations: Plug-on connector

Backbox Requirement: 1 gang (Non-gangable), 3 1/2" Deep

DESCRIPTION

The Code Station is a call pushbutton station providing the ability to place a code call. Pressing the cancel button cancels the call. This station provides an output for an elapsed timer supporting a momentary or latched contact closure output. The Code Blue button is back-lit for easier location in dark room. Using special buttons, the stations can be customized for unique call-ins such as "Code Pink". The Code Blue station is connected to its associated corridor light or Domeless room controller and is continually supervised. A non-cancelable call annunciates at the associated console(s) when the station is removed from the system or a short occurs. The call will detail the location of the station (see Configuration and Installation Manual for details).

*Architect and Engineer (A&E) Specifications available online at: customerconnection.rauland.com
Specifications subject to change without notice*

©Copyright 2008 Rauland-Borg Corporation Printed in USA Rev 08/2008