

MODEL: R5K PATIENT STATION w ¼" JACK & BUTTON



R4K15V



FEATURES

- One (1) input for call cord or dry contact auxiliary alarm with Call-Assurance/Monitor LED
- One (1) call point with Call-Assurance LED
- Back-lit pushbutton for easy activation
- Cancel button
- Continuous supervision of station
- Programmable delay of call in
- Optional antimicrobial Bio-seal to cover cancel button and allow for easy disinfecting of the station
- Annunciates cord-out

SPECIFICATIONS

Power Required: 4mA @15VDC

Power Required when used with Speaker Module:
7mA @ 15VDC

Weight: 0.2 lb. (0.09 kg)

Size: W: 3.2" (8.0 cm)

H: 4.25" (10.8 cm)

D: 0.6" (1.5 cm) in back box: 0.5" (1.3 cm) off-wall

Housing and Finish: High-impact molded Cycloy 2950 UL 94-5VB; light grey faceplate

Controls/Indicators: One (1) ¼" Jack, One (1) Push button for call actuation, One Call-Assurance LED, One (1) Call-Assurance/Monitor LED, and One (1) Cancel button

Terminations: Plug-on connector

Backbox Requirement: 1-gang, Non-gangable [W: 2.25" (5.7 cm) H: 4" (10.2 cm) D: 3.5" (8.9 cm)]

Backbox Requirement when used with Speaker

Module: 3-gang, Non-gangable [W: 5.5" (14 cm) H: 3.75" (9.5 cm) D: 3.5" (8.9 cm)]

Certification: Designed for compliance to ANSI/UL 1069, IEC 60950, CE, RoHS / WEEE Compliant. Assembled in a U.S. FDA Registered facility.

DESCRIPTION

The Responder® 5000 Patient Station w ¼" Jack & Button provides the ability to place two unique call priorities from a resident single station. This station is typically installed in a resident room, in conjunction with Responder® 5000 Speaker Module and allows both residents and staff to place different call-in priorities, depending on their requirements. It can also be used to monitor medical equipment at the assigned console(s) or wireless devices. The R4K15V offers the added capability of placing an emergency call. The ¼" jack input is super-

vised, so if a call cord or piece of equipment is unplugged, a call will be placed.

The Single ¼" Jack & Button station is connected to its associated corridor light and is continually supervised for station presence. Through programming, a "Trouble" message can annunciate at the associated console(s) when the station is removed from the system.