



# ReadyMadeRC

## Wiring Adapter Modification for EZOSD Telemetry

The Male IRC to Female ReadyMadeRC style adapter allows the user to easily connect the ReadyMadeRC cables to ImmersionRC and FatShark equipment. Since many video transmitters have mono audio, and the ImmersionRC connectors are designed for stereo audio, there may be times that the user would want to change which channel on the IRC connector is being used for audio.

This is the case when the user wants to use the telemetry from the EZOSD system instead of the audio from the camera or a separate microphone. For video systems with mono audio, you will be able to select using the telemetry, or the audio from the microphone, but not both simultaneously.

The conversion is relatively simple. All you need is a tool with a sharp point such as a hobby knife.

The first thing to do is remove the yellow wire from the IRC connector. To do this, carefully press the metal tab down for the yellow wire so it no longer holds the wire in place, and gently pull out the connector.



Then, gently bend the clip back up as shown, and insert the connector into the outside slot. You're done!

