

MICRO MOTOR FM20 SERIES

Output : APPROX 1.0~2.5W
Weight : 24g (approx)



Application

Office Automation Equipment
Precision Instruments
Electric Shaver
CD Player
CD-ROM

| MODEL | VOLTAGE | | NO LOAD | | AT MAXIMUM EFFICIENCY | | | | STALL | | | |
|--------|-----------------|---------|----------------|--------------|-----------------------|--------------|----------------|----------------|-------------|----------------|----------------|--------------|
| | OPERATING RANGE | NOMINAL | SPEED r/min | CURRENT A | SPEED r/min | CURRENT A | TORQUE g-cm | TORQUE mN-m | OUTPUT W | TORQUE g-cm | TORQUE mN-m | CURRENT A |
| FM2002 | 1.0~4.0 | 3 | 3600 | 0.04 | 2781 | 0.14 | 7.02 | 0.69 | 0.20 | 30.86 | 3.02 | 0.46 |

Specification FM2002

DIRECTION OF ROTATION

