

## WAY ELECTRONIC CROSSOVER BX-55



**2/3 Way electronic crossover**  
**inputs: front, rear and subwoofer**  
**Outputs: front, rear and subwoofer**  
**Selectable crossover frequencies**  
**Subwoofer: 45hz-4.2khz**  
**Low Pass (Bandpass): 300hz-4.6khz**  
**Rear high pass: 65hz-4.5khz**  
**Front high pass: 65hz-4.5khz**  
**Variable Bass Boost, 0 - + 18db**  
**Slope rate: 12 db/octave**  
**Signal - to - noise ratio: > 110db**  
**Remote subwoofer level control**  
**Lowpass input selector: direct or Front/Rear mix**  
**Gold plated connectors**  
**Remote on/off power control**  
**Led power indicator**  
**Subwoofer phase switch**  
**Dimensions (W X L X H): 8 ¾ X 6 ½" X 1 ½"**