

OSLO 100

astro

GENERAL

LOCATION:	Exterior
CLASS:	cETLus (Class 1)
LOCATION RATING:	Wet
VOLTAGE:	Mains 120V
INSTALLATION ORIENTATION:	Wall Mount
FITTING METHOD:	4" Octagon Box
MAIN MATERIAL:	Metal - Aluminium
DIMENSIONS:	H:110mm W:110mm D:106mm H: 4.33" W: 4.33" D: 4.17"
CUT OUT HOLE:	Not Applicable
RECESS DEPTH:	55mm/2.16"
FIRE RATING:	Not Applicable
CABLE LENGTH:	Not Applicable
GROSS WEIGHT:	1.58lbs
ADA COMPLIANT:	No
IC RATING:	Not Applicable

LAMP

LIGHT SOURCE:	HIGH POWER LED
MAXIMUM WATTAGE:	3.4W
LAMP INCLUDED:	Yes (Integral)
MAXIMUM LAMP LENGTH:	Not Applicable
LUMINOUS FLUX:	89.35 lm
COLOUR TEMP:	3000K
CRI:	90
R9:	9.1
MACADAM ELLIPSE:	3-step
TILT ADJUSTABLE ANGLE:	Not Applicable
ROTATION ADJUSTABLE ANGLE:	Not Applicable
AVERAGE LIFESPAN:	60,000 hours
L70:	>60,000 hours
BEAM ANGLE:	To Be Advised

ELECTRICAL

SWITCHED:	No
DIMMABLE:	Not Applicable
DIMMING METHOD:	Not Applicable
DRIVER INCLUDED:	Yes (Integral)
DRIVER OUTPUT CURRENT:	700
DRIVER OUTPUT VOLTAGE:	Not applicable
SUPPLY FREQUENCY:	50/60Hz
DRIVER/BALLAST VOLTAGE:	100-277V
DRIVER AVERAGE LIFESPAN:	30000
EFFICACY:	26.28

ADDITIONAL INFORMATION

SHADE INCLUDED	Not Applicable
SHADE MATERIAL	Not Applicable



CODE: 1298010 (8076)
FINISH: TEXTURED WHITE



CODE: 1298011 (8077)
FINISH: TEXTURED BLACK



CODE: 1298012 (8078)
FINISH: TEXTURED GREY

TO MAINTAIN THIS PRODUCT TO ITS BEST CONDITION, PLEASE VIEW OUR CARE AND CLEANING GUIDE ON THE SUPPORT SECTION OF THE ASTRO WEBSITE.

Pour entretenir au mieux ce produit, veuillez consulter notre guide d'entretien et de nettoyage, dans la rubrique d'aide sur le site Web d'Astro.

Um dieses Produkt im besten Zustand zu erhalten, beachten Sie bitte unseren Leitfaden zu Pflege und Reinigung im Abschnitt „Support“ auf der Astro-Website.

Per mantenere questo prodotto nelle sue migliori condizioni, consultare la nostra guida per la manutenzione e la pulizia nella sezione dedicata all'assistenza del sito Web Astro.

PRODUCT ELEVATIONS

astro

Please note that some dimensions may vary slightly due to manufacturing tolerances, this includes cable entry and fixing holes.

