



<b>PRODUCT NAME</b>	1000W LED Power Supply CV, 24VDC
<b>SKU</b>	PS-MW-1000-24
<b>URL</b>	<a href="#">Click Here</a>
<b>DESCRIPTION</b>	This 1000W, 24VDC LED Power Supply / Transformer, has a 100 - 240AC input and 24VDC output. For dry locations only. Built in short circuit, overload, over voltage, and overheating protection allows for system shutdown upon any of these circumstances. Forced air cooling by built in DC fan allows for cool operating temperatures. Working temperatures are -4°F through 140°F. CN3 port allows for remote control of this power supply. It can be used to connect large amounts of LED Wall Washers, LED Lights, LED Light Ribbons, RGB LED lighting and any other 24VDC Constant Voltage LED Lighting products. UL and CE approved. Can connect up to 900 watts of 24VDC LED lights. Only install face up with sufficient breathing space.
<b>INPUT VOLTAGE</b>	100VAC - 240VAC
<b>DC OUTPUT</b>	24VDC / 41.7A
<b>OUTPUT WATTS</b>	1000 watts max
<b>HOUSING TYPE</b>	Aluminum
<b>DIMENSIONS</b>	L 10.94" X W 5.0" X H 2.5" (L 278mm X W 127mm X H 63.5mm)
<b>APPROVALS</b>	UL, CE
<b>RATING</b>	Dry
<b>WARRANTY</b>	1 year manufacturers

These specification are subject to change without notice. This specification information is from the manufacturer of this product. Ecolocity LED is not the manufacturer of this product. Copyright © 2014 Ecolocity LED