

CALLSHOP SCENARIO (checklist)

Login to the system as owner:

№	Check list with required steps	Done
Vendor section menu:		
Enter to the Destination sets page		
1.	Click Add Vendor (specify: name, currency, balance etc.)	
2.	Click action Open Connections	
3.	Click Add connection under the new created vendor (specify: name, destination(IP), username/password etc.)	
Routing section menu:		
Enter to the Destination sets page		
6.	Click Add Destination Set (specify: name, currency etc.)	
7.	Click Open Routes (it is prefixes and prices of your vendor)	
8.	Click Add Route or Upload Routes from file (add new prefixes and prices etc.)	
Enter to the Routing Groups page		
9.	Click Add Routing Group (specify: name, routing policy (active list), on-net routing (if requires), routing entries list)	
Tariffs & Currencies section menu:		
Enter to the Tariffs page		
10.	Click Add Tariff (specify: name, currency, avg call duration etc.)	
11.	Click Open Rates (it is prefixes and prices for your customers)	
12.	Click Add Rate or Upload Rate from file (add new prefixes and prices etc.)	
My Customers section menu:		
Enter to the Customers page		
13.	Click Add Customer (callshop) (specify: Customer name, tariff, routing group, balance, credit limit, Callshop Enabled etc.)	

Login to the system as Callshop customer:

№	Check list with required steps	Done
Tariffs & Currencies section menu:		
Enter to the Tariffs page		
1.	Click Add Tariff (specify: name, currency, avg call duration etc.)	
Enter to the Service Plan page		
2.	Click Add Service Plan (specify: name, basic tariff, billing cycle, billing type, on billing failure etc.)	
My Customers section menu:		
Enter to the Accounts page		
3.	Click Add Account (with zero balance) (specify: Account Name, Voip Login, Voip Password, Service Plan, Routing group, balance(should be zero), credit limit (should be zero) etc.)	
Callshop section menu:		
Enter to the Preferences page		

4.	Specify the Defaults/Behavior values. (specify the default values: Prepaid Amount, Credit limit and actions when you click Start and Stop on the page Callshop)	
Enter to the Callshop page		
5.	Click Start for some cabine/account to allow making calls from it (specify values: Prepaid Amount, Credit limit (if requires) or use the default values which you have specified above)	
6.	Click Stop to stop calls for some cabine/account	

