

J6-1(12core)limit

Core number	Wire number
1	224(red)
2	225(blue)
3	X positive(orange)
4	X negative(green)
5	Ypositive(green)
6	Ynegative(light yellow)
7	Z positive(light blue)
8	Z negative(gray)
9	
10	
11	
12	

J7-1(9core)Z-axis air valve

Core number	Wire number
1	102
2	10(air valve)
3	11(abrasive valve)
4	A+(red)
5	AC-(white)
6	A-(blue)
7	B+(green)
8	BC+(yellow)
9	B-(black)

J8-1(10core)

HP electric outlet of cutting table electric box

Core number	Wire number
1	X1 17
2	X1 18
3	X1 20
4	
5	X1 19
6	
7	X1 5
8	X1 6
9	
10	

A&V

www.avwaterjet.com

Pin chart of aviation electrical outlet

A&V Waterjet Tech. Inc

Design mark	Weight	Ratio
Total page		Page

Designed by		Date	
Checked by		Date	

APW-SK II - 5 - 2