

Connecting Resistograph to ToughBook via Bluetooth

Process

- 1) On the ToughBook, locate and tap the Wireless Switch Utility in the system tray near the Date/Time. It looks like a red dot with a yellow lightning bolt.



- 2) In the context menu, make sure Bluetooth Power ON. If not, tap this option to turn Bluetooth ON.
- 3) Locate, tap and hold the Bluetooth icon in the system tray near the Date/Time. In the context menu, select the Bluetooth Settings. In the General tab, make a note of the Device Name.
- 4) Locate, tap and hold the Bluetooth icon in the system tray near the Date/Time. In the context menu, select the Bluetooth Assistant.



- 5) The Bluetooth Assistant dialog will display and search for Bluetooth devices. This dialog will auto-dismiss after a few moments of searching.
- 6) While the Bluetooth Assistant is searching for Bluetooth devices, set the resistograph drill to discoverable using the following steps.
- 7) On the resistograph drill display, turn the knob to move the highlight option to the System Control Menu. Select the option by pressing the knob.



- 8) Locate and select the Bluetooth menu. The Bluetooth settings will display.



- 9) Confirm that Bluetooth State = ON and Mode = Active. If these are not set properly, move the highlight to each and correct the settings.
- 10) Move the highlight to the Connection section, then select New to establish a new connection.
- 11) In the Select Location screen, move the selector to a storage location to be used. If you select a storage location that is already used by another connection, the existing connection will be overwritten.

- 12) After selecting the storage location, new Bluetooth devices will be searched. When a Bluetooth device is found, it will be displayed.
- 13) If the first Bluetooth device found is NOT the ToughBook name that was noted in step 3 above, select NO to display the next Bluetooth device within range. Once the ToughBook name has been located, select YES to store the connection.
- 14) A dialog will be displayed on the ToughBook requesting a PIN. Enter 0000 then tap OK. If the device was able to establish the connection, then it will be stored.