Hotel Preferred Fresh Remote Operating Instructions

Automatic Function

- 1. Remote light can be on or off
- 2. Press and HOLD both [SETUP] and [CC] till remote light starts 3 flashes (hold 3~6 seconds).
- 3. Hold [SETUP] as long as the remote light starts on/continue blink= starts code searching; it will take a while to pair the codes
- 4. Be sure not to release button during paring (remote light should be keep on/continue blink, any break should go back to step 2.). Once the TV turns off, the pairing is successful.

You could also use the Learning function and code input to pair the remote quickly.

Learning function

- 1. Press and hold the key [SETUP] firstly, then long press [VOL+] about 5 seconds; the LED will be lit. Release the two keys. It is ready to learn.
- 2. Point the original remote control to the HP Fresh Remote. The distance should be within 1-3 cm.
- 3. Press the function key of original remote control, the LED of the HP Fresh Remote will keep flashing, then press any key of the HP Fresh Remote to learn the code.
 - 4. The Red LED of the HP Fresh Remote will stay on solid. Please repeat Step 2 to continue learning other function keys.
- 5. After learning all the keys, please press and hold the key [SETUP] firstly, then press [VOL-], the LED will be extinguished. The learning will be saved.

NOTE: During the learning process, if no key is pressed in 25 seconds the learning state will be exited without saving.

Code Input:

Find the 4 digital codes from the TV CODE LIST as attached:

- 1. Press and hold the device key [MUTE] firstly, then press and hold [POWER] key, after 3 seconds LED will light, release them.
- 2. Input the 4 digital codes. If the codes are right, the LED will be off. If not, the LED will flash 4 times and setting will be exited.
- 3. Test the remote control function keys. If it didn't work well, please repeat Step 1, 2, 3 and try other codes.

NOTICE: During the whole set up process, if no key is pressed in 10 seconds the setting will be exited.

BRAND	TV/LCD CODE	BRAN	ID I	TV/LCD CODE	BRAND	TV/LCD CODE
		DAYTRON		14,1301	KOLIN	1200,1201,1202,1203
		DELUX	10:		KONKA 1038	,1062,1086,1218,1255,1258,1350.1427.1428.1429
3517 (AGT) 11 3548 (AGT) 11		DENON	10	09	KOTRON	1074
3550 (AGT) 11		DIAMOUD	10	39 41(MODEL:100840)	KTV KURAZAI	1002,1019,1032,1114,1298,1302,1303,1306
ACTION 10 ADMIRAL 1048.1:	298.1299.1008.1015.1027.1072.1259.1346	DISNEY	12	58	KWORLD LCD(3517)	1170,1294
ADVENT 12	57,1278,1002,1034	DUMONT DURABRAND	10	87,1098,1015,1301 20,1081,1113,1141,1348	LCD(3517) LEXUS	1176 1020
ADVENTURA 13 AIKO 11	65,1032,1399	DWIN	10	08,1072	LG	1022 1011 1044 1301 1183 1001 1358
	43	DYNASTY DYNEX	10	19,1028,1032	LODGENET	1359,1360,1361,1299,1015.1392.1384 1299,1324
AIWA 10 AKAI 12 AKAWA 10 AKIO 10 AKISHI 10 ALARON 12	43 19.1024 04.1216.1217.1255.1301.1010 19.1298.1302.1303 76.1082.1012.1032.1033.1304	ELECTROBAND	10	60,1261,1279,1278 02,1306	LOEWE	1034
AKAWA 10	19.1298.1302.1303	ELECTROHOME ELECTROLIGHT	11	14.1408	LOGIK	1148,1153,1155,1299
AKISHI 10	76,1082,1012,1032,1033,1304	ELECTROTUNE	13:		LUXMAN	1301
ALARON 12	98	ELEKTRA	10	11,1074,1019,1023,1032,1044,1033,1114	LXI	1003,1008,1015,1021,1034,1072,1301,1355
ALFIE 10 ALLEGRO 10	172	ELEMENT	12	18,1299,1301,1303,1304,1326 81,1282,1283,1284	MAGNAVOX 103 MAJESTIC	34,1076,1114,1298,1301,1306,1317,1325.1430.1431.1432.1362 1034,1301
AMARK 13 AMBASSADOR 10	04,1028,1043,1002	ELTEC	13-	42	MATSUI	1034
AMERICAN ACTION 10		EMERSON	1013.1026.1 1038 1114 1	062.1087.1199.1014.1019.1020.1021.1023.1027.1033 198.1259.1298.1301.1303.1306.1341.1343.1409.1410	MATSUSHITA MAXENT	1014
AMPRO 10			1411.1412.1	413.1414.1415	MEGATRON	1009,1028,1043,1301
	119 31,1014,1019,1028,1043,1305	ENVISION	12	50,1251,1252,1253,1254	MEI	1306
ANAM NATIONAL 13	05	ER-21613(XZ415	i) 12: 10:		MEMOREX MERRITT	1182,1188,1270,1014,1021,1259,1298,1299,1301,1304 1032
AOC 1250,1251,125 AOMI 13	2,1253,1254,1301,1306,1400,1401,1402 65	FEEL-NOLOGY		04,1105	MGA	1301
	20,1269	FISHER FLO	12:	21,1317,1060,1075,1077,1106,1112,1113,1180	MICROSONIC MIDI AND	1048 1008,1015,1114,1317,1355
ASAHI 11	13	FUJITSU	13	14,1320,1317 12,1013,1019,1067,1198,1199,1298.1416	MIDLAND MIKADO	1010,1304
ASCENT (LCD) 10 AUDIOLOGIC 10		FUNAL	10	12,1013,1019,1067,1198,1199,1298.1416 13,1125,1132,1141	MILLROCK	1194
AUDINAC 10	48,1076,1019	FUTRONIC FUTURETECH	10	19	MITSUBISHI	1006,1046,1065,1082,1287,1301,1059,1072
AUDIOVOX 10	19,1020,1032,1033,1120	GE	100	77,1008,1010,1088,1120,1015,1017,1018,1031 33,1043,1072,1081,1301,1305,1317,1347,1355	MITSUI	1023,1002,1019,1020,1038,1142,1218,1341,1343
AUDITRON 13 AURORA 11	64	GFM	10	13,1198,1199	MITACHI MONTGOMERY WARD	1019 0 1002,1072,1301
BAYSONIC 10	19,1062	GIANT	10	32,1064	MOTEVA	1012
BELCOR 13 BELL&HOWELL 10	21,1299	GIBRALTER GOLDMUND	111	15,1301 18	MOTOROLA MTC	1072,1305,1456 1019,1114,1300,1301,1304,1306
BENO(LCD) 13	31	GOLDSTAR	1044,	1097,1183,1114,1301,1028.1417.1418.1419	MULTITECH	1019
BGH 10	48,1090,1104,1105,1337 66,1169,1019	GOLDTEXT	10:		MUSTANG NAD	1107,1167 1003,1301,1344
BLUESKY 11 BLUE LIGHT(LCD) 10	07,1334 19,1303,1304	GO VIDEO	10	10,1304	NAOKI	1037,1020
BLUE PUINT 10	19,1303,1304	GRADIENTE GRUNDIG	100	05,1033,1058,1061,1063,1070,1080,1301 64,1055(SAT),1056(VIDEO),1096	NEC NEWTECH	1321,1095,1301,1305,1259,1340 1021
BROCKWOOD 13	01	GRUNPY	10	19.1298	NICO	1026
BROKSONIC 10	19,1026,1027,1028,1029,1031,1033,1043 67,1071,1074,1259,1299,1302,1308,1164	HAIER HALLMARK	1348,	1219,1221,1267,1268,1269,1270,1271,1272,1289	NIKKO NIPPON	1003,1015,1021,1032,1301 1301
BROKSONIC 1-14 13	108	HANSTAI	13	00	NOKIA	1078
BROKSONIC 1-16 10 BROKSONIC LETRAS 10	31	HANTEK	0N 10	19	NOBLEX	1021,1066,1068,1084,1085,1093,1117,1158
CALCULADORA 10	78	HARMAN/KARD HARLY DAVIDSO	ON 12	98	NORCENT	1163,1164,1171,1173,1175,1177.1393.1389 1252,1269,1332
CAMIVALE 10	01,1076	HARVARD	10		NOSHI	1316
CARVER 10		HAVERMY HCI	10	72 96,1197	NUEVO NTC	1048 1032
CARREFOUR 11 CCE 1022.1024	68	HDE	113	31	NU-TEC	1289
CEGESA 11	,1033,1047,1057,1064,1067,1068,1073,1076 62	HELLO KITTY	10:	1089 1021 1234 1266 1083 1111 1114 1001	OLEVIA(LCD) OLIVIA	1327,1202.1455 1200,1201,1202,1203,1327
CELEBRITY 10 CELERA 12	02 67,1269,1003	HITACHI 1		1089.1021.1234.1266.1083.1111.1114.1001 1301.1309.1310.1420.1422.1421.1425.1390	OLYMPIC	1048
CENTURION 13	01	HIMITSU	10	19,1038 26,1130,1141,1154,1157,1169,1290	ONCOMMAND ONKING	1323
CENTURY 10	19,1032,1114	HISENSE HITECH	110	03	ONWA	1019
CETRONIC 10 CHANGHONG 10		HP	124	33 1047 1064 1067	OPTIMUS	1014,1021,1344 1005
CHASSIS 10 CHONGUI 11	39,1113	HPS HYUNDAI	10:	33,1047,1064,1067 20,1021,1108,1148,1289	OPTONICA	1072,1340,1346
CINERAL 10	32,1033,1048,1050,1081,1092	ILO	123	33,1349,1352	ORION	1278,1026,1259,1298
CITIZEN 13	04,1032,1114,1259,1299,1301,1303	INSIGNIA		34 1257,1258,1259,1260,1261,1277,1278,1279,1280.1470	PACK PACIFIC	1032 1019
CLAIRTONE 13 CLARION 10		INTEQ	10	15	PACKARD BELL	1019,1032,1114,1299,1304
CLASSIC 10	19	JBL	10 10	34	PANASONIC	1014,1069,1021,1023,1030,1031,1072,1229 1230(ID),1301,1304,1305,1340,1346.1454
COBY 14 COLOMBIA 10	-65	JCB	10	02	PANATRONIC	1259,1302
CONCERTO 13	01 16,1159	JC PENNEY JEC	10	33,1008,1114,1301,1304,1316,1317,1347,1355 34,1298	PANABLACK PAXAN	1014
CONVERSOR 11	16,1159	JEC JENSEN	10	02.1034	PDI	1183,1184,1185,1186
CONTEC 10 CORONADO 10	19.1306.1403 02,1114	JERROLD JVC		35,1036 31,1259,1005.1426	PHILCO	1019,1020,1025,1032,1033,1002,1009,1034,1038,1045,1052 1072,1076,1114,1259,1301,1305,1306,1317,1074,1088,1341,1343
CRAIG 10 CROSLEY 10	19	JWIN	11	04	PHILCO-VCR	1052
CROWN 10	85.1107.1167.1002.1019.1114.1302	KAWASHO KEC	13 10	13	PHILIPS 1001	1,1005,1016,1339,1034,1012,1047,1050,1051,1345,1053,1433 7,1066,1067,1184,1187,1213,1214,1215,1222,1252,1325.1382
CURTIS MATHES 1220,10	08,1009,1010,1021,1033,1034 14,1299,1301,1304,1344,1355.1404	KENBROWN	10	26	PHILIPS RC2144	1051
CXC 10	19	KENWOOD KINGSEI	10 10	02,1301 29	PHILIPS-MAGNAVOX	1001,1005,1016,1034,1012,1339,1047,1050,1051,1053 1057,1066,1067,1184,1187,1213,1214,1215,1222,1252
CYBER HOME 13 DAEWOO 1033.1032.1114.1120.1	38,1002	KIREY	10	19	PILOT	1114.1301
DAYTEK 11	1218.1301.1019.1002.1458.1405.1406.1407 20,1292	KOWBNOW	10 10		PIONEER	1010,1301,1309,1344.1434 1188,1189,1205,1206,1207,1208,1209,1210,1211,1330
		попынон	10	-	POLAROID	1100,1109,1205,1206,1207,1208,1209,1210,1211,1330

_		
	BRAND T\	//LCD CODE
_	POLOROID	1255,1258,1259,1278,1353
9	PRIMA :	1002,1032,1033,1114,1301 1002,1048,1260
_		1034
_	DDOCCAN .	1000 1001 1040 1001 1055
	PROTON	1301.1457.1435 1281,1282,1283,1284 1015,1301
-	PROVIEW	1281,1282,1283,1284
_	PULSAR	1015,1301
_	PULSAR PXCATV QUASAR	1100,1102 1014,1031,1305,1340,1346
-	RADIO SHACK	1014.1031.1305.1340.1346 1002.1008.1019.1021.1114.1301.1340.1346.1355
-		1119
_	1007 100	1109 8 1017 1018 1115 1120 1297 1301 1305 1309 1316
	RCA 1317.1010	8.1017.1018.1115.1120.1297.1301.1305.1309.1316 0.1033.1072.1090.1344.1355.1356.1357.1362.1363.1364
182		37,1438,1439,1440,1441,1442,1443,1444,1386 1017
102	RCONWA RCZTTO8 RCZY35(NAN 2) REALISTIC RINEX	1086 1296
_	RC27T08	1296 1152
_	REALISTIC	1019.1021.1114.1301.1340.1346
_	RINEX RECCOR RHAFSODY ROOMCONX ROOMCONX ROOMCONX ROWA SOWA SOWA SOWA SOWA SOWA SOWA SOWA S	
Ξ.	RECCOR	1144
4	ROOMCONX	1354
-	ROYAL	1034.1341
_	ROWA	1124
_	RUNCO	1015.1299.1301.1351
_	SAMSOUN	1114.1301 1073
=	SAMSUNG 1010.1088.104	1107 134 135 136 137 138 138 138 138 138 138 138 138
	SAMSUX	1114 1090.1122.1123.1137.1259.1278.1291 5.1077.1106.1112.1113.1180.1285.1286.1319.1019.1317
2	SANYO 1021.1060.107	5.1077.1106.1112.1113.1180.1285.1286.1319.1019.1317
_	SCEPTRE	1385
_	SCOTT	1301 1019 1026 1114 1298 1301
-	SEARS 1003.1008.1	012.1021.1032.1034.1114.1298.1301.1304.1317
_	SCEPTRE SCIMITSU SCOTT SEARS 1003.1008.1 SEMIYOX SEMP	1019
_	SENOR	1385 1301 1019,1026,1314,1298,1301 1012,1021,032,1034,1114,1298,1301,1304,1317 1019 1049,1121,1003 1373 1373
_	SENSEI	1373 5, 111, 1160, 1161, 1287, 1298, 1301, 1340, 1346, 1445,
_	SHARP 1004.1040.1072.109	95.1114.1160.1161.1287.1298.1301.1340.1346.1445.144 1072
	SHOGUN	1019.1298.1301.1304
-	SHIMASU	1298
	SIMILAR	1048
_	SIMPSON	1317
	SONIC	1317 1012.1032.1033.1034.1304 1144 1002.1311.1212.1395.1383.1381 1002.1311 1002.002 1002 1002 1002 1002 1002
_	SONY	1002.1311.1212.1395.1383.1381
	SONY PANTALLA	1002.1311
-	SONY RM-720	1002
_	SONY TRINITRON MENU	1002
	SONY WEGA MENU	1002
-	SOYO 1235.1236.1	1237.1238.1239.1240.1241.1242.1243.1244.1245.1246.1247 1019.1298.1301
	SPECTRICON	1028
_	SEMIVOX SEMP R SENSE 1004.1040.1072.108 SHARP 1004.1040.1072.108 SHENG CHIA SHOOL SHARP 1004.1040.1072.108 SHENG CHIA SHOOL SHARP 1004.1040.1072.108 SHOOL SHARP 1004.1040.1072.108 SHARP SHARP 1004.1040.1072.108 SHARP SHARP 1004.1040.1072.108 SHARP SHARP 1004.1040.1072.108 SHARP	1837,1238,1239,1240,1241,1242,1243,1244,1245,1246,1247 1019,1298,1301 1028 1012,1447 1019,1301
-	ŠŤĂRLITE	1019
	SUPERSONIC	1019.1285
_	SVA	1091.1269
-	SYLVANIA 1198.1199	0.1012.1013.1034.1114.1301.1306.1317.1448
_	SYNTAX	1200.1201.1202.1203
_	S/M(LCD)	1265.1335.1336.1453
	TAHOCI	1142
_	TANDY	1072
_	TAKATA	1181
-	TATUNG	1305
2	TCL TECHNOLACE	1090.1128.1386 1298
3_	TECHNOVALLEY	1019.1032.1259.1301.1304.1303
	TECHNICS TECHNOOD	1014.1015.1031
3	SQUAREVIEW STARILE SUPERSONIC SUPERME SYVANIA STAPLICE SYMPHONIA STAPLICA STAPLICA AND A A AND A AND A AND A AND A A AND A AND A A A A A A A A A A A A A A A A A A A	1012-1447 1017-1447 1018-1385 1019-1285 1019-1285 1019-1285 1019-1019-1019-1019-1019-1019-1019-1019
	TEKNIKA	1019.1032.1034.1114.1298.1299.1301.1304
3	TELEFUNKEN 1063.1	1079.1088.1099.1101.1127.1129.1133.1134 136.1138.1140.1150.1156.1289.1291.1301.1010
-	TERA	1378
_	TERA TELERENT THOMSON	1378 1299 1110



SAT DEVICE

Acces	sory	Stream	iing	, Pla	ayer	
BRAND	CODE	BRAND	CC	DDE	BRAND	CODE
Access HD	2117	Echostar		2129	RCA 214	2.2007.214
Airlink 101	2118	Epson		2130	Roku	2101.214
Alpha digital	2117	Evolution		2131	RTC	212
AMTC	2117	Firebird syst		2123	Samsung	2144.208
Apex digital	2082	GE	2123	2132	Sansonic	213
Apple	2119	Goodmind	2123	2132	Seagate	214
Artec	2120	Gridlink		2133	Scientific Atlan	nta 200
Asus	2121	Insignia		2132	Sony	214
Boxee	2151	iomega	2148	2156	Sunkey	214
CASTI	2122	Laconic		2133	Sylvania	213
Centronics	2123	LG	2150	2134	Tivax	211
		Logitech		2157	Ventura	214
Channel master	2124	Magnavox	2135	2130	Venturer	214
Cisco		Memorex		2136	Vizio	216
Coby	2125	Micca		2132	Western digita	
Coship	2126 2127	MicroGEM		2137	Windows media ce	
Daewoo Davtek		Microsoft		2138	Winegard	214
	2122		2139	.2158	xbox	213
Digital stream	2128	Netgear 215	9.2160		xbox one	2166,216
Digiwave	2123	Patriot	0.2100	2162	Xtreamer	216
Dish Network	2129	Philco		2130	Zenith	213
D-link 2152. 21		Popcorn Hour		2140	Zentech	211
2154. 21	55. 2151	QNAP		2163	Zinwell	214
		4,171		2100		214

IPTV

BRA	ND	CODE		BRAND	CODE
ADB		2106		MTS	2113
Amino		2108.2110		Sasktel	2113
AT@T		2112	_	Scientific Atlanta	2005.2112
Bell		2113		Scientific Atlanta	2114.2115
Cisco	2005.211	2.2004.2114.2115.21	16	SureWest	2108.2113
KoolConne	ct	2108	_	Telus	2115
Motorola	2	004.2112.2114.21	13	Verizon	2004

SATELLITE SET TOP BOX

BHAND	I CODE	BRAN	עו	CODE
Bell Expressvu	2100	Cisco	2005.2	112.2004.2114.2115.2116
Direc TV	2096.2097.2007.2083	Comcast		2004.2005.2114.2111
Dish Network	2100	Cox		2004.2005
Dishpro	2100	Digeo		2111
Echostar	2100	i3 Micro		2107.2109
Expressvu	2100	Insight		2004.2005
GE	2083	Knology		2005
General Instrument	2104	KoolConnect		2108
GOI	2100	Mediacom		2004.2005
HTS	2100	Motorola		2004.2112.2114.2113
Hughes Network Systems		Moxi		2111
Jerrold	2104	MTS		2113
JVC	2100	Myrio		2107.2109
Motorola	2104	Pace		2004.2005.2114
Next Level	2104	Panasonic		2114
Proscan	2007.2083	Pioneer		2005
Radio Shack	2104	RCN		2004
RCA	2007.2083.2105	Rogers		2005
Samsung	2096	Samsung		2005
Shaw Direct	2104	Sasktel		2113
Star Choice	2104	Scientific Atlanta		2005.2112.2114.2115
Voom	2104	Segin		2107
ADB	2106	Shaw		2004
Amino	2107.2108.2109.2110	Suddenlink		2004.2005
Arris	2111	SureWest		2108.2113
AT@T	2112	Telus		2115
Bell	2113	Thomson		2114
Bright House	2004.2005	Time Warner		2004.2005.2111
Cable One	2004.2005	Verizon		2004
Cablevision	2004.2005	Videotron		2005
Charter	2004.2005.2111	WideOpenWest		2005

AMPLIMATIC	2027(RP500)
ANTINA	2076(3573)
AUDINAK	2036
CABLEVISION :	2001.2002.2003.2004.2058(RT-100S)
CMEMOREX	2072
COMCAST	2099
CONV	2069(RC09).2074
CONVERSOR	2010
COSAT	2045.2029
CQ-B370R	2038
CROMUS	2032(CBR-2000)
DDA	2052.2049
DIRECTV all Mo	dels 2096.2097.2098
DISHNETWORK	2100
DRAGON	2045
DSTV	2062.2063
ELECOM	2023.2024.2025
FALCOM	2036
2016(S	RE300).2017(SRE350).2018(SRE400)
FRESAT 2016(S	RE300).2017(SRE350).2018(SRE400) 2019(SRE-3000).2020(3000PLUS)
2016(S FRESAT 2021)	RE300).2017(SRE350).2018(SRE400) 2019(SRE-3000).2020(3000PLUS) 300PLUS).2022(SRE500).2035
2016(S FRESAT 2021) GE(GRD33G2A/33G	RE300).2017(SRE350).2018(SRE400) 2019(SRE-3000).2020(3000PLUS) 300PLUS).2022(SRE500).2035 3A/122GW) 2083.2007
2016(S FRESAT 2021) GE(GRD33G2A/33G GENERAL INST	RE300).2017(SRE350).2018(SRE400) 2019(SRE-3000).2020(3000PLUS) 300PLUS).2022(SRE500).2035 3A/1226W) 2083.2007 RUMENT 2008
FRESAT 2016(S 2021) GE(GRD33G2A/33G GENERAL INST GMI	RE300),2017(SRE350),2018(SRE400) 2019(SRE-3000),2020(3000PLUS) 300PLUS),2022(SRE500),2035 304/122GW) 2083,2007 RUMENT 2008 2060(C0963)
FRESAT 2016(S FRESAT 2021) GE(GRD33G2A/33G GENERAL INST GMI GRADINER	RE300).2017(SRE350).2018(SRE400) 2019(SRE-3000).2020(3000PLUS) 3009PLUS).2022(SRE500).2035 304/122GW) 2083.2007 RUMENT 2008 2060(C0963) 2055
PRESAT 2016(S FRESAT 2021) GE(GRD33G2A/33G GENERAL INST GMI GRADINER GRADINER	RE300),2017(SRE359),2016(SRE400) 2019(SRE-3000),2020(3000PLUS) 300PLUS),2022(SRE500),2035 3A122GW) 2083,2007 RUMENT 2008 2060(C0963) 2055 2002(GSD600),2003
2016(S FRESAT 2021(GE(GRD33G2A/33G GENERAL INST GMI GRADINER GRADIENTE GRADIENTE	RE300),2017(SRE350),2016(SRE400) 2016(SRE-300),2020(S000PLUS) 300PLUS),2022(SRE500),2035 34/1220W) 2083,2007 2081(2089) 2060(C0963) 2060(C0963) 2022(GSD600),2003 2041(GR8300)
2016(S FRESAT 2021) GE(GRD33G2A/33G GENERAL INST GMI GRADINER GRADIENTE GRADCOM GRUNDIG	RE300).2017(SRE350).2018(SRE400) 2019(SRE-300).202(3000PLUS) 300PLUS).2022(SRE500).2035 \$M1220W) 2083.2007 RUMENT 2060(C0983) 2050(C0983) 2002(GSD600).2003 2041(GR3000)
PRESAT 2016(S 2021) GE(GRD33G2A/33G GENERAL INST GMI GRADINER GRADIENTE GRADCOM GRUNDIG HICON	RE300).2017(SRE359).2018(SRE400) 2019(SRE.3000).2020(3000-U01) 300PLUS).2022(SRE500).2035 3A11260W) 2083.2007 2083.2007 2080(C9983) 2090(C9983) 2092(GSD600).2003 2041(GR3000) 2041(GR3000) 2081 2081(2081)
FRESAT 2016(S 2021) GE(GRD33G2A/33G GENERAL INST GMI GRADIENTE GRADIENTE GRADCOM GRUNDIG HICON HITACHI(HDX98	RE300,2017(SRE390),2018(SRE400), 2019(SRE-3000),2020(3000FUUS), 300PLUS),2022(SRE500),2035 ANIZ36W) 2085,2007 RUMENT 2008 2080(C0963) 2095(C0963) 2002(GSD600),2003 2041(GR3000) 2081 2081 2081 2081 2081 2081 2081 2081
PRESAT 2016(S 2021) GE(GRD33G2A/33G GENERAL INST GMI GRADINER GRADIENTE GRADCOM GRUNDIG HICON HITACHI(HDX98 HNS(HIRD-E8,H	RE300,2017(SRE359),2018(SRE400) 2019(SRE-3000),2020(3000PLUS) 300PLUS),2022(SRE600),2035 3017(220W) 2083,2007 RUMENT 2008 2061(C0983) 205(SSDE00),2003 2041(GRE300) 2041(GRE300) 8) 2023(SSDE00),2003 2041(GRE300) 8) 2023(SSDE00),2003 8) 2045(SSDE00),2003 2041(GRE300) 8) 2023(SSDE00),2003 8) 2045(SSDE00),2003 8) 2045(SSDE000),2003 8) 2
PRESAT 2016(S FRESAT 2021) GE(GRD33GZA/33G GENERAL INST GMI GRADINER GRADIENTE GRADCOM GRUNDIG HICON HITACHI(HDX98 HNS(HIRD-E8,H'HUGHES Netwo)	RE300), 2017(\$RE350), 2016(\$RE400) 2016(\$RE300), 2020(3000PULS) 300PULS), 2022(\$RE500), 2036 3047(26W) 2083, 2007 RUMENT 2008 2056 2002(\$SD800), 2003 2041(\$R9300) 2041 2031 2032(\$800) B) 2032(\$800) B) 2082 TIHD) 2008, 2091
2016(S FRESAT 2021) GE(GRD33G2A)336 GENERAL INST GMI GRADINER GRADIENTE GRADCOM GRUNDIG HITACHI(HDX98 HNS(HIRD-E8,H' HUGHES Netwoi	RE300), 2017(\$RE300), 2017(\$RE300), 2017(\$RE400) 2019(\$RE300), 2021(\$000PULB), 2022(\$RE500), 2035 AVIZEOWN 2083, 2007 RUMENT 2008 2001(\$SE00), 2035 2041(\$RS00), 2035 2041(\$RS00), 2035 2041(\$RS00), 2035 2041(\$RS00), 2035 4041(\$RS00), 2035 4041(\$RS
PRESAT 2016(S GE(GRD33G2AJ33G GEMERAL INST GMI GRADINER GRADIENTE GRADOM GRUNDIG HICON HITACHI(HDX98 HUGHES Netwo) INFOCUS INSTRUMENT	RE300), 2017(8RE309), 201 (SRE400) 2019(SRE-300), 2020(2000PUL) 300PLUS), 2022(SRE500), 2035 AR1252W) 2085, 2007 RUMENT 2008 2008 2008 2008 2008 2008 2008 2008
2016(S FRESAT 2021) GE(GRD33G2A)336 GENERAL INST GMI GRADINER GRADIENTE GRADCOM GRUNDIG HITACHI(HDX98 HNS(HIRD-E8,H' HUGHES Netwoi	RE300),2017(8RE300),2017(8RE400) 2019(8RE-300),2012(9RE400) 2009(14),2022(9RE500),2033 RUMENT 2085,2007 2081(9RE300),2003 2091(9RE300),2003 2091(9RE900),2003 2093(9RE900),2003 2093(9RE900),200
FRESAT 2016(S GE(GRD33G2A33G GENERAL INSTEMBLE GRADINER GRADIENTE GRADOLIENTE GRADOLIENTE	RE300),2017(8RE309),2017(8RE309),2017(8RE309),2012(000PUL9),2012(9RE500),2021(000PUL9),2025(2RE500),2025(2RE5
PRESAT 2016(S GE(GRD33G2AJ33G GEMERAL INST GMI GRADINER GRADIENTE GRADOM GRUNDIG HICON HITACHI(HDX98 HUGHES Netwo) INFOCUS INSTRUMENT	RE300),2017(8RE300),2017(8RE400) 2019(8RE-300),2012(9RE400) 2009(14),2022(9RE500),2033 RUMENT 2085,2007 2081(9RE300),2003 2091(9RE300),2003 2091(9RE900),2003 2093(9RE900),2003 2093(9RE900),200

JERROLD LG MEGACABLE MITSUBISHI MOTORALS MULTICHOICE NEGRO

RLU	E-RAY	טעט
AND		CODE

2065(3153=3162)	BRAND	CODE
06.2082(SRHD5)	LG	3057
2004.2073.2013	PANASONIC	3021
2062.2063	PHILIPS	3387
2013	SAMSUNG	3384
2051	SONY	3386
/1080,HD-SAT520)	TOSHIBA	3385
	VIZIO	3388.3389.3390(AUDIO)