

Popcorn Machine Instructions

Setup

1. Please wipe up the oil that may spill while you are popping the popcorn.
2. Use only utensils provided with the machine
3. Clean machine after every use. It should be as clean as - or cleaner than - it was when you started.
4. Please be cautious! Do not burn yourself!

To pop popcorn

1. Turn on **Kettle Heat Switch**. For the first batch, allow the kettle to preheat for 5-7 minutes. No preheating is required after the first batch is done.
2. After preheating, add popping oil to the kettle. Use the oil measuring cup (cup with red print) and fill to the line indicated for the G8 model (2.6 oz of oil).
3. Measure out popcorn in popcorn measuring cup (cup with yellow print) and fill to the line indicated for the G8 model (8 oz of popcorn). Add one teaspoon (plastic spoon) of seasoning salt on top of popcorn in the measuring cup. Add popcorn and seasoning salt to kettle.
4. When popping stops, immediately empty the kettle by turning the handle to dump it.
5. Repeat steps 2, 3, and 4 to make more popcorn or turn the **Corn Agitator Switch** and **Kettle Heat Switch OFF**

IMPORTANT!! TURN THE KETTLE HEAT SWITCH OFF WHEN NOT POPPING! NEVER POP POPCORN WITHOUT OIL!

Cleanup

1. *Spray the cart and the outside of the machine* with the Dawn soap/water spray, and scrub clean. Spray with water and wipe with a damp washcloth, then dry with a dry cloth.
2. *Remove the kettle and spray the inside of the cart* with the Dawn soap/water spray, and scrub clean. Spray with water and wipe with a damp washcloth, then dry with a dry cloth.
3. *Spray the Kettle* with the Dawn soap/water spray, and scrub clean. Spray with water and wipe with a damp washcloth, then dry with a dry cloth.
4. *Empty the catch tray* and spray with the Dawn soap/water spray, and scrub clean. Spray with water and wipe with a damp washcloth, then dry with a dry cloth.
5. Reassemble the popcorn machine and return it to the RSC Information Desk.

DO NOT USE ANY MATERIALS OTHER THAN PROVIDED WITH THIS MACHINE!

Updated 9/10/04