



BROOKS
EQUIPMENT

EXIT & EMERGENCY LIGHT COMBO SIGN

Illumination

- Ultra-bright, energy efficient white LED emergency lighting
- 4.5 W (36 LEDs x 0.125 watts) per light pipe
- High-performance smooth-chrome-plated metallized reflector and polycarbonate "light pipe" lens for optimal light distribution and resistance to discoloration
- Adjustable light pipe allows for optimal use of light output
- Long-lasting, energy efficient red LED exit sign



Electrical

- Dual 120/277 VAC
- Charge rate/power "ON" LED indicator light and push-to-test switch for mandated code compliance testing
- Remote capable standard
- 4.8V long-life, maintenance-free, rechargeable Ni-Cad battery
- Internal solid-state transfer switch automatically connects the internal battery to LED board/light pipe for minimum 90-minute emergency illumination
- Fully automatic solid-state, two-rate charger initiates battery charging to recharge a discharged battery in 24 hours

Mounting

- EZ-snap thermoplastic mounting canopy (included)—provides top, end, or back mount

Housing

- Injection-molded, engineering-grade, 5VA flame retardant, high-impact thermoplastic in white finish
- EZ-snap out Chevron directional indicators

Warranty/Listing

- Five year warranty on all electronics and housing (battery pro-rated for five years)
- UL listed for damp locations (0°-50°C/32°-122°F standard)
- Meets UL924, NFPA 101 Life Safety Code, NEC, OSHA, local and state codes

Dimensions

