
ACCESSORIES

SOUND SYSTEM 420 E WITH SPEAKERS





- 1 Sound system
- **2** Exciter speakers

Individual Speaker, optional

walls and ceilings

composite boards > Screw or glue mounted

3 3-way distributor with switching function





> For installation in furniture, tables, counters, mirrors,

> Can be installed on glass and mirrored glass (3-6 mm (1/8" - 1/4"), acrylic glass (3 mm (1/8"), chipboard (10-20 mm (3/8" - 3/4") and mineral

> Output: rated/music capacity 4/15 W Ø x H: 65 x 22 mm (2 9/16" x 7/8")

> Item No. 822.65.039 SRP \$50.00

Supplied with 2 m (78 3/4") lead


Item No.	822.65.034
SRP	\$230.00
LxWxH	140 x 45 x 15 (5 1/2" x 1 3/4" x 9/16")
Wattage	Amplifier power 20 W
Power consumption	Operation with 2 speakers: max. 19 W, Operation with 4 speakers: max 32 W
Material/Finish	Plastic, black
Supplied with	2 m (78 3/4") lead, 4 connections and 2 exciter speakers



Note

Multi-room control for separating different users in adjacent rooms is available upon request.











Sound systems






> App for individual settings available on request







(2) Exciter speakers

0

Dimensional data not binding. Dimensions in mm, inches are approximate. We reserve the right to alter specifications without notice

Please order extension lead 2000 mm (78 3/4") 833.73.766 for exciter speaker separately.

> Material/Color: Plastic, black

L x W x H: 140 x 45 x 15 mm (5 1/2" x 1 3/4" x 9/16")
Power Operation with 2 exciter speakers: Max. 19 W, operation with 4 exciter speakers: Max. 32 W,

standby: <0.3 W

> Music wattage: Operation with 2 or 4 exciter speakers:

2 x 10 W (RMS)

> Reception range: Max. 10 m (32' 9 11/16")

> Mounting: For screw fixing

> Supplied with: 1 Bluetooth® receiver with 2000 mm (78 3/4")

lead and 4 connections for exciter speakers,

incl. 2 exciter speakers

Item No. 822.65.034



Please observe the installation regulations for bathrooms. Can be installed on glass and mirror glass 3–6 mm (1/8"–1/4"), acrylic glass 3 mm (1/8"), chipboard 10–20 mm (3/8"–3/4") and mineral composite boards.





Loox5 12 V driver see page 124 Please order 6-piece adapter set 833.95.753 separately, see page 116.



Exciter speaker

Dimensions:
Wattage:
Mounting:
Supplied with:
Ø 65 x 22 mm (2 9/16" x 7/8")
Rated/music load capacity 4/15 W
For screw fixing or for glue fixing
1 exciter speaker with 1 m (39 3/8")
speaker lead

Item	No.





822.65.039