

# SECURA KEY RK65KS-KIT1

## Single Door, Standalone Proximity Access Control System Kit

The Radio Key® RK65K is fully programmable, standalone single door access control system. It's a compact, weather-resistant, surface mounted unit. The reader can manage up to 65,000 individual users with sequentially-numbered cards or tags. Users are added and deleted easily with an RK-HHP handheld programmer. The latch timer can be set from  $\frac{1}{4}$  second up to 18 hours, or to toggle (on/off). This simple but powerful reader is now available in a kit, which contains everything you need to control a single door, to program and to power the reader and enough keytags for 10 users.

A Wiegand output allows the reader to be connected to a multi-door access control or telephone entry system, if desired. When used as part of a larger system, the local card memory and relay may be used for degraded mode or other special functions.

- **Low Priced Single Door Proximity Entry System**
- **Epoxy potted for Outdoor Locations**
- **125 kHz Proximity Technology**
- **Dynascan® Auto Tuning for Superior Read Range**
- **Up to 6" Read Distance**
- **No Control Panel Required**
- **Program with Handheld Programmer**
- **Wiegand Output for Future Expansion**

Just Add a Door Locking Device  
or Gate Operator with Separate  
Power Supply and Cable for a  
Complete Single Door Access  
Control System.

### RK65KS-KIT1 STANDALONE KIT INCLUDES:

**1 RK65KS READER**  
**10 RKKT Keytags**  
**1 RK-HHP HANDHELD PROGRAMMER**  
**1 RK600PS 12 VDC POWER SUPPLY**

**RADIO KEY®**

**Secura Key**  
Smart. Reliable. Secure.

**RK65KS-KIT1**  
Single Door Standalone Proximity Access Control Kit



**KIT INCLUDES:**

- 1 - RK65KS Reader
- 1 - RK-HHP Handheld Programmer
- 1 - RKPS Power Supply
- 10 - RKKT-02 Proximity Keytags

**• Expandable: Wiegand Output for Future Upgrade**  
• Low Priced Single Door Proximity Entry System  
• Weather Resistant Reader for Outdoor Locations  
• 125 kHz Proximity Technology  
• Dynascan® Auto Tuning for Superior Read Range  
• Up to 8" Read Distance  
• No Control Panel Required  
• Program with Handheld Programmer

20301 Nordhoff Street, Chatsworth, CA 91311  
PHONE (818) 882-0020 • FAX (818) 882-7052  
TOLL-FREE (800) 891-0020

Website: [www.securakey.com](http://www.securakey.com) • E-mail: [mail@securakey.com](mailto:mail@securakey.com)

7715

**Secura Key**  
A Division of SOUNDCRAFT Inc.  
Smart. Reliable. Secure.