TECHNICAL DATA

Fluke PM9091/001 50 Ohm Coaxial BNC cable set (3 x 1.5m)



Key features

- Cable length is 1.5 m
- Maximum Signal Voltage: 300 V rms
- Maximum Voltage to Ground: 600 V rms. CAT III per IEC 61010-031
- BB120 Shielded Banana to BNC Adapter is required to adapt to ScopeMeter 120 Series shielded banana jack inputs

Product overview: Fluke PM9091/001 50 Ohm Coaxial BNC cable set (3 x 1.5m)

Each set consists of three black cables with colored BNC male connectors (red, gray and black) for easy identification.

Ordering information



Fluke PM9091

50 Ohm Coaxial BNC cable set (3 x 1.5m)

Part-GB#: 935598
EAN-GB: 0095969022064

Fluke. *Keeping your world up and running.®*

Fluke Europe B.V.
P.O. Box 1186
5602 BD Eindhoven
The Netherlands
www.fluke.com/en
©2026 Fluke Corporation. All rights reserved.
Data subject to alteration without notice.
11/2026

For more information call:
In Middle East/Africa
+31 (0)40 267 5100

Modification of this document is not permitted without written permission from Fluke Corporation.