


Functional Devices, Inc. 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com **Toll Free:** (800) 888-5538 Office: (765) 883-5538 | Fax: (765) 883-7505

# **20 AMP POWER CONTROL RELAY**

## RIBT243P

Power Relay, 20 Amp 3PST-N/O, 24 Vac/dc Coil, Hi/Lo Voltage Separation, NEMA 1 Housing













## **SPECIFICATIONS**

# Relays & Contact Type: One (1) 3PST Continuous Duty Coil Expected Relay Life: 10 million cycles minimum mechanical

Operating Temperature: -30 to 140° F

Humidity Range: 5 to 95% (noncondensing)

Operate Time: 20ms

Relay Status: LED On = Activated

**Dimensions:** 4.000"H x 4.000"W x 1.800"D with .50" NPT Nipple

**Housing Detail:** See **Housing C** in housing guide for dimensions

Origin Made of US and non-US parts

Wires: 16", 600V Rated

Approvals: UL Listed, UL916, C-UL, CE, RoHS Housing Rating: UL Accepted for Use in Plenum, NEMA 1

Gold Flash: No Override Switch: No

## **Contact Ratings:**

20 Amp Resistive @ 300 Vac, 28 Vdc 20 Amp Ballast @ 277-480 Vac Not rated for Electronic Ballast 15 Amp Resistive @ 600 Vac 770 VA Pilot Duty @ 120 Vac, 1 Phase 1,158 VA Pilot Duty @ 240 Vac, 1 Phase 1,110 VA Pilot Duty @ 277 Vac, 1 Phase 1,640 VA Pilot Duty @ 480 Vac, 1 Phase 1,466 VA Pilot Duty @ 240 Vac, 3 Phase 2,112 VA Pilot Duty @ 480 Vac, 3 Phase Heavy Pilot Duty @ 600 Vac 7.5 HP @ 480 Vac, 3 Phase 5 HP @ 240 Vac, 3 Phase 3 HP @ 480-600 Vac, 1 Phase 2 HP @ 240-277 Vac, 1 Phase

1 HP @ 120 Vac, 1 Phase

## **Coil Current:**

210 mA @ 24 Vac 154 mA @ 30 Vdc

#### **Coil Voltage Input:**

24 Vac/dc; 50-60 Hz Drop Out = 3 Vac / 3.8 Vdc Pull In =  $20 \, \text{Vac} / 22 \, \text{Vdc}$ 

• Order Normally Closed by adding "-NC" to end of model number