

Lyric™ C2 Wi-Fi Security Camera

SUBMITTAL SHEET

Job Name	
Engineer	
Mechanical Contractor	
Contractor's P.O. No.	
Representative	
Notes	

Model(s)				
	Qty.		Notes	
	Qty.		Notes	
	Qty.		Notes	
Approval				
Service				
Tag No.				



APPLICATION

The Lyric C2 Wi-Fi Security Camera allows the user to keep an on their home or business while they are away. It connects via Wi-Fi and is accessed using the Honeywell Lyric app.

SPECIFICATIONS

Model: Lyric C2 Wi-Fi Camera

SOC: RTL8197FS @1GHz

RF: RTL8197FS2.4GHz & RTL8822BE 5GHz

Backend: SONIX98672

Flash:

RTL8197FS -32MB

SONIX98672 -16MB

Bluetooth: RTL8822BEBLE4.1

Wi-Fi: IEEE802.11 a/b/g/n/ac

Bluetooth: BLE 4.1

RAM:

RTL8197FS -128MB (Embedded)

SONIX98672 -32MB (Embedded)

Image Sensor: AR0237, 1/2.7" 3 Megapixel CMOS Sensor

Lens: F1.8; DFOV 145.0°, HFOV: 140.0°

Max Resolution: 1920 x 1080P; H.264@ 30fps; MJPEG@ 30fps

Two Way Audio: Build-in microphone and speaker

Microphone sensitivity: -25 dB

IR-Cut: Supported

Night Vision: IR10M

Power: 5V/2A Power Adaptor

Certification: FCC Class B, CE Mark, RoHS

Temperature, Humidity: 0~40°C (104°F), 10~90% (Non-Condensing)

FEATURES

- Industry leading security through AES 256-bit end-to-end data encryption
- 1080p full HD resolution with H.264 video compression
- Night vision/low-light control for visibility for 24hr monitoring
- 145° Field of view
- Free 24hr cloud storage
- Up to four multi-area selectable motion detection zones with different levels of sensitivity
- Audio analytics to recognize baby cry/CO-smoke alarms
- Control the camera through the free Honeywell Lyric app
- Free encrypted 8GB MicroSD card provided. Upgradeable to 64GB
- Email & in-app push notifications
- Two-way audio push to talk
- Digital zoom: 6x
- App support for iOS & Android devices
- Automatic home/away privacy mode through Lyric's geofencing technology

STATUS LED

LED	Detector State
During Installation	
Blinking Blue	Powered up. Ready to begin setup.
Solid Blue	Connected to App. Ready to complete setup.
Solid Purple	QR Code scan complete. Re-start Connect to Wi-Fi process.
Blinking Green	Connected to Wi-Fi network.
Solid Green	Connected to Wi-Fi network.
Solid Red	Setup timed out. Unplug camera, plug it back in, and restart the process.
During Operation	
Blinking Green	Connecting to Wi-Fi network.
Solid Green	Connected to Wi-Fi and operating.
Blinking Red	Not connected to Wi-Fi.

Home and Building Technologies

In the U.S.:


Honeywell

1985 Douglas Drive North

Golden Valley, MN 55422-3992

customer.honeywell.com

* U.S. Registered Trademark
© 2017 Honeywell International Inc.
33-00286-01 M.S. 06-17
Printed in United States



33-00286-01