

Product data sheet

Specifications



plastic nut and self tapping screw
placed in the notches of PLM for
DIN rail

NSYTCSPLM

Main

category	Mounting accessory
Product or component type	Nut
Range compatibility	Thalassa Thalassa PLM
Application	Multi-purpose
Nominal dimensions of the housing	-
Mounting location	Rear of enclosure
Device composition	1 plastic nut 1 self- tapping screw
Quantity per set	Set of 20

Complementary

Fixing mode	Direct fixing - screw type self-tapping screw - notches of enclosure location
ISO thread	M6

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	3.500 cm
Package 1 Width	14.000 cm
Package 1 Length	15.000 cm
Package 1 Weight	5.000 g
Unit Type of Package 2	BB1
Number of Units in Package 2	20
Package 2 Height	3.000 cm
Package 2 Width	15.000 cm
Package 2 Length	11.000 cm
Package 2 Weight	114.000 g

Contractual warranty

Warranty	18 months
----------	-----------

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

How this information helps you >

Environmental footprint

Environmental Disclosure

[Product Environmental Profile](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard

No

Packaging without single use plastic

No

[EU RoHS Directive](#)

Pro-active compliance
(Product out of EU RoHS legal scope)

SCIP Number

E893f0a0-d2cc-4011-9425-3873dde70142

REACH Regulation

[REACH Declaration](#)

China RoHS Regulation

[China RoHS declaration](#)

Use Again

Repack and remanufacture

Circularity Profile

No need of specific recycling operations

Take-back

No

Image of product / Alternate images

Alternative



Image of product in real life situation

