

# FAP32100

## FA/LA MOLDED CASE CIRCUIT BREAKER

### 240V, 100A, 3P

Product availability : Non-Stock - Not normally stocked in distribution facility



#### Main

Product or component type	Circuit breaker
Range of product	I-Line
Trip Unit Type	Thermal-magnetic
Rating Code	A

#### Complementary

Line Rated Current	100 A
Number of Poles	3P
Interrupt Rating	10 kA at 240 V AC 5 kA at 250 V DC
System Voltage	240 V AC 250 V DC
Mounting mode	Unit mount
Electrical connection	Terminal line Lugs load
Wire Gauge	AWG 14...AWG 1/0 (copper) 1 cable(s) AWG 12...AWG 1/0 (aluminium) 1 cable(s)
Terminal Type	AL100FA
Magnetic hold current	900 A
Magnetic tripping current	1700 A
Phase connection	ABC
Height	6.4 in
Width	4.5 in
Depth	4.13 in

#### Environment

Product certifications	CSA
------------------------	-----

UL listed

## Ordering and shipping details

Category	00901 - FAL 240V BREAKERS & SWITCH
Discount Schedule	DE2
GTIN	00785901313779
Nbr. of units in pkg.	1
Package weight(Lbs)	4.7300000000000004
Returnability	N
Country of origin	MX

## Offer Sustainability

Sustainable offer status	Green Premium product
RoHS (date code: YYWW)	Compliant - since 1304 - Schneider Electric declaration of conformity <a href="#">Schneider Electric declaration of conformity</a>
REACH	Reference not containing SVHC above the threshold <a href="#">Reference not containing SVHC above the threshold</a>
Product environmental profile	Available
Product end of life instructions	Need no specific recycling operations
California proposition 65	WARNING: This product can expose you to chemicals including:
----- Substance 1	DINP, which is known to the State of California to cause cancer, and
----- Substance 2	DIDP, which is known to the State of California to cause Birth Defects or other reproductive harm.
----- More information	For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>

## Contractual warranty

Warranty period	18 months
-----------------	-----------

## FAP32100 is replaced by:



### Unit Mount BDP36100

PowerPact - circuit breaker - 100A 3P AC 18kA at 600Y/347V (UL) - Everlink Lug

Qty 1

Reason for Substitution: End of life | Substitution date: 30 June 2019 | (Ref #) is replaced by (New Ref #)