


Data sheet | Item number: 706-3340/300-100

System cable; for Schneider Modicon M340; 16 digital inputs or outputs for higher voltages; Length: 1 m; Conductor cross-section: 0.34 mm²

www.wago.com/706-3340_300-100



Item description

Note:

If less than 3 channels used at the same time, the maximum current per wire 2 A and up to 5 A (amb. T 30 °C) or 3.5 A (amb. T 50 °C) on the power supply pins N/L. If more than 3 channels used at the same time, the maximum current per wire 0.75 A and up to 5 A (amb. T 30 °C) or 3.5 A (amb. T 50 °C) on the power supply pins N/L.

Data

Electrical data

Inputs/outputs	16 digital inputs or outputs; for higher voltages
Operating voltage	≤ AC/DC 250 V
Current per wire (max.)	0.75 A

Connection data

Compatible PLC Modules	Schneider Modicon M340
Compatible PLC I/O Card Types	BMX DAI 1602 BMX DAI 1603 BMX DAI 1604

Subject to changes. Please also observe the further product documentation!

WAGO Corporation
Germantown, WI 53022
Phone: 1-800-DIN-RAIL (346-7245) | Fax: (262) 255-6222
Email: info.us@wago.com | Web: www.wago.us

Do you have any questions about our products?
We are always happy to take your call at (262) 255-6222 or 1 800-DIN-RAIL.



	BMX DDI 1603 BMX DRA 0805
Connection type (1)	System
Pole number 1	10
Pluggable connectors	WAGO 231 Series
Connection type 2	System
Pole number 2	10
Connector 2	WAGO 231 Series
Connection type (3)	System
Pole number 3	20
Connector 3	Schneider BMXFTB2020
Cable type	LiYY
Wire cross-section	0.34 mm ²
Color code	per DIN VDE 47100

Physical data

Cable length	1 m
--------------	-----

Material data

Weight	330 g
--------	-------

Environmental requirements

Surrounding air temperature (operation)	-20 ... 50 °C
---	---------------

Commercial data

Packaging type	bag
Country of origin	FR
GTIN	4055143980456
Customs tariff number	8544429090

Downloads

Documentation

System Description

WAGO System Wiring, Selection Guide

This guide will help you select the appropriate interface modules and system cables for the controller you are using.

pdf
545.9 kB

[Download](#)

Subject to changes. Please also observe the further product documentation!

WAGO Corporation
Germantown, WI 53022
Phone: 1-800-DIN-RAIL (346-7245) | Fax: (262) 255-6222
Email: info.us@wago.com | Web: www.wago.us

Do you have any questions about our products?
We are always happy to take your call at (262) 255-6222 or 1 800-DIN-RAIL.

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 706-3340/300-100

URL

Download

System cable; for Schneider Modicon M340; 16 digital inputs or outputs for higher voltages; Length: 1 m; Conductor cross-section: 0.34 mm²

Installation Notes



Subject to changes. Please also observe the further product documentation!

WAGO Corporation
Germantown, WI 53022
Phone: 1-800-DIN-RAIL (346-7245) | Fax: (262) 255-6222
Email: info.us@wago.com | Web: www.wago.us

Do you have any questions about our products?
We are always happy to take your call at (262) 255-6222 or 1 800-DIN-RAIL.