Data sheet | Item number: 706-4756/410-300

System cable; for Rockwell Control Logix; 6 analog inputs for RTD; Length: 3

m; Conductor cross-section: 0.25 mm²

www.wago.com/706-4756_410-300





Item description

Note:

When using more than 10 wires, the maximum current per wire must be reduced to 1 A.

Data Electrical data

Inputs/outputs	6 analog inputs; for RTD
Operating voltage	≤ AC/DC 35 V
Current per wire (max.)	2 A

Connection data

Compatible PLC Modules	Rockwell Control Logix
Compatible PLC I/O Card Types	1756 - IR6I
Connection type (1)	System
Pole number 1	25
Pluggable connectors	D-sub female connector
Connection type 2	System
Pole number 2	25
Connector 2	Sub-Min-D; female connector
Connection type (3)	System
Pole number 3	20

 $\label{thm:continuity} \textbf{Subject to changes. Please also observe the further product documentation!}$

WAGO Corporation Germantown, WI 53022

Phone: 1-800-DIN-RAIL (346-7245) | Fax: (262) 255-6222

Email: info.us@wago.com | Web: www.wago.us

Do you have any questions about our products? We are always happy to take your call at (262) 255-6222 or 1 800-DIN-RAIL.

Data sheet | Item number: 706-4756/410-300

www.wago.com/706-4756_410-300



Connector 3	Allen Bradley 1756-TBSH
Cable type	LiYCY
Wire cross-section	0.25 mm²
Color code	per DIN VDE 47100

Physical data

Cable length 3 m

Material data

Weight 1413 g

Environmental requirements

Surrounding air temperature (operation) -20 ... 50 °C

Commercial data

Packaging type	bag
Country of origin	FR
GTIN	4055143984102
Customs tariff number	8544429090

Downloads

Documentation

System Description

WAGO System Wiring, Selection Guide pdf Download
This guide will help you select the appropriate interface modules and system cables 545.9 kB for the controller you are using.

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 706-4756/410-300 URL

System cable; for Rockwell Control Logix; 6 analog inputs for RTD; Length: 3 m;

Conductor cross-section: 0.25 mm²

Subject to changes. Please also observe the further product documentation!

WAGO Corporation Germantown, WI 53022

Phone: 1-800-DIN-RAIL (346-7245) | Fax: (262) 255-6222

Email: info.us@wago.com | Web: www.wago.us

Do you have any questions about our products? We are always happy to take your call at (262) 255-6222 or 1 800-DIN-

RAIL.

Download

MAGO

Installation Notes



 $\label{thm:continuity} \textbf{Subject to changes. Please also observe the further product documentation!}$

WAGO Corporation Germantown, WI 53022

Phone: 1-800-DIN-RAIL (346-7245) | Fax: (262) 255-6222

Email: info.us@wago.com | Web: www.wago.us

Do you have any questions about our products? We are always happy to take your call at (262) 255-6222 or 1 800-DIN-RAIL.