



RoHS ✓
Compliant

BOMcheck.net

Item description

The WAGO USB Communication Cable connects a PC (notebook) to either the service interface of the 857 Series Signal Conditioners and Relay Modules (JUMPFLEX), or to WAGO-I/O-SYSTEM buscouplers/controllers.

Notice: Using the WAGO 759-923 USB Communication Cable in combination with select programmable fieldbus controllers requires the specific firmware versions

Data

Technical Data

Connection type	4-pole male connector - USB A-type plug
No. of poles	4
Cable length	5 m
Supported operating systems	Windows XP (SP3 or later) Windows 7 Windows 10

Geometrical Data

Width	15 mm / 0.591 inch
Height	50 mm / 1.97 inch
Depth	19 mm / 0.748 inch

Mechanical data

Weight	114.3 g
--------	---------



Environmental Requirements

Surrounding air (operating) temperature	-25 ... 70 °C
Protection class	IP20
EMC immunity to interference	acc. to EN 61000-4-3, EN 61000-4-6
EMC emission of interference	acc. to EN 55022
Fire load	0 MJ

Commercial data

Product Group	15 (Remote I/O)
Country of origin	DE
GTIN	4045454765200
Customs Tariff No.	85444290900

Downloads

Documentation

Bid Text

750-923/000-001	Apr 4, 2012	doc	Download
IO, Zubehoer		26.1 kB	

Tutorial

Set IP address with Ethernet Settings	3.0	mp4	Download
In this video we are demonstrating how you can set a IP address with Ethernet Settings. Content: 00:27 – Chapter #1 Download and install software; 00:56 – Chapter #2 Open Ethernet Settings; 01:10 – Chapter #3 Establish serial Connection; 01:34 – Chapter #4 Set IP address; 02:10 – Chapter #5 Check IP address	Dec 18, 2017	88.3 MB	

System Description

750/753 Series I/O-System – General Product Information	pdf	Download
	1.7 MB	

Device Files

Device Driver

WAGO USB Service Cable Driver / 750 and 857 Series	6.5.3.0	zip	Download
759-923	Sep 10, 2014	4.8 MB	



Subject to changes.
