iX Panel T7B


High-Performance HMI with 7" Display and Automation Software

The high-performance iX Panel T7B features a bright 7" widescreen TFT display with touch screen, powerful processor and iX software with universal connectivity.



Product Highlights

- ▶ 800 x 480 pixel, 7" diagonal, LED lighted, TFT color LCD display with touch screen
- ► One 10/100Base-T and one 10/100/1000Base-T Ethernet ports
- ► Four serial ports (RS-232, -422/485), optional CANbus interface
- ▶ Powder-coated aluminum housing
- ▶ iX Software with protocols for most industrial automation controllers





Dimensions shown in mm.

| iX Panel T7B Specifications | | | |
|-----------------------------|----------------------------------|--|--|
| Feature | Detail | Description | |
| Display | Туре | 800 x 480, TFT Color LCD | |
| | Size | 7" | |
| | Lighting | White LED | |
| | Brightness | 500 cd/m2 | |
| Touch Screen | Туре | Analog-resistive | |
| Interface | Ethernet | 10/100Base-T, 10/100/1000Base-T | |
| | Serial | 2 x RS232, 2 x RS422/485 | |
| | USB | Three USB 2.0 | |
| | Communication Modules (Optional) | Two isolated CANbus ports (CiX-CAN), MPI (pending) | |
| Processor | Туре | Intel® Atom (1.1 GHz) | |
| Memory | Main | 1 GB DDR2 MB | |
| | Application | 1.4 GB | |
| | External Storage Media | One SD card | |
| Realtime Clock | Standard | Battery-backed | |
| Power | Input Voltage | +24 VDC (18-32 VDC) | |
| | Consumption | 14 Watts | |
| Mechanical | Туре | Panel-mount and VESA 75 x 75 | |
| | Size WxHxD | 204 x 143 x 51 mm | |
| | Cut-out Dimensions WxHxD | 187 x 126 x 43 mm | |
| | Mass | 1.0 kg | |
| | Housing Material | Powder-coated aluminum | |

| Environmental | Protection (front/rear) | IP65 / IP20 |
|----------------|-------------------------|--|
| | Temperature | Operating: -10 to 50 °C; Storage: -20 to 70 °C |
| Certifications | UL | UL 508 (pending), DNV (pending) |
| | CE | EN61000-6-4, EN61000-6-2 |

| Software | Development Environments | iX Developer |
|----------|--------------------------|--------------|
| | Runtime Environments | iX Software |



US Office

Beijer Electronics, Inc. 1865 West 2100 South Salt Lake City, Utah 84119-1303 USA www.BeijerInc.com / 1-801-466-8770 Beijer Electronics Products AB P.O. Box 426 201 24 Malmö, Sweden www.BeijerElectronics.com / +46 40 35 86 00 $\begin{array}{c} \text{M01-076-00 REV 02} \\ \text{16 DECEMBER 2013} \\ \text{Copyright } \circledcirc \text{2013 Beijer Electronics. All rights reserved.} \end{array}$

The information at hand is provided as available at the time of printing. Beijer Electronics reserves the right to change any information without updating this publication. Beijer Electronics does not assume any responsibility for any errors or omissions in this publication.