

MODEL: 350004 - L-NET HUB ADAPTER



350004

FEATURES

- Provides connections to tap an L-Net run for redirection into hallway intersections or corner areas
- Plug-in RJ45 connectors for easy installation and service
- Rugged metal case for location in plenum or back-box

SPECIFICATIONS

Power Required: 24-36V from L-Net input connection

Weight: 0.5 lbs (0.23 kg)

Size: W: 2.75" (7.0 cm)

L: 4.0" (10.2 cm)

D: 0.75" (1.9 cm)

Housing and Finish: Steel case with black paint

Terminations: Three (3) RJ45 connectors

DESCRIPTION

The L-Net Hub Adapter is a metal case module that allows for an L-Net run on the Responder 5 to be tapped and redirected to areas such as hallway intersections, corner areas, or across sides of a hallway distribution. The L-Net Hub Adapter is powered from the L-Net power conductors in the CAT5/6 connection cable. It represents the power load equivalent to a corridor light and a network load of approximately 250' deducted from the L-Net cable distribution on a single Branch Regional Control L-Net port.

All power grounds are common on connectors.

*Architect and Engineer (A&E) Specifications available online at: customerconnection.rauland.com
Specifications subject to change without notice*

©Copyright 2008 Rauland-Borg Corporation Printed in USA Rev 08/2008