



VL408-2 Sounder

The VL408-2 is a wall mount unit featuring pulse tone lengths at a fixed high-pitch frequency. This sounder may be used in any location where louder audible alarm annunciation is desired. The VL408-2 Sounder connects to a powered relay on the Micro- Vision 200Z, 200Plus, 400Z or 500Z wireless console receiver.

Specifications

Dimensions:	Height: 3" Width: 3" Depth: 1.25"
Voltage:	9 to 18 VDC
Wire:	May be installed up to 300 feet from console using 2 pair, 18 AWG wire.

Architect and Engineers Specifications

The Console/Receiver shall have an optional sounder available for areas requesting louder alarm annunciation. The optional sounder shall provide a tone with three distinct pulse lengths: Fast (0.02 sec), Medium (0.25 sec), and slow (1 sec). It shall connect to the system on a powered relay at the rear of the console/receiver.

System Components

<u>Model No.</u>	<u>Description</u>
MV200	MicroVision 200Z Console
MV200plus	MicroVision 200Plus Console
MV400	MicroVision 400Z Console
MV500	MicroVision 500Z Console